Direct *in vivo* measurement of cochlear place coding in humans

Authors: Amit Walia, MD[1*], Amanda J. Ortmann, PhD[1], Shannon Lefler, AuD[1], Timothy A. Holden, BSE[1], Jacques A. Herzog, MD[1], Craig A. Buchman, MD[1]

[1]Department of Otolaryngology—Head and Neck Surgery, Washington University School of Medicine in St. Louis, St. Louis, Missouri, USA.

*Corresponding Author: Amit Walia, Washington University School of Medicine, Department of Otolaryngology Head & Neck Surgery, 660 S. Euclid Ave. Campus Box 8115, St. Louis, MO 63110; Phone: (314)-448-5847; Fax: (314)-453-0489; Email: amitwalia@wustl.edu

KEYWORDS: tonotopic organization, cochlea, acoustics, hearing, cochlear microphonics, intracochlear electrocochleography

ABSTRACT:

Although tonotopic place-coding in the cochlea has been extensively studied, our understanding of how the human cochlea responds *in vivo* to acoustic stimuli remains limited. We recorded acoustically-evoked intracochlear responses from 50 human subjects using a cochlear implant electrode and constructed an electrophysiology-based map using postoperative imaging to locate each electrode contact. The basal shifted frequency-place map resulting from higher stimulation more closely aligns with everyday speech levels.

The cochlea is responsible for converting sound waves into electrical impulses for hearing, by spatially separating sound waves by frequency using the basilar membrane and other soft tissues. This specificity, known as cochlear tonotopy, was first detailed by Nobel Laureate Georg von Békésy[1]. While *ex vivo* stroboscopic photography in cadavers[1, 2], *in vivo* electrophysiological and pressure recordings in animals[3, 4], and post-mortem histologically-derived retrograde tracer and imaging methods in both humans and animals[5, 6] have provided insights into the cochlear transduction process, they have limitations. These include inherent artifacts and spatial limitations resulting from surgical modifications and histologic processing[1, 7], difficulty studying cochlear amplification *ex vivo*[8], anatomical and physiological differences between animal models and humans[9], and inability to replicate dynamic biologic changes affecting passive cochlear mechanics in cadavers[10]. Therefore, little is known about how the human cochlea responds *in vivo* to various acoustic stimuli.

Existing technologies for *in vivo* electrophysiologic recordings within the human cochlea have been limited by their inability to achieve reliable and consistent intracochlear recordings and have mostly been limited to extracochlear recording sites.[11] However, intracochlear recordings could provide valuable insights into cochlear tonotopy. Cochlear implantation is an excellent model for analyzing cochlear mechanics in humans, as it involves placement of a multi-electrode array along the longitudinal axis of the cochlear lumen.

We report *in vivo,* acoustically-evoked recordings in 50 cochlear implant recipients, using the cochlear implant electrode array immediately after insertion at the round window (Fig. 1A). The array includes 22 platinum-iridium electrode contacts, spread evenly across 14.4 mm, which are individually used for recording. The implant package communicates with external recording instrumentation via a transcutaneous radiofrequency telemetry coil.

Acoustic tone-burst stimuli (250, 500, 1000, 2000, 3000, 4000 Hz) are presented and responses are recorded independently at all 22 electrodes. The electrocochleography (ECochG) responses include the cochlear microphonic (CM), auditory nerve neurophonic (ANN), transient compound action potential (CAP), and time-invariant summating potential (SP)[12]. Prior *in vivo* animal studies have shown that the CM potential reflects basilar-membrane displacement and that basilar membrane motion and auditory nerve tuning are exquisitely interrelated.[13] *In vivo* human recordings performed in this study are qualitatively similar to those recorded previously using a guinea pig model, with the unique use of multiple longitudinally inserted, intracochlear recording electrodes (Fig. 1B)[4].

To assess tonotopic frequency-position distributions, we precisely measured the location of each electrode along the array using computed tomography (CT) imaging after implantation[14]. A CT volume rendering of the electrode array within the cochlea was viewed along the mid-modiolar axis by an expert observer relative to a micro-CT atlas to measure cochlear dimensions and electrode position (Fig. 2B). The angular position (in degrees) of each electrode was measured based on the rotation about the mid-modiolar axis, with the 0° reference line starting at the round window membrane. The mean number of turns across 50 subjects was 2.6 (range, 2.2 – 2.9 turns).

Von Békésy established tonotopy and frequency-to-place mapping, with high-frequency tones peaking near the base and low-frequency tones near the apex of the basilar membrane, giving each place a distinct "best frequency" (BF). Wever and Bray II first showed electrical activity from the cochlea in response to sound in cats (i.e., Wever-Bray effect)[15]. Hallowell Davis later confirmed these responses in guinea pigs and cats, attributing them to the CM and action potential of the cochlear nerve[16]. These electrophysiological measurements combined with

von Békésy's physical and anatomical descriptions are essential for understanding human sound
perception.
To determine the tonotopic distribution of BF in the human cochlea, acoustic tone-burst
stimuli were presented and the fast Fourier transformation of the CM, taken as the difference
between rarefaction and condensation waveforms, was evaluated at each electrode (Fig. 2A),
resulting in CM tuning curves for each subject. The largest response on each curve was defined
as the BF location. BF electrodes were then angle-mapped using CT reconstructions to relate the
angular depth to tonotopic frequency in 50 human subjects (Fig. 2C-D).
We then compared the electrophysiologically-derived frequency-position map with organ
of Corti (OC) and spiral ganglion (SG) maps by Greenwood[17] and Stakhovskaya et al[6],
respectively (Fig. 2D). The modified SG and OC functions were compared using established
frequency-position equations from synchrotron radiation phase-contrast imaging, providing
better measurements of the helicotrema and hook region within the cochlea[18]. The
electrophysiologically-derived frequency map was found to be shifted at least one octave
downwards or more basal in location compared to both the OC and SG maps. Possible
explanations for this shift were explored.
Can stimulus intensity explain the difference between the electrophysiologically-derived
map and the SG/OC maps? Animal models have shown that higher stimulus intensities result in
less sharp tuning and a shift towards lower frequencies[19, 20]. We investigated this relationship in
20 human subjects with residual hearing post-implantation, varying stimulus intensities from 36
dB HL to 91 dB HL across 250 Hz to 2000 Hz. We found that frequency tuning and BF location
did not shift with decreases in stimulus intensity, although responses were limited by residual
hearing (Supplementary Fig. 1-3). A patient with auditory neuropathy spectrum disorder (with
present distortion product otoacoustic emissions—DPOAEs) was also tested, revealing an
expected shift towards Greenwood[17] and Stakhovskaya et al.[6] with reduction in stimulus level to
the limits of the equipment. Stimulation at conversational speech levels showed responses
similar to high-level stimulation rather than threshold, suggesting that frequency place maps
during conversation are more similar to those reported in pitch-matching experiments with
cochlear implants[21] than those described by the Greenwood equation (Fig. 3).
Does the electrode array impact the frequency-position map and explain the shift seen in
Fig. 2D? The impact of the electrode on the basilar membrane and the acoustic frequency-
position map is poorly understood. To investigate this, we compared pitch percepts of acoustic
stimuli presented to the non-implanted and implanted ear using pure tones ranging from 125 to
1250 Hz. The stimuli were balanced for loudness between both ears using a seven-point loudness
scale. One ear was used as a reference with a single pure tone delivered at 250, 500, or 1000 Hz,
while the other ear was presented with pure tones in random order. Subjects were asked to
indicate whether the pitches presented to each ear separately sounded the same or different
(Supplementary Fig. 4A). Results showed a small average difference (range, 1.30-1.65
semitones) in the acoustic perception of pure tones between both ears in two subjects
(Supplementary Fig. 4B-C), suggesting that the presence of the perimodiolar electrode does not
significantly explain the tonotopic basal shift observed in Fig. 2D.
Does creating an artificial cochlear 'third-window' alter the frequency-position map? Von
Békésy observed the traveling wave *ex vivo* using a rubber membrane-cemented brass ring as an
artificial stapes and a fenestration near the cochlear apex[1, 7, 22]. While the possibility of low-
frequency stimulation artifact as a result of the fenestration has been acknowledged[1, 7, 22], the
impact of the third window *in vivo* within the human cochlea is unknown. To investigate this, the

same electrode array described above was inserted into the round window of the cochlea during a
translabyrinthine approach to remove a vestibular schwannoma in a human with good residual
hearing. The location of the BF for frequencies between 250 Hz and 4 kHz was determined
before and after the creation of the fenestration near the upper cochlear turns, and the frequency-
position map did not shift with the creation of the third window, indicating that von Békésy's
artificial window did not affect the estimate of the frequency-position map (Supplementary Fig.
5).
The electrophysiological findings in this study must be considered in the context of the
subjects' underlying hearing loss. In mammals, outer hair cells act as cochlear amplifiers,
enhancing frequency selectivity and auditory sensitivity up to 40 dB[23], while high-level
stimulation causes a well-established half-octave shift of the tonotopic map toward the basal or
downward frequency direction[24]. The subjects' underlying otopathology further impairs active
cochlear mechanisms, resulting in a shift in the tonotopic map[25]. These factors likely account for
the lack of shift in the cochlea's tonotopic place coding upon reduction in stimulus intensity in
most patients. However, in the auditory neuropathy patient with preserved amplifier functions
(i.e., preserved DPOAEs), the expected impact of sound intensity modulation on place coding
was evident. At stimulus intensities similar to everyday listening (~70 dB HL), the frequency-
position responses more closely matched the high intensity stimulus results, suggesting the
electrophysiologically-derived tonotopic map may be more relevant for everyday listening and
cochlear implant mapping.
Direct intracochlear electrophysiology recordings were carried out for the first time to
determine the tonotopic map in humans, revealing results similar to those observed by von
Békésy. Although the role of cellular motors such as the cochlear amplifier cannot be ruled out,
our quantitative analysis of outer hair cell function indicates that the tonotopic place map is
basally or downward shifted at suprathreshold stimulus levels, more closely resembling typical
hearing conditions than the Greenwood 1990 model[17]. Clinical studies that utilize
electrophysiological recordings to evaluate patient-specific frequency mapping in cochlear
implant recipients could help improve frequency representation and potentially enhance their
hearing outcomes.

195
196
197
198
<u>REFERENCES</u>:

1.   Von Békésy, G. & Peake, W.T. Experiments in Hearing. *The Journal of the Acoustical*

Society of America 88, **2905** (1990).

2.   Von Békésy, G. Travelling Waves as Frequency Analysers in the Cochlea. *Nature* **225**,

1207-1209 (1970).

3.   Müller, M. The cochlear place-frequency map of the adult and developing Mongolian

gerbil. *Hearing research* **94**, 148-156 (1996).

4.   Tasaki, I., Davis, H. & Legouix, J.P. The Space□Time Pattern of the Cochlear

Microphonics (Guinea Pig), as Recorded by Differential Electrodes. *The Journal of the*

Acoustical Society of America **24**, 502-519 (1952).

5.   Liberman, M.C. Single-neuron labeling in the cat auditory nerve. *Science* **216**, 1239-1241

(1982).

6.   Stakhovskaya, O., Sridhar, D., Bonham, B.H. & Leake, P.A. Frequency map for the

human cochlear spiral ganglion: implications for cochlear implants. *Journal of the Association*

for Research in Otolaryngology **8**, 220-233 (2007).

7.   Von Békésy, G. *Zur Theorie des Hörens: Die Schwingungsform der Basilarmembran*

(Éditeur inconnu, 1928).

8.   Brownell, W.E., Bader, C.R., Bertrand, D. & de Ribaupierre, Y. Evoked mechanical

responses of isolated cochlear outer hair cells. *Science* **227**, 194-196 (1985).

9.   Nadol, J.B., Jr. Comparative anatomy of the cochlea and auditory nerve in mammals.

Hear Res **34**, 253-266 (1988).

10.   Zhang, Y.*, et al.* Prestin derived OHC surface area reduction underlies age☐related

rescaling of frequency place coding. *Hear Res* **423**, 108406 (2022).

11.   Fitzpatrick, D.C.*, et al.* Round window electrocochleography just before cochlear

implantation: relationship to word recognition outcomes in adults. *Otology & neurotology* **35**,

64-71 (2014).

12.   Eggermont, J.J. Cochlea and auditory nerve. *Handbook of clinical neurology* **160**, 437-

449 (2019).

13.   Ruggero, M.A., Narayan, S.S., Temchin, A.N. & Recio, A. Mechanical bases of

frequency tuning and neural excitation at the base of the cochlea: comparison of basilar-

membrane vibrations and auditory-nerve-fiber responses in chinchilla. *Proc Natl Acad Sci U S A*

97, 11744-11750 (2000).

14.   Teymouri, J., Hullar, T.E., Holden, T.A. & Chole, R.A. Verification of Computed

Tomographic Estimates of Cochlear Implant Array Position: A Micro-CT and Histologic

Analysis. *Otology & Neurotology* **32** (2011).

15.   Wever, E.G. & Bray, C.W. Action Currents in the Auditory Nerve in Response to

Acoustical Stimulation. *Proceedings of the National Academy of Sciences* **16**, 344-350 (1930).

16.   Davis, H. The Electrical Phenomena of the Cochlea and the Auditory Nerve. *The Journal*

of the Acoustical Society of America **6**, 196-197 (1935).

17.   Greenwood, D.D. A cochlear frequency-position function for several species--29 years

later. *The Journal of the Acoustical Society of America* **87**, 2592-2605 (1990).

18.   Helpard, L.*, et al.* An Approach for Individualized Cochlear Frequency Mapping

Determined From 3D Synchrotron Radiation Phase-Contrast Imaging. *IEEE transactions on bio-*

medical engineering **68**, 3602-3611 (2021).

19.   Versteegh, C.P.C. & van der Heijden, M. Basilar membrane responses to tones and tone

complexes: nonlinear effects of stimulus intensity. *Journal of the Association for Research in*

Otolaryngology **13**, 785-798 (2012).

20.   de Boer, E. & Nuttall, A.L. The mechanical waveform of the basilar membrane. III.

Intensity effects. *The Journal of the Acoustical Society of America* **107**, 1497-1507 (2000).

21.   Peters, J.P.M., Bennink, E. & van Zanten, G.A. Comparison of Place-versus-Pitch

Mismatch between a Perimodiolar and Lateral Wall Cochlear Implant Electrode Array in

Patients with Single-Sided Deafness and a Cochlear Implant. *Audiology and Neurotology* **24**, 38-

48 (2019).

22.   Von Békésy, G. Concerning the pleasures of observing, and the mechanics of the inner

ear." Nobel Lecture, December 11 (1961).

23.   Liberman, M.C.*, et al.* Prestin is required for electromotility of the outer hair cell and for

the cochlear amplifier. *Nature* **419**, 300-304 (2002).

24.   Ruggero, M.A., Rich, N.C. & Recio, A. The effect of intense acoustic stimulation on

basilar-membrane vibrations. *Auditory Neuroscience* **2**, 329-345 (1996).

25.   Robles, L. & Ruggero, M.A. Mechanics of the mammalian cochlea. *Physiological*

reviews **81**, 1305-1352 (2001).

260
261

AUTHOR CONTRIBUTIONS:
A.W. designed the study, participated in data collection and analyses, drafted and approved the final version of this paper. C.A.B. designed the study, participated in data collection, drafted and approved the final version of this paper. T.A.H., S.M.L., J.A.H., and A.J.O. participated in data collection, manuscript preparation, and approved the final version of this manuscript.

COMPETING INTERESTS:
C.A.B. serves as a consultant for Advanced Bionics, Cochlear Ltd., Envoy, and IotaMotion and has equity interest in Advanced Cochlear Diagnostics. J.A.H. serves as a consultant for Cochlear Ltd. For the remaining authors, none were declared.

ADDITIONAL INFORMATION:
AW was supported by NIH/NIDCD institutional training grant T32DC000022. CAB is supported by Department of Defense grant W81XWH19C0054 and NIH/NIDCD grant DC020936-01.

DATA AVAILABILITY:
The data that support the findings of this study are being made available on Zenodo.

CODE AVAILABILITY:
The code to analyze the data and generate the figures of this manuscript are being made available on GitHub.

    FIGURES:

Fig. 1. Measurement of live cochlear place coding in humans. (A) An insert earphone was placed into the
external auditory canal which was then connected to a sound processor to generate the acoustic stimulus. The
surgical site for placement of the recording electrode was then prepared in a sterile-fashion and the round
window of the cochlea was exposed using a post-auricular incision and mastoidectomy. The receiver-
stimulator for the implant electrode was placed in a subperiosteal pocket and the perimodiolar electrode array
was inserted into the round window, within scala tympani according to the manufacturer specification.
Following insertion of the electrode, a telemetry coil was placed over the skin in alignment with the cochlear
implant antenna which allowed for direct measurement from each of the 22 electrodes on the array in response
to acoustically-generated stimulus. The complex signal response measured from each electrode consisted of
the electrical activity from outer and inner hair cells and the spiral ganglion (inset). Post-hoc analysis of the
ongoing response was performed off-line to separate the hair cell and neural components of the response. A
significant response was defined as one whose magnitude exceeded the noise floor by 3 standard deviations.
(B) Acoustic stimuli were presented at 250, 500, 1000, 2000, 3000, and 4000 Hz and *in vivo* recordings were
made at all 22 electrode contacts. The responses at all even electrodes are shown in the color-matched figure
on the right panel where the most-apical electrode (electrode **a**) shows a large response for the 250 Hz stimulus
and the responses along more basal electrodes show larger responses for higher frequencies. The
electrophysiological properties of the human cochlea are demonstrated with greater electrical responses to
higher frequencies at the basal end and larger responses to lower frequencies at the apex. These recordings
were performed in 50 subjects, showing similar findings.

Fig. 2. Electrophysiologically-derived frequency-position map. (A) The difference curve was calculated by
subtracting rarefaction from condensation phase stimuli. The difference consists primarily of the cochlear
microphonic or the ongoing cyclical signal due primarily to the receptor current of outer hair cells. The
ongoing portion of the response was selected for fast Fourier transformation and the amplitude of the response
to the particular stimulus frequency was determined. Here, 500 Hz is shown for one subject. This was
performed across all 22 electrodes in response to 500 Hz and the largest amplitude response was defined as the
best frequency (BF) location for that particular frequency (e.g., $BF_{500 Hz}$). In this subject, the BF was at
electrode-18 for 500 Hz. (B) Computed tomography (CT) imaging and 3D reconstructions were performed
postoperatively to identify the individual electrodes and visualize the adjacent soft tissue anatomy. To
determine the position of each electrode, the CT image of each subject's cochlea was viewed along the mid-
modiolar axis and the round window was marked at the 0° at the start of the cochlear canal since all insertions
were performed at the round window. The angular position was then measured based on the rotation at the
mid-modiolar axis. For this subject, the BF was at electrode-18 which was measured at 364° within the
subject's cochlea. Here, the frequency-position relationship using electrophysiologic responses was determined
for 500 Hz. (C) The same methodology described above was performed for 1000, 2000, 3000 and 4000 Hz to
develop a frequency-position function for the individual subject's cochlea using the electrophysiologic
responses and CT imaging for the location of each electrode. (D) These electrophysiologic measurements were
repeated in 49 additional subjects and CT imaging was performed to identify the precise location of each BF to
generate a cumulative frequency-position function for the electrophysiologically-derived map (ECochG map).
Error bars are +/- 2 standard deviations (SD). This was compared to organ of Corti (OC) and spiral ganglion
(SG) maps as established by Greenwood and Stakhovskaya et al., respectively. The ECochG map in this study
is at least one octave shifted downward in frequency or more basal in location compared to both the SG and
OC maps. The OC map is also shown across various size cochleae (i.e., 2.1 and 2.9 turns), illustrating that the
size variability cannot account for the difference between the ECochG map and the OC map.

Fig. 3. Impact of intensity stimulus on frequency-position map. A subject with auditory neuropathy
spectrum disorder was tested, a condition known to have substantial preservation of cochlear hair cell function
as evidenced by present distortion-product otoacoustic emissions (2-8 kHz) and cochlear microphonics on
auditory brainstem response testing. This was carried out to determine whether stimulus intensity modulation
could account for the basal shifted tonotopic tuning derived from the intracochlear electrocochleography (Fig.
2D). Reduction in stimulus level to the limits of the equipment revealed the expected shift in an apical
direction for all four frequencies tested: (A) 1000 Hz, (B) 2000 Hz, (C) 3000 Hz, and (D) 4000 Hz. The
amplitude shown here are the fast Fourier transformation amplitudes of the difference response, which is
primarily representative of the cochlear microphonic tuning curve (i.e., outer hair cell tuning curve). The
asterisk (*) represents the best frequency (BF) electrode for each frequency and particular stimulus intensity.
The stimulus levels more similar to conversational speech showed responses similar to those seen at highest
stimulation level rather than those at threshold, which emphasizes that the frequency-position maps during
conversation are more similar to the high-intensity electrophysiologically-derived map rather than that
described by the Greenwood equation.
363

Methods

Study Design

Objectives of the study were to (i) describe the frequency-position function using the electrophysiologic recordings and compare with previously derived organ of Corti and spiral ganglion tonotopic maps of the human cochlea and (ii) investigate whether stimulus intensity, presence of the recording electrode, and creation of a third window could impact the frequency-position map.

Fifty human subjects were recruited to participate in this study under Institutional Review Board (IRB) approval (Washington University in St. Louis IRB #202007087). Subjects were considered for recruitment if they were undergoing cochlear implantation. Eligible subjects were adults with residual low-frequency hearing prior to surgery, defined as low-frequency pure tone average of 125, 250 and 500 Hz ≤ 60 dB HL. Subjects who had middle ear pathology or those undergoing revision surgery were excluded. Additionally, subjects who did not have a patent external auditory canal were excluded as the acoustic stimulus was delivered via air conduction. A demographic summary of all subjects is presented in table S1.

Surgical Technique for Electrode Placement

Five surgeons performed the operations and recordings with assistance of an audiologist. Surgery included a standard post-auricular incision and mastoidectomy to access the temporal bone. A posterior tympanotomy is used to access the cochlea and a round window related approach to scala tympani is used for the electrode array insertion. The receiver-stimulator is placed in a subperiosteal pocket. A perimodiolar electrode array was used for all insertions (CI632; Cochlear Corp., Sydney, NSW, Australia).

Intracochlear Electrophysiologic Measurements

Prior to sterile preparation of the surgical site, an ER3-14A insert earphone (Etymotic, Elk Grove Village, IL, United States) is placed into the external auditory canal. After the electrode has been inserted into the cochlea, a telemetry coil is placed over the skin in alignment with the cochlear implant antennae via a sterile ultrasound drape. All 22 electrodes along the electrode array are conditioned with reference to the case ground. Tone burst stimuli of 250-, 500-, 1000-, 2000-, 3000-, and 4000-Hz were independently delivered in condensation and rarefaction starting phases, with at least 30 repetitions per phase. The 250-, 500-, 1000-, 2000-, 3000-, and 4000-Hz stimuli were delivered at 108-, 99.5-, 98-, 104-, 102-, and 101-dB HL, respectively, which was based on the maximal output of the speaker. The stimulus duration was 14 ms with rise and fall time of 1 ms, shaped by a Blackman window. The recording epoch was 18 ms, starting 1 ms before the stimulus onset, with a sampling rate of 20 kHz. Responses were recorded across all 22 electrodes along the array.

Electrophysiology Signal Analysis

The electrophysiologic responses were processed offline and stored as condensation and rarefaction phases. Using MATLAB R2020a (MathWorks Corp., Natick, MA, United States) with custom software procedures, the difference curve was calculated by subtracting rarefaction form condensation phase stimuli. From the difference curve, the ongoing portion of the response was selected for fast Fourier transformation (FFT) and the amplitude of the response to the

409 various stimulus frequencies was determined. These amplitudes were used to generate cochlear
410 microphonic (CM) tuning curves for each individual frequency across the entire electrode array.
411 As described in previous studies, a significant response was defined as one whose magnitude
412 exceeded the noise floor by 3 standard deviations [1-3]. The noise floor was ~0.3 µV for this series
413 of recordings.

Computed Tomography Imaging of Electrode Position

The position of all 22 electrodes along the electrode array were determined in all patients using
computed tomography (CT) scans and 3D reconstructions. The platinum iridium contacts affect
the CT image by creating a bloom effect which makes it difficult to identify the individual
electrodes and adjacent soft tissue anatomy. A validated technique to overcome this artifact was
used to precisely identify the position of the implanted electrodes within the cochlea [4-6]. Each
subject's pre-implant CT image voxel space which is optimized for anatomical detail is co-
registered with their post-implant CT image space which is optimized for resolution of the
electrode. The electrode contacts are identified and then segmented from the post-implant image
data and copied onto the pre-implant image space to generate a composite image of the electrode
within an individual subject's cochlea. The scalar position of the electrode array and the
individual electrode contacts is visualized by aligning the composite CT volume to that of a
high-resolution micro-CT cochlear atlas derived from cadaveric temporal bones; this is used to
infer the location of the soft tissue structures within the cochlea not resolved by CT (e.g., basilar
membrane). To determine the position of each electrode, the composite CT volume of each
subject's cochlea is viewed along the mid-modiolar axis. The round window is marked as the 0°
starting point of the cochlear canal as all electrode insertions were performed using a round
window-related approach. The angular position of each electrode is then measured based on
rotation about the mid-modiolar axis from the 0° start point.

Electrophysiologically-Derived Frequency-Position Map

434 The best frequency (BF) is defined as that electrode along the array (i.e., cochlear place on the
435 basilar membrane) that responds maximally to a particular frequency stimulus. The CT-derived
436 angle-based mapping of the BF electrode for each stimulus was used to create a tonotopic map in
437 all 50 subjects. This electrophysiologically-derived map was then compared to derived organ of
438 Corti and spiral ganglion frequency-position map functions [7-9].

Stimulus Intensity and the Frequency-Position Map

The impact of stimulus intensity on the frequency tuning of the cochlea was evaluated using
electrophysiologic recordings in eleven subjects (20 of the 50 patients above and 1 with auditory
neuropathy spectrum disorder). Once the BF electrode was identified at the highest intensity
stimulus (as defined by the limit of the speaker) for a particular frequency, the stimulus intensity
was decreased in 5-dB increments. These measurements were performed at the BF electrode and
immediately adjacent electrodes to determine whether there would be an apical or basal shift of
the BF with decreasing stimulus intensity. A single sweep was performed for these
measurements and the noise floor for these measurements was ~1.0 µV. The rest of the stimulus
and recording parameters including the signal processing was identical to that described above.

To model the impact of stimulus intensity modulation on BF place in a cochlea with substantially
preserved hair cell function, a patient with auditory neuropathy spectrum disorder was identified.

This patient had both present distortion-product otoacoustic emissions (DPOAEs) between 2 and
8 kHz and auditory brainstem response waveforms consistent with a CM and absent neural
waveforms. After electrode array placement, measurements were made across every electrode
along the array at high-intensity, conversation-level intensity (~70 dB HL) and near threshold
(~20-30 dB HL) for 4 stimulus frequencies (1000-, 2000-, 3000, and 4000-Hz). Thirty sweeps
were performed for this subject. The CM tuning curves were generated for varying intensities
and frequencies.

Pitch Discrimination Testing with Electrode Array

To study the impact of the electrode on the frequency-position map, acoustic pitch-
discrimination was compared between ears in two unilateral cochlear implant subjects. The
cochlear implant processor was not used for this portion of the testing. Both subjects had their
implant for less than 6 months and had residual hearing preserved in the implant ear after
implantation (postoperative low-frequency pure tone average of 125-, 250-, and 500-Hz <60 dB
HL). Additionally, both subjects had similar residual hearing in the non-implanted ear. Each
participant attended two sessions, with at least two weeks between sessions. Both sessions were
approximately 2 hours in length and were conducted in a double-walled sound booth.
Audiometric air conduction thresholds from 250 Hz to 8 kHz were obtained using insert
earphones for each ear. The acoustic stimuli were first balanced for loudness at the tested
frequency between ears using a seven-point loudness scale from inaudible to uncomfortably loud
in order to identify that the stimulus intensity was comfortable in both ears [10]. Next, the non-
implanted ear was kept at a stimulus intensity that was determined as comfortable and the
acoustic stimulus intensity of the implanted ear was adjusted at 5-dB increments and then 1-dB
increments to identify the precise stimulus level where the tone sounded similar in both ears.
This process was repeated three times for each individual frequency tested (i.e., 250-, 500-,
1000-Hz) and the median value was used for the pitch-discrimination portion of the testing. After
loudness balancing at a comfortable level, the non-implant ear was then held constant at the
tested frequency (i.e., 250-, 500-, 1000-Hz) and the implant ear was presented with acoustic pure
tones ranging 2 octaves from the non-implant ear's constant frequency in a random order. There
was a total of 80 individual presentations of the various pure tones. The subject was then asked
to indicate whether both pitches presented to each ear separately sounded the 'same' or
'different'. The outliers were defined where the subject had one response that was different from
the other 4 responses, which is commonly noted as a component of fatigue in pitch-
discrimination testing [11]. This testing was then repeated at a separate session, where the implant
ear frequency was held constant and the non-implant ear frequency was varied.

Third Window and the Frequency-Position Map

Previous *ex vivo* experiments on tonotopy, including von Békésy's experiments, have used a
fenestration of the cochlear lumen to directly observe or record the traveling wave. The potential
impact of this artifact on the frequency-position map has not been previously studied. The impact
of the third window on electrophysiologic recordings was assessed in a human subject with
excellent residual hearing who was undergoing a translabyrinthine craniotomy (which
intentionally destroys the residual hearing) for resection of a vestibular schwannoma. Prior to
labyrinthine resection, the cochlea was approached and the same type of device was inserted in a
manner, identical to that described above. BF was identified along the array for 250-, 500-, 1000-
, 2000-, 3000-, and 4000-Hz at the maximum intensity output of the speaker and the signals were

processed as discussed above. After generating the CM tuning curves, a 1-mm diamond burr was
used to create a fenestration near the upper cochlear turns and the CM tuning curves were
generated again to determine whether the third window had an impact on the location of the BF.
The implant was removed and surgery proceeded without inciedent. The CM tuning curves were
generated for the individual frequencies, comparing pre- and post-fenestration of a third window.

1.   Walia, A*., et al.* Promontory Electrocochleography Recordings to Predict Speech-

Perception Performance in Cochlear Implant Recipients. *Otology & neurotology : official*

publication of the American Otological Society, American Neurotology Society [and] European

Academy of Otology and Neurotology **43**, 915-923 (2022).

2.   Fitzpatrick, D.C*., et al.* Round window electrocochleography just before cochlear

implantation: relationship to word recognition outcomes in adults. *Otology & neurotology :*

official publication of the American Otological Society, American Neurotology Society [and]

European Academy of Otology and Neurotology **35**, 64-71 (2014).

3.   Calloway, N.H*., et al.* Intracochlear electrocochleography during cochlear implantation.

Otology & neurotology : official publication of the American Otological Society, American

Neurotology Society [and] European Academy of Otology and Neurotology **35**, 1451-1457

(2014).

4.   Holden, L.K*., et al.* Factors affecting open-set word recognition in adults with cochlear

implants. *Ear and hearing* **34**, 342-360 (2013).

5.   Teymouri, J., Hullar, T.E., Holden, T.A. & Chole, R.A. Verification of computed

tomographic estimates of cochlear implant array position: a micro-CT and histologic analysis.

Otology & neurotology : official publication of the American Otological Society, American

Neurotology Society [and] European Academy of Otology and Neurotology **32**, 980-986 (2011).

6.   Skinner, M.W.*, et al.* In vivo estimates of the position of advanced bionics electrode

arrays in the human cochlea. *The Annals of otology, rhinology & laryngology. Supplement* **197**,

2-24 (2007).

7.   Greenwood, D.D. A cochlear frequency-position function for several species--29 years

later. *The Journal of the Acoustical Society of America* **87**, 2592-2605 (1990).

8.   Stakhovskaya, O., Sridhar, D., Bonham, B.H. & Leake, P.A. Frequency map for the

human cochlear spiral ganglion: implications for cochlear implants. *Journal of the Association*

for Research in Otolaryngology : JARO **8**, 220-233 (2007).

9.   Helpard, L.*, et al.* An Approach for Individualized Cochlear Frequency Mapping

Determined From 3D Synchrotron Radiation Phase-Contrast Imaging. *IEEE transactions on bio-*

medical engineering **68**, 3602-3611 (2021).

10.   Blamey, P.J. & Martin, L.F. Loudness and satisfaction ratings for hearing aid users. *J Am*

Acad Audiol **20**, 272-282 (2009).

11.   Elliott, D.N., Sheposh, J. & Frazier, L. Effect of Monaural Fatigue upon Pitch Matching

and Discrimination. *The Journal of the Acoustical Society of America* **36**, 752-756 (1964).