A Wearable Platform for Real-Time Control of a Prosthetic Hand by High-Density EMG

RICARDO G. MOLINARI[1,2], VALERIA AVILÉS-CARRILLO[1,2], GUILHERME A. G. DE VILLA[2,3], and LEONARDO A. ELIAS[1,2] (Member, IEEE)

[1]Department of Electronics and Biomedical Engineering, School of Electrical and Computer Engineering, University of Campinas, Campinas, SP 13083-852 Brazil)

[2]Neural Engineering Research Laboratory, Center for Biomedical Engineering, University of Campinas, Campinas, SP 13083-881 Brazil (molinari@unicamp.br, v222717@dac.unicamp.br, and leoelias@unicamp.br)

[3]State University of Goiás, Itaberaí, GO 76630-000, Brazil (e-mail: guilhermea1991@gmail.com)

Corresponding author: Leonardo A. Elias (e-mail: leoelias@unicamp.br).

This work was supported by the Brazilian Public Ministry of Work (contract number 002118.2019). Leonardo A. Elias is a Research Productivity Fellow of CNPq (Brazilian NSF, process number 316320/2023-4).

ABSTRACT This study presents a wearable platform for high-density surface electromyography (HD sEMG) acquisition and real-time myoelectric control of a hand prosthesis. The system integrates two 64-channel RHD2164 front-ends (128 channels total) with a Zynq UltraScale+ MPSoC for heterogeneous processing. A PYNQ-based Python/Linux framework enables scalable algorithm development. Experiments with 21 healthy subjects performing eight motor tasks (finger flexion/extension, thumb opposition, and grasp patterns) at two frequencies (0.50 and 0.75 Hz) demonstrated the platform's capability in HD sEMG recording and real-time control of a single degree of freedom (1-DoF). Signal quality exceeded recommended thresholds (SNR: 13.93 ± 7.51 dB; SMR: 25.18 ± 5.18 dB), confirming the effectiveness of the dual-front-end architecture. The processing pipeline combined reinforced electrode signal adaptation (RESA), non-negative matrix factorization (NMF), and Kalman filtering, resulting in strong agreement between estimated and reference signals, with maximum normalized cross-correlation (XC_{max}) values from 0.54 ± 0.22 to 0.80 ± 0.16. The coefficient of determination (R^2) for HD sEMG reconstruction ranged from 0.87 ± 0.09 to 0.95 ± 0.03, with higher values for prehension tasks. End-to-end latency from acquisition to command output ranged from 63.3 ± 1.0 ms (30 ms buffer) to 219.1 ± 4.5 ms (150 ms buffer), maintaining temporal alignment (XC_{max} lag: 0.02 ± 2.09 s). The heterogeneous architecture supports full local processing (2052.52 Hz/channel), with the FPGA handling acquisition and the Arm Cortex-A53 cores performing motor intention decoding, providing a scalable foundation for adaptive multi-DoF prosthetic control.

INDEX TERMS Heterogeneous Computing; Myoelectric Control; Prosthesis; Surface EMG; Wearable Technology.

I. INTRODUCTION

HIGH-DENSITY surface electromyography (HD sEMG) has become a key technology for non-invasive neuromuscular signal acquisition, enabling advanced control of upper-limb prostheses [1]. By capturing spatially detailed muscle activation patterns with dense electrode grids, HD sEMG enables the accurate decoding of user intent, which is essential for intuitive and precise prosthetic control. This is particularly relevant for transradial amputees, for whom restoring fine finger movements and grip force modulation remains a challenge [2]. Nevertheless, the rejection rate of below-elbow prostheses remain as high as 71.4%, mainly owing to issues of comfort, weight, and limited functionality

[3].

The technological evolution of myoelectric control systems has followed a clear trajectory toward increasingly efficient processing architectures. Early real-time control schemes relied on desktop computers connected to external amplifiers, offering few channels and limited portability [4]. The advent of wireless communication enabled cloud-based architectures, in which wearable acquisition devices transmitted raw signals to remote servers for computation [5]. However, this approach introduced critical vulnerabilities, including dependence on network reliability, increased latency from data transmission overhead, elevated power consumption, and privacy risks associated with sending physiological data [6].

Edge computing subsequently emerged as an intermediate solution, performing preliminary processing locally while offloading more complex computations to nearby devices [7], [8]. The current frontier lies in fully embedded processing, where high-density signal acquisition and advanced algorithm execution occur entirely on the wearable device, enabling reliable closed-loop control. This architectural shift addresses the limitations of cloud-based systems and supports autonomous operation with the real-time responsiveness required for safe prosthetic control [9]–[11].

Despite these advances, a substantial gap remains between the computational capabilities demanded by state-of-the-art myoelectric control algorithms and the resources available on current embedded platforms. Recent advances in HD sEMG signal decomposition have demonstrated not only the feasibility of non-invasively extracting individual motor unit discharge patterns, but also the importance of achieving robustness to signal non-stationarities [12]. Likewise, deep learning methods have achieved remarkable results in decoding complex movement intentions, including proportional and simultaneous control of multiple degrees of freedom [13]. Yet, these approaches impose heavy computational loads: motor unit decomposition requires iterative optimization over high-dimensional signal spaces, while deep neural networks depend on extensive matrix operations and large memory footprints. Translating these algorithms from laboratory environments — with effectively unlimited computational resource — to wearable devices constrained by power and thermal limits remains a major challenge [14]. There is therefore a pressing need for high-performance embedded platforms that can serve as experimental platforms, bridging the gap between algorithmic innovation and clinical translation by providing sufficient processing capability to evaluate demanding methods under realistic operating conditions.

This paper presents a 128-channel HD sEMG acquisition and processing device with heterogeneous embedded computing. The platform integrates high-density signal acquisition with onboard real-time processing to implement advanced myoelectric control strategies directly on a device [15]. We validated the system using a proportional movement-intention decoding (PMID) approach for a single degree of freedom (1-DoF), demonstrating its potential to support the intuitive control of a prosthetic hand, thereby bridging the gap between research and real-world application for transradial amputees.

II. ACQUISITION AND PROCESSING SYSTEM

Fig. 1 shows a schematic diagram of the HD sEMG signal acquisition and processing platform developed for real-time control of prosthetic hands. The platform consists of two analog front-ends and a heterogeneous computing system. The analog front-ends used RHD2164 devices (Intan Technologies, USA), each connected to a 64-channel electrode grid (GR10MM0808, OT Bioelettronica, Italy). Each front-end amplifies, filters, digitizes, and transmits myoelectric signals to the processing system.

The processing system used the FZ3 CARD development board (MYiR Tech Ltd., China), which incorporates the Zynq UltraScale+ Multiprocessor System-on-Chip (MPSoC) (Advanced Micro Devices Inc., USA). The Zynq UltraScale+ integrates an application processing unit (APU) and a field-programmable gate array (FPGA) in a single device. The FPGA acts as a protocol bridge between the analog front-ends and the APU. In addition, the FPGA enables direct memory access (DMA) to the data registers. The APU consists of four Arm Cortex-A53 cores and runs a Linux Ubuntu operating system based on a customized version of the PYNQ (Python Productivity for Zynq) framework. This setup orchestrates the entire platform, including hosting a graphical user interface (GUI), configuring the analog front-ends, initializing the FPGA, monitoring the battery status, and executing the PMID loop.

The estimated proportional movement intention (see description below) was transmitted via the SN65HVD1050 transceiver (Texas Instruments, USA), using the Controller Area Network (CAN) protocol to a modified version of the open-source Brunel Hand 2.0 (Open Bionics, UK). The GUI of the system, developed in the Jupyter Notebook, was accessed remotely through a VAP11G-300 Wi-Fi bridge (Vonets Network Co. Ltd., China) using a browser connected to the same network. The GUI enabled the initial configuration of the devices, operational control of the platform, and visualization of the HD sEMG signals. Rechargeable lithium-ion batteries (model 369108, Hamilton Medical, Switzerland) consisting of three cells in series and two sets in parallel (3S2P, with a nominal voltage of 10.8 V and 72 Wh), along with a battery management system (BMS) BQ20Z95 (Texas Instruments, USA), were used to power the platform. The FZ3 CARD board includes a power management integrated circuit (PMIC) TPS650864 (Texas Instruments, USA) that manages power delivery to the MPSoC and other onboard devices. In parallel, the battery also supplies power to the bionic hand via a Buck-Boost DC/DC converter module (XL6009, KylinChip Electronic, China), which regulates the voltage to 10.8 V (as shown in Fig. 1 by red arrows).

A. THE ANALOG FRONT-END MODULE

Table 1 presents the critical parameters for HD sEMG acquisition and compares the recommended features [16], [17] with the technical specifications of the RHD2164 device (as provided in its datasheet). The comparison includes aspects of analog front-end quality (such as amplitude, impedance, noise rejection, voltage range, intrinsic noise, and filtering) and analog-to-digital converter (ADC) performance, including sampling rate, resolution, and number of bits. The device employed in the platform features configurable third-order Butterworth analog band-pass filters, whose cutoff frequencies were set to 10 Hz and 500 Hz. Moreover, a first-order digital high-pass filter was activated and configured with a cutoff frequency of 10 Hz to remove oscillations and drift in the baseline level of the signal. The RHD2164 operates in slave mode, with a per-channel sampling rate of 2052.52 Hz,

FIGURE 1. Schematic diagram of the developed HD sEMG acquisition and processing platform for real-time prosthetic hand control. Two 64-channel analog front-ends amplify, filter, digitize, and transmit the signals to a heterogeneous processing system (Zynq UltraScale+ MPSoC), which combines FPGA and CPU cores running a customized Linux-based PYNQ framework. The system handles signal acquisition, movement intention decoding, GUI operation, and battery monitoring. A rechargeable Li-ion battery pack with a BMS powers the platform and the prosthetic hand, with voltage regulated for each device. The image illustrates the hardware and software components as well as the information and power flow. Wireless access to the GUI is provided via a Wi-Fi bridge. The top right corner shows the platform prototype, and the bottom right corner shows the Brunel Hand 2.0 (Open Bionics, UK) controlled by the platform.

which is directly determined by the frequency of commands received via the Serial Peripheral Interface (SPI) generated by the FPGA. Each RHD2164 integrates two 32-channel modules that operate in parallel, with the ADC data combined using a Double Data Rate (DDR) multiplexer for transmission via the Master Input Slave Output (MISO) channel. Low-Voltage Differential Signaling (LVDS) was employed for data transmission through 0.9-meter flexible cables (RHD SPI Interface, Intan Technologies, USA) connecting the analog front-ends to the processing system.

B. DUAL-MODE FPGA INTERFACE FOR RHD2164 DEVICES
The Advanced Extensible Interface (AXI) - DDR SPI module, implemented in the MPSoC FPGA, was responsible for converting between the LVDS DDR SPI and AXI protocols. A finite state machine was employed to manage the bridge between these protocols, handle data alignment of the master DDR SPI interface channels, perform (de)serialization, identify valid MISO message cycles, and configure the operating modes: configuration and streaming. In the configuration mode, the interface enables the GUI to access the registers of the RHD2164 devices for setup and calibration. In streaming mode, the module continuously generates analog-to-digital

conversion commands for the RHD2164 devices and sends the results to external memory via the AXI DMA block. AXI DMA operates cyclically based on the buffer size defined through the APU GUI. The FPGA design communicates reliably with the RHD2164 chip, with a maximum setup time of 10.40 ns and hold time of 12 ns, which are within the operational limits specified in the chip datasheet.

C. THE PORPORTIONAL MOVEMENT INTENTION DECODING LOOP
The proportional movement intention decoding (PMID) loop utilizes successive and overlapping analysis windows of HD sEMG recordings with a duration of T_a to maximize the processing capacity of the APU [4]. The first stage of the loop implements a fourth-order Butterworth band-pass digital filter (10-500 Hz) and a 60 Hz notch filter to remove possible motion artifacts, high-frequency noise, and power line interference that may bypass the analog front-end filtering. The second stage applies the Reinforced Electrode Signal Adaptation (RESA) algorithm to remove non-stationary artifacts caused by impedance variations at the skin-electrode interface [18]. The RESA algorithm computes an adaptation weight matrix for the channels based on the similarity between the

TABLE 1. Comparison between recommended HD sEMG signal acquisition features and RHD2164 specifications.

Specification	Recommendations [16], [17]	RHD2164
Amplifier AC Input Voltage Range, mV	± 7.5	± 5.0
Input Impedance, MΩ	≥ 80 at 50–60 Hz	1300 at 10 Hz and 13 at 1 kHz
Common-Mode Rejection Ratio (CMRR), *dB*	≥ 90 at 50–60 Hz	82 at 50–60 Hz
Power Supply Rejection Ratio (PSRR), *dB*	≥ 60	75
Input-Referred Noise, μV_{RMS}	≤ 2.0	2.4
High-Pass Cutoff Frequency (analog prefilter), Hz	0.10–20	0.02–1000
Low-Pass Cutoff Frequency (analog prefilter), Hz	500–1000	10–20000
ADC Sampling Rate per Channel, Hz	≥ 2048	up to 30000
ADC Resolution, bits	≥ 12	16
Input-Referred Resolution, μV	≤ 0.500	0.195

virtual reference signal (VRS) and electrode signals. To enable real-time implementation on the proposed platform, two modifications were applied to the original algorithm [18] to reduce the processing time of computationally intensive functions. The first modification replaces the Beta distribution model used in the VRS calculation with a Gaussian distribution model. The second modification substitutes the mutual information metric using Pearson's correlation coefficient.

The third stage of the loop calculates the root mean square (RMS) value of the HD sEMG channels using sliding windows of duration T_a. The fourth stage decomposes the matrix into two components via non-negative matrix factorization (NMF) [19]. One component captures finger flexion, thumb opposition, or grasp-closing movements, whereas the other represents finger extension, thumb reposition, or grasping movements. The algorithm assign each component to a movement direction by analyzing the phase of the cross-spectral density between its temporal signal and the task command signal (described in Section III-B). This directional mapping subsequently derived the proportional movement intention from the difference between the two components and standardized the resulting signal to have zero mean and unit variance. The fifth and final stage apply a one-dimensional Kalman filter [20] (without a dynamic model) to reduce noise associated with movement intention prediction. The process noise variance was set to 10^{-4}, and the measurement noise variance was 10^{-2}.

III. EXPERIMENTAL EVALUATION
A. PARTICIPANTS
Twenty-one healthy participants (10 women and 11 men) participated in the study. Participants' demographics are (mean $\pm$ standard deviation): 27.19 ± 6.55 years, body weight of 73.52 ± 16.06 kg, and height of 1.68 ± 0.11 m. Only one participant reported being left-handed. None of the participants had a history of neuromuscular or joint disorders affecting their dominant hand. This study was approved by the Research Ethics Committee of the University of Campinas (CAAE 80299124.2.1001.5404) on October 24, 2024, and all participants provided informed consent before the experi-

ments.

B. EXPERIMENTAL PROTOCOL
The electrode grids were placed centrally over the Extensor Digitorum Communis (EDC) and Flexor Digitorum Superficialis (FDS) muscles [21] after skin abrasion with an exfoliating paste and cleansing with 70% alcohol. The reference electrodes were attached to the wrist using a water-moistened conductive strap. Participants followed instructions to replicate dynamic, sinusoidal finger movements displayed by a virtual model of the bionic hand on a monitor placed in front of them (Fig. 2) while seated comfortably in a chair with their elbow resting on a height-adjustable table. Tasks began with the fingers fully extended, followed by the execution of eight movement patterns: flexion and extension of the index finger, middle finger, and ring and little fingers simultaneously; thumb opposition and retraction; pinch grasp and release with the index finger and thumb, and with the middle finger and thumb; tripod pinch with the index, middle, and thumb fingers; and 5-finger grasp. Sinusoidal finger movements were displayed at 0.50 Hz and 0.75 Hz, with 16 trials per set. Each participant completed three sets, for a total of 48 tasks. Each task lasted 45 s, with at least 30 s of rest between tasks. The order of the tasks was randomized, and HD sEMG signals were recorded at rest to assess signal quality.

The designed platform synchronized the start of the HD sEMG signal recording, virtual bionic hand movements shown on the monitor, and the motion capture system (Fig. 3). Synchronization signals were transmitted over Wi-Fi using the TCP/IP protocol to the monitor interface, developed with Unity Engine (Unity Technologies, USA), and via the UDP/IP protocol to the Vicon Vero 2.2 motion capture system (Vicon Motion Systems, UK). Kinematic data were processed using a custom-made trigonometric model that estimates the 1-D metacarpophalangeal joint angles.

C. HD SEMG PROPERTIES
The analysis examined HD sEMG recordings obtained with the new platform in both the time and frequency domains. The signals underwent only the analog and digital filter-

FIGURE 2. (A) Experimental setup. Each participant was instructed to follow sinusoidal dynamic movements displayed on a screen. HD sEMG of EDC and FDS muscles were recorded synchronously with the virtual bionic hand movements, along with hand markers to estimate joint angles by a Vicon motion capture system. Panels B to I illustrate the eight movements studied: (B) Index finger flexion; (C) Middle finger flexion; (D) Ring and little finger flexion; (E) Thumb opposition; F) Pinch grasp with the index finger; (G) Pinch grasp with the middle finger; (H) Tripod grasp; (I) 5-finger grasp.

FIGURE 3. Example of the recordings obtained during the flexion-extension task of the middle finger at 0.75 Hz. (A) Command signal controlling the position of the fingers of the virtual bionic hand displayed on the screen. (B) Metacarpophalangeal joint angles of the middle (green), ring (red), index (orange), thumb (blue), and little (purple) fingers. (C) *sEMG_{RMS}* from the electrode grid positioned over the FDS muscle (gray), along with the average *sEMG_{RMS}* across all channels (black). (D) *sEMG_{RMS}* from the electrode grid positioned over the EDC muscle (gray), and the corresponding average signal (black). (E) to (G) *sEMG_{RMS}* activation maps from the electrode grid over the EDC muscle. (I)-(L) *sEMG_{RMS}* activation maps from the electrode grid over the FDS muscle. (M) and (N) *sEMG_{PSD}* (Power Spectral Density) of the electrode grid over the FDS and EDC muscles, respectively (gray), along with their mean PSD (black).

ing stages integrated into the front-end of the system, with no additional filtering applied during the processing of the properties and quality metrics. The evaluation of HD sEMG characteristics included the peak-to-peak amplitude of the sEMG ($sEMG_{P2P}$), mean value of the $sEMG_{RMS}$, coefficient of variation (CoV) of the $sEMG_{RMS}$, and median frequency (MF) of the sEMG power spectral density ($sEMG_{PSD}$). Calculation of the $sEMG_{RMS}$ employed 300 ms windows. The PSD was estimated using Welch's method with 2 s Hanning windows without overlap.

D. HD SEMG QUALITY ASSESSMENT

The assessment of HD sEMG data quality utilized metrics derived from the $sEMG_{PSD}$, which quantified the contamination level of each recording, including motion artifacts, power line interference, noise, and intrinsic distortions of the

acquisition system [22]. Six quality metrics were calculated (Tab. 2): Signal-to-Noise Ratio (SNR), Signal-to-Motion-artifact Ratio (SMR), Signal-to-Power-line-interference Ratio (SPR), Signal-to-High-frequency-Noise Ratio (SHR), Spectrum Maximum-to-Minimum Drop in Power Density (SMMD), and Power Spectrum Deformation Ratio (PSDR). The evaluation of the results considered acceptable levels previously defined in the literature, when available [23], [24]. The distribution of SNR values was analyzed based on the taxonomy proposed by [24], where values below 1.8 dB do not necessarily indicate unacceptable signals but a low signal-to-noise ratio, suggesting a lack of relevant myoelectric activity for control applications; signals with SNR between 1.8 dB and 10 dB are acceptable; signals with SNR between 10 and 18 dB demonstrate minimized noise interference, rendering

them highly suitable for precise control; and values above 18 dB indicate negligible noise, characterizing high-quality signals ideal for myoelectric control systems.

TABLE 2. Spectral metrics used to evaluate the quality of myoelectric signals.

Metric (Abbreviation)	Equation	Acceptable Level [23], [24]
Signal-to-Noise Ratio (SNR)	$\dfrac{P_{signal}}{P_{rest}}$	> 1.8 dB
Signal-to-Motion-artifact Ratio (SMR)	$\dfrac{P_{signal}}{P_{0-20\,Hz}}$	> 12 dB
Signal-to-Power-line-interference Ratio (SPR)	$\dfrac{P_{signal}}{P_{60,120,\ldots}}$	N/A
Signal-to-High-frequency-noise Ratio (SHR)	$\dfrac{P_{signal}}{P_{500-1026\,Hz}}$	> 15 dB
Spectrum Maximum-to-Minimum Drop in Power Density (SMMD)	$\dfrac{MPD_{highest}}{MPD_{lowest}}$	> 30 dB
Power Spectrum Deformation Ratio (PSDR)	$\dfrac{(M_2/M_0)^{0.5}}{M_1/M_0}$	< 1.4

P_{signal} and P_{rest} are the total signal power measured during the task and at rest, respectively. P_{0-20Hz} represents a power below 20 Hz. $P_{60,120\ldots Hz}$ corresponds to the power at 60 Hz and its harmonics up to half of the sampling frequency. $P_{500-1026}$ denotes the sum of the power at frequencies greater than 500 Hz. *MPD* represents the mean power density of 13 consecutive points shifted across all the frequencies. M_n is the n-th order spectral moment.

E. PROPORTIONAL MOVEMENT INTENTION DECODING LOOP

The estimation time (T_e) of the PMID loop and contribution of each stage (filters, RESA, RMS, NMF, Kalman, and CAN) were evaluated for analysis window lengths (T_a) of 30, 60, 90, 120, and 150 ms. We calculated the accumulated time from the start of the acquisition window to the end of processing ($T_a + T_e$) and the ratio T_e/T_a. This ratio indicates the degree of overlap between consecutive windows, as the step between them approximates T_e. Values above 1 imply no overlap—risking loss of transient signal information, whereas values below 1 indicate overlapping windows, which enhance the temporal resolution.

The CAN transmission time was measured 10 times using a RIGOL MSO5074 oscilloscope and an ESP32 WROOM-32E microcontroller. It is defined as the interval between the rising edge of a step signal generated by the MPSoC just before sending a CAN message and the rising edge of a signal generated by the microcontroller upon message reception.

For NMF training, the first 5 s of the HD sEMG recordings were discarded to avoid transients, and the following 20 s were used for model training. The analysis window T_a was defined as the sliding window for the RMS calculation to ensure consistent temporal parameters during testing. The coefficient of determination (R^2) was used to quantify how well the NMF-reconstructed $sEMG_{RMS}$ signals matched the original data.

During training, the RESA weight matrix was updated every 30 ms, and the final weights served as the initial values for testing. The last 20 s of each trial (testing interval) was used to assess the ability of the PMID loop to track oscillations in the command signal. During testing, the PMID loop processed consecutive windows of length T_a using the spatial component matrix learned during training (Fig. 4A–D).

FIGURE 4. Example of the NMF decomposition and similarity evaluation between model output and command signals. (A and C) First spatial components extracted from the electrode grids over the EDC and FDS. (B and D) The second spatial components from the EDC and FDS muscles. (E) First and second temporal components. (F) Command signal of the virtual bionic hand (gray) and PMID loop output (black). (G) Normalized cross-correlation function between command and estimated signals (black) with *XCmax* highlighted (red circle).

F. STATISTICAL ANALYSIS

Before statistical analysis, the normality of data from HD sEMG properties and the similarity between the estimated proportional movement intention and command signals were assessed using the D'Agostino-Pearson test. In both cases, the data consistently failed the normality assumption across all metrics ($p < 0.001$), indicating the need to adopt non-parametric hypothesis tests.

The influence of task type and task frequency on HD sEMG properties was analyzed using a multifactorial Kruskal–Wallis test. Given the large sample size, all comparisons were statistically significant ($p < 0.001$) across all metrics. Therefore, the analysis focused on reporting the effect size using epsilon squared (ε^2), which provides a robust measure that is independent of the sample size [25]. The effect size was considered negligible when $\varepsilon^2 < 1\%$, small when $1\% \leq \varepsilon^2 < 8\%$, medium when $8\% \leq \varepsilon^2 < 26\%$, and large when $\varepsilon^2 \geq 26\%$ [26].

The similarity between the estimated proportional movement intention and command signals was quantified by the maximum normalized cross-correlation (XC_{max}) of the test data (Fig. 4G). The effect of T_a on XC_{max} was analyzed using the Kruskal–Wallis test. The effects of task type and frequency on XC_{max}, training R^2, and the lag at XC_{max} during testing were assessed using a multifactorial Kruskal–Wallis test at $T_a = 60$ ms, followed by Dunn's post hoc test for pairwise comparisons.

All descriptive statistics are reported as the mean ± standard deviation. Statistical significance was set at $p < 0.05$.

IV. RESULTS

A. HD SEMG PROPERTIES

Of the 129,024 signals recorded during the platform evaluation, only two channels (0.002 %) exceeded the amplifier's linear range (±5 mV). At rest, HD sEMG showed $sEMG_{P2P}$ of 244.15 ± 253.14 µV, $sEMG_{RMS}$ of 15.62 ± 11.02 µV, and $sEMG_{MF}$ of 128.90 ± 37.18 Hz. The low $sEMG_{RMS}$ confirmed negligible muscle activity and defined the baseline for SNR calculation.

Dynamic tasks at 0.75 Hz produced higher $sEMG_{P2P}$ amplitudes (1.36 ± 0.64 mV) than at 0.50 Hz (1.13 ± 0.55 mV; Fig. 5A), with a small effect size of frequency ($\varepsilon^2 = 4.37\%$). Mean $sEMG_{RMS}$ followed the same trend: 82.60 ± 36.69 µV at 0.75 Hz vs. 66.71 ± 29.07 µV at 0.50 Hz ($\varepsilon^2 = 6.83\%$). Task type had a medium effect size on $sEMG_{P2P}$ ($\varepsilon^2 = 10.80\%$) and a small effect size on mean $sEMG_{RMS}$ ($\varepsilon^2 = 6.75\%$). The interaction between task type and frequency had medium effect sizes ($sEMG_{P2P}$: $\varepsilon^2 = 15.37\%$; $sEMG_{RMS}$: $\varepsilon^2 = 13.68\%$). The 5-finger grasp task produced the highest mean $sEMG_{RMS}$ (0.75 Hz: 96.34 ± 47.25 µV; 0.50 Hz: 73.29 ± 30.11 µV), whereas the lowest values occurred in the index (0.75 Hz: 68.65 ± 26.53 µV) and thumb (0.50 Hz: 55.93 ± 25.04 µV) tasks (Fig. 5B).

Kruskal–Wallis analysis revealed a large effect of task type on $sEMG_{RMS}$ CoV ($\varepsilon^2 = 35.28\%$), a negligible effect of frequency ($\varepsilon^2 = 0.02\%$), and a large task type and frequency interaction ($\varepsilon^2 = 35.47\%$), indicating that CoV primarily depended on task type, with higher variability during grasping. The $sEMG_{RMS}$ CoV was consistently high for the 5-finger grasp (0.50 Hz: 51.8 ± 18.0%; 0.75 Hz: 50.1 ± 13.1%) and low in single-finger tasks (e.g., index at 0.75 Hz: 24.8 ± 7.7%; middle at 0.50 Hz: 28.7 ± 10.6%).

The $sEMG_{PSD}$ exhibited the expected monopolar pattern with power concentrated between 20–150 Hz [27], [28]. The

FIGURE 5. Distributions of HD sEMG signal properties by task type and movement frequency ($N = 8,064$). (A) Peak-to-peak amplitude ($sEMG_{P2P}$), (B) mean $sEMG_{RMS}$, (C) coefficient of variation (CoV) of $sEMG_{RMS}$, (D) median frequency ($sEMG_{PSD}$).

Kruskal–Wallis test revealed small effect sizes for task type ($\varepsilon^2 = 7.38\%$) and frequency ($\varepsilon^2 = 1.00\%$), and a medium effect size for the interaction between task type and frequency ($\varepsilon^2 = 9.20\%$). Median frequency ($sEMG_{MF}$) decreased by approximately 10 Hz in middle and ring–pinky tasks at 0.75 Hz vs. 0.50 Hz (e.g., middle: 83.14 ± 22.84 Hz vs. 93.78 ± 21.58 Hz), , whereas other tasks showed smaller changes (index: 103.94 ± 20.75 Hz vs. 101.72 ± 22.98 Hz; thumb: 100.80 ± 18.66 Hz vs. 103.72 ± 21.61 Hz; Fig. 5D).

B. HD SEMG QUALITY ASSESSMENT

The analysis of the distribution of the quality metric values for the HD sEMG signals (Fig. 6) indicated that all metrics exceeded their respective acceptance thresholds. The SNR (Fig. 6A) showed a mean value of 13.93 ± 7.51 dB, reflecting the overall quality of the acquired signals. Only 2.76 ± 9.32% of the channels exhibited an SNR < 1.8 dB, suggesting a small percentage of functionally irrelevant signals for control purposes. Approximately 30.58 ± 34.12% of the signals fell within the 1.8 to 10 dB, indicating suitability for myoelectric control applications. The highest proportion of channels

(39.66 ± 35.03%) exhibited SNR values between 10 and 18 dB, a range where noise impact on extracted sEMG parameters is considered minimal. Finally, 27.00 ± 39.35% of the channels showed an SNR above 18 dB, indicating negligible noise presence and high-quality signals suitable for myoelectric control purposes. The SNR values close to the acceptance threshold were expected, given the low-intensity contractions during the dynamic movements employed in our study, with $sEMG_{RMS}$ values below those observed in isometric tasks at 10% of maximum voluntary contraction [29].

FIGURE 6. Distributions of spectral quality metrics of the HD sEMG signals. Red dashed lines and arrows are shown only when acceptable thresholds are reported in the literature [24]. Arrows indicate the direction of acceptable values. (A) Signal-to-Noise Ratio (SNR). (B) Signal-to-Motion Artifact Ratio (SMR). (C) Signal-to-Power Line Interference Ratio (SPR). (D) Power Spectrum Deformation Ratio (PSDR). (E) Signal-to-High Frequency Noise Ratio (SHR). (F) Spectrum Maximum-to-Minimum Drop in Power Density (SMMD).

The SMR metric (Fig. 6B) showed a value of 25.18 ± 5.18 dB, with only 2.44 ± 14.55% of channels falling below the 12 dB threshold, suggesting that motion artifacts were minimal in the recorded data. The SPR values (Fig. 6C), which quantify power line interference at 60 Hz and its harmonics, were 20.99 ± 1.30 dB. While no established threshold exists for this metric in the literature, a visual examination of the $sEMG_{PSD}$ reveals negligible interference. The PSDR metric (Fig. 6D) had a value of 0.77 ± 0.22, with 98.67 ± 11.03% of channels below the recommended threshold of 1.4 [23], indicating a high spectral quality of the signals. The SHR metric (Fig. 6E) yielded a value of 23.16 ± 2.85 dB, with 99.81 ± 1.08% of channels exceeding the 15 dB threshold, indicating a negligible presence of high-frequency noise in the signals. The SMMD metric achieved a mean value of 41.71 ± 4.69 dB, with 99.20 ± 1.86% of channels surpassing the 30 dB threshold, indicating that nearly all signals exhibit power spectra properly sampled across the frequency range corresponding to sEMG signals.

C. PROPORTIONAL MOVEMENT INTENTION DECODING LOOP

The developed platform successfully controlled the bionic hand in real time, with the PMID loop output effectively modulating the prosthetic hand actuators (Fig. 7; see supplementary videos). Figure 8 summarizes the estimation time

(T_e) and total processing time ($T_a + T_e$) of each PMID loop stage for different analysis windows (T_a). Processing times for filters, RESA, and RMS increased with T_a, while NMF, Kalman, and CAN remained nearly constant. RESA had the highest processing time (17.69±0.82 ms to 35.34±4.36 ms), followed by filtering (9.21±0.17 ms to 22.34±0.70 ms) and RMS (1.39 ± 0.04 ms to 6.26 ms). NMF, Kalman, and CAN times were 3.34±0.31 ms, 0.05±0.02 ms, and 1.79±0.55 ms, respectively. T_e ranged from 33.30 ± 1.01 ms to 69.11 ± 4.47 ms. Total control latency (T_a+T_e) increased from 63.30±1.01 ms (T_a = 30 ms) to 219.11 ± 4.47 ms (T_a = 150 ms). The T_e/T_a ratio exceeded 1 only at T_a = 30 ms, indicating no overlap and potential loss of transient information. For $T_a \geq 60$ ms, the ratio dropped below 1 (0.76–0.46), reflecting an increasing overlap and improved temporal resolution.

Figure 9 shows R^2 and XC_{max} distributions as a function of T_a. R^2 slightly increased with larger windows (0.89 ± 0.07 to 0.94 ± 0.07). XC_{max} during training rose from 0.51 ± 0.19 to 0.67 ± 0.19, likely due to reduced RMS noise with higher T_a. XC_{max} for the test data remained unchanged ($\sim 0.66 \pm 0.20$), with no significant differences across T_a (Kruskal–Wallis, $p = 0.197$, $\varepsilon^2 = 0.12\%$), indicating that model generalization was unaffected.

Figure 10 presents the performance of the PMID loop across the motor tasks and the execution frequencies for T_a = 60 ms. The Kruskal–Wallis test revealed that task type had a large effect on R^2 ($p < 0.001$, $\varepsilon^2 = 28.94\%$), frequency had no significant effect ($p = 0.053$, $\varepsilon^2 = 0.37\%$), and the interaction between task type and frequency was significant with a large effect size ($p < 0.001$, $\varepsilon^2 = 29.53\%$), indicating that the influence of frequency depended on the specific task. Grasping tasks consistently showed the highest reconstruction quality ($R^2 = 0.95 \pm 0.03$ for the 5-finger grasp at 0.75 Hz). In contrast, non-grasping movements (index, middle, and ring–pinky fingers) exhibited lower performance ($R^2 = 0.87 \pm 0.09$ for index flexion–extension at 0.50 Hz).

Kruskal–Wallis analysis of XC_{max} for the test data revealed significant effects of task type ($p < 0.001$, $\varepsilon^2 = 11.70\%$), frequency ($p = 0.003$, $\varepsilon^2 = 0.87\%$), and the interaction between task type and frequency ($p < 0.001$, $\varepsilon^2 = 12.92\%$). The middle finger task at 0.50 Hz exhibited the highest similarity between the model output and command signal (0.80 ± 0.16). In contrast, the index finger task at 0.75 Hz showed the lowest similarity (0.54 ± 0.22) compared with the other tasks.

Analysis of the cross-correlation lags showed values near zero for all tasks and frequencies (0.02 ± 2.09 s). Kruskal–Wallis tests indicated no significant effects of task type ($p = 0.578$, $\varepsilon^2 = 0.56\%$), frequency ($p = 0.459$, $\varepsilon^2 = 0.05\%$), or their interaction ($p = 0.754$, $\varepsilon^2 = 1.09\%$), confirming the minimal temporal offset in the model output.

V. DISCUSSION
A. TECHNOLOGICAL FRAMEWORK
The primary contribution of this work is the development and validation of a wearable platform for high-density myoelec-

FIGURE 7. Illustrative example of real-time myoelectric control of the bionic hand during a 5-finger grasp task. (A) $sEMG_{RMS}$ recorded from the electrode grid positioned over the *Flexor Digitorum Superficialis* (FDS) muscle. (B) $sEMG_{RMS}$ from the electrode grid over the *Extensor Digitorum Communis* (EDC) muscle. (C) Output of the Proportional Movement Intention Decoding (PMID) loop. (D) Position of the bionic hand actuator shafts corresponding to the thumb (blue), index (orange), middle (green), and ring-pinky fingers (red); (E) to H) Video frames synchronized with the HD sEMG recordings, showing the bionic hand and the participant operating the myoelectric control system at 3 s, 6 s, 10 s, and 20 s, respectively (also indicated by vertical lines in the plots).

tric control of a prosthetic device, utilizing a heterogeneous computing architecture. Unlike most solutions reported in the literature, that rely on wearable devices with external processing for high-density signal acquisition [30], [31], the proposed system performs both acquisition and processing entirely embedded in the device. This design enables real-time, local algorithm execution, reduces latency and enhances system autonomy, while providing a technical foundation for scalable and reconfigurable architectures. By integrating analog circuits for HD sEMG signal acquisition with an adaptive MPSoC, the platform supports continuous signal capture and processing under realistic usage conditions, effectively addressing challenges related to connectivity, mobility, and dependence on external computing resources [32], [33].

B. HD SEMG PROPERTIES AND QUALITY ASSESSMENT

The acquired signals exhibited amplitudes well below the full scale of the acquisition system, indicating a robust operational margin and absence of saturation for the analyzed tasks. However, more intense muscle contractions, approaching maximum voluntary contraction, were not assessed. Despite relatively low average $sEMG_{RMS}$ values, consistent variations across tasks were observed, as reflected by the coefficient of variation ($sEMG_{RMS}$ CoV), demonstrating the sensitivity of the system to varying levels of muscle activation depending on the executed motor tasks. The reduced amplitude observed during thumb opposition movements likely arises from the predominant involvement of the intrinsic hand muscles, which are located distally within the hand and originate near the carpal bones. Because these muscles lie far from the electrode grids placed on the proximal forearm, the sEMG signals they generate are attenuated compared with signals

FIGURE 8. Processing performance of the Proportional Movement Intention Decoding (PMID) loop as a function of acquisition window (T_a). (A) Processing time of each stage, with estimation time (T_e) shown in black. (B) Total acquisition and estimation time ($T_a + T_e$), with stacked bars representing the contribution of each processing stage. (C) Ratio of T_e to T_a; the red dashed line indicates $T_e = T_a$, with values below the line representing estimation times faster than acquisition. Error bars denote standard deviation. Sample size slightly decreased with T_a: $N = 66{,}640$ (30 ms), $66{,}560$ (60 ms), $66{,}480$ (90 ms), $66{,}400$ (120 ms), and $66{,}320$ (150 ms).

FIGURE 9. Performance metrics of the Proportional Movement Intention Decoding (PMID) loop as a function of acquisition windows (T_a, $N = 1{,}008$). (A) Distributions of the coefficient of determination (R^2) for reconstructing HD sEMG signals from the NMF components. (B) Distributions of the maximum cross-correlation values (XC_{max}) between the estimated signals and the command signals for training (green) and testing (red) data. Diamonds denote mean values, boxes represent the interquartile range, and whiskers indicate minimum and maximum values (excluding outliers).

FIGURE 10. Distribution of performance metrics for the Proportional Movement Intention Decoding (PMID) loop across different motor tasks and execution frequencies, for $T_a = 60$ ms ($N = 63$). (A) Coefficient of determination (R^2) for the reconstruction of HD sEMG signals from NMF components. (B) Maximum cross-correlation value (XC_{max}) for the training data. (C) XC_{max} for the test data. (D) Temporal lag at which XC_{max} occurs for the test data. Diamonds represent the mean values, boxes indicate the interquartile range, and whiskers show the minimum and maximum values (excluding outliers).

[34].

Higher mean $sEMG_{RMS}$ values at increased task frequencies reflect increased movement cadence, which requires greater muscle recruitment to execute faster movements. This increased activation results in larger signal amplitudes, consistent with evidence showing a strong correlation between movement speed and surface EMG activity, where higher velocities systematically elicit stronger muscular responses [35].

Overall, the spectral quality metrics of the signals were quite satisfactory, showing negligible contamination by noise and artifacts, surpassing the minimum (or maximum for the PSDR) acceptability thresholds suggested in the literature [24]. Therefore, this initial investigation confirmed that the developed platform is well-suited for real-time myoelectric control applications and neurophysiological analysis of HD EMG signals.

from the more proximal and thicker extrinsic forearm muscles

C. PROPORTIONAL MOVEMENT INTENTION DECODING LOOP

The PMID loop demonstrated that the system successfully reconstructed the dynamics of the modulating signals, achieving high values of R^2 and XC_{max}, particularly in tasks involving grasping movements. However, these findings do not necessarily imply higher performance in motor tasks representing daily activities [14]. The higher R^2 values observed in grasping tasks likely resulted from their reduced synergistic control, which facilitated the separability of 1-DoF patterns during the NMF stage. In contrast, non-grasping movements often require additional muscular contractions to stabilize fingers that are not actively engaged in the task. These postural contractions distribute control more broadly and induce multimodal motor unit activity shaped by the hand configuration. Such complexity increases the dimensionality of the HD sEMG signals. Unlike the low-dimensional synergistic control characteristic of grasping, this may account for the lower R^2 values observed when modeling 1-DoF movements [36], [37].

The discrepancy between the high explained variance (R^2) in the reconstruction of $sEMG_{RMS}$ signals and the strong similarity (XC_{max} for the test data) between the model output and command signal observed in the middle finger task reflects an intrinsic limitation of this measure. Surface EMG amplitude metrics such as $sEMG_{RMS}$ are more directly related to the amplitude of motor unit action potentials than to the underlying motor unit activity, thus providing only a coarse approximation of the neural drive for muscle activation [38].

For the tasks analyzed, which involved cyclostationary signals, the cross-correlation function exhibited multiple peaks separated by integer multiples of the signal period. Consequently, XC_{max} values occurring at lags exceeding the command signal period may result from the signal's inherent periodicity or intrinsic noise, rather than representing a true physiological delay. This interpretation aligns with the theoretical foundations outlined in the literature, which highlights the phase ambiguity inherent in periodic signals and the resulting limitations in accurately estimating time delays [39], [40].

VI. CONCLUSION

This work demonstrates the design and validation of a wearable HD sEMG acquisition and processing platform with a heterogeneous architecture that enables real-time estimation of one degree-of-freedom (1-DoF) proportional movement intention. The system consistently produced outputs that closely match the command signals across specific hand motor tasks, while maintaining processing latencies well within real-time control requirements. Although the embedded algorithm cannot yet represent coordinated and proportional multi-finger movements, the designed platform effectively handles 1-DoF motor tasks and establishes a robust foundation for the development of more advanced control strategies.

VII. ACKNOWLEDGMENT

The authors would like to thank Mr. Flavio Renato Santos, Mr. Nelio Hilton Gava, and Mr. Glaudson Frade Assunção from the Main Design Lab, Center for Biomedical Engineering, UNICAMP, for their technical support in designing and fabricating the platform and the bionic hand prototypes.

REFERENCES

[1] N. Jiang, C. Chen, J. He, J. Meng, L. Pan, S. Su, and X. Zhu, "Bio-robotics research for non-invasive myoelectric neural-interfaces for prosthetic control—a ten-year perspective review," *National Science Review*, 4 2023.

[2] F. Cordella, A. L. Ciancio, R. Sacchetti, A. Davalli, A. G. Cutti, E. Guglielmelli, and L. Zollo, "Literature review on needs of upper limb prosthesis users," *Frontiers in Neuroscience*, vol. 10, no. MAY, pp. 1–14, 2016.

[3] S. Salminger, H. Stino, L. H. Pichler, C. Gstoettner, A. Sturma, J. A. Mayer, M. Szivak, and O. C. Aszmann, "Current rates of prosthetic usage in upper-limb amputees–have innovations had an impact on device acceptance?," *Disability and Rehabilitation*, vol. 44, no. 14, pp. 3708–3713, 2022.

[4] K. Englehart and B. Hudgins, "A Robust, Real-Time Control Scheme for Multifunction Myoelectric Control," *IEEE Transactions on Biomedical Engineering*, vol. 50, no. 7, pp. 848–854, 2003.

[5] F. Chiariotti, P. Mamidanna, S. Suman, C. Stefanovic, D. Farina, P. Popovski, and S. Dosen, "The Future of Bionic Limbs: The untapped synergy of signal processing, control, and wireless connectivity," *IEEE Signal Processing Magazine*, vol. 41, no. 4, pp. 58–75, 2024.

[6] E. Rodriguez-Villegas, S. Iranmanesh, and S. A. Imtiaz, "Wearable Medical Devices: High-Level System Design Considerations and Tradeoffs," *IEEE Solid-State Circuits Magazine*, vol. 10, no. 4, pp. 43–52, 2018.

[7] C. Beach, E. Balaban, and A. J. Casson, *Edge algorithms for wearables: An overview of a truly multi-disciplinary problem.* Elsevier Inc., 2 ed., 2020.

[8] O. Karaali, H. Farag, S. Dosen, and C. Stefanovic, "5G-Enabled Smart Prosthetic Hand: Connectivity Analysis and Assessment," 2025.

[9] A. Boschmann, A. Agne, G. Thombansen, L. Witschen, F. Kraus, and M. Platzner, "Zynq-based acceleration of robust high density myoelectric signal processing," *Journal of Parallel and Distributed Computing*, vol. 123, pp. 77–89, 2019.

[10] V. M. Navarro, R. Nieto, P. R. Fernandez, A. Hernandez, A. J. Del-Ama, and S. Borromeo, "SoC Architecture for Acquisition and Processing of EMG Signals," *2023 38th Conference on Design of Circuits and Integrated Systems, DCIS 2023*, 2023.

[11] I. B. Abdallah and Y. Bouteraa, "A Newly-Designed Wearable Robotic Hand Exoskeleton Controlled by EMG Signals and ROS Embedded Systems," jul 2023.

[12] D. Yeung, F. Negro, and I. Vujaklija, "Adaptive HD-sEMG decomposition: towards robust real-time decoding of neural drive," *Journal of Neural Engineering*, vol. 21, no. 2, 2024.

[13] R. C. Sîmpetru, D. I. Braun, A. U. Simon, M. März, V. Cnejevici, D. S. de Oliveira, N. Weber, J. Walter, J. Franke, D. Höglinger, C. Prahm, M. Ponfick, and A. Del Vecchio, "MyoGestic: EMG interfacing framework for decoding multiple spared motor dimensions in individuals with neural lesions," *Science Advances*, vol. 11, no. 15, pp. 1–14, 2025.

[14] I. Vujaklija, A. D. Roche, T. Hasenoehrl, A. Sturma, S. Amsuess, D. Farina, and O. C. Aszmann, "Translating research on myoelectric control into clinics-are the performance assessment methods adequate?," *Frontiers in Neurorobotics*, vol. 11, no. FEB, pp. 1–7, 2017.

[15] L. Crockett, D. Northcote, C. Ramsay, F. Robinson, and B. Stewart, "Zynq Ⓡ MPSoC With PYNQ and Machine Learning Applications," tech. rep., 2019.

[16] R. Merletti and G. L. Cerone, "Tutorial. surface emg detection, conditioning and pre-processing: Best practices," *Journal of Electromyography and Kinesiology*, vol. 54, 10 2020.

[17] E. A. Clancy, E. L. Morin, G. Hajian, and R. Merletti, "Tutorial. Surface electromyogram (sEMG) amplitude estimation: Best practices," *Journal of Electromyography and Kinesiology*, vol. 72, no. June, p. 102807, 2023.

[18] M. Stachaczyk, S. F. Atashzar, and D. Farina, "Adaptive spatial filtering of high-density emg for reducing the influence of noise and artefacts in myoelectric control," *IEEE Transactions on Neural Systems and Rehabilitation Engineering*, vol. 28, pp. 1511–1517, 7 2020.

[19] S. Muceli, N. Jiang, and D. Farina, "Extracting signals robust to electrode number and shift for online simultaneous and proportional myoelectric

control by factorization algorithms,'' *IEEE Transactions on Neural Systems and Rehabilitation Engineering*, vol. 22, pp. 623–633, 2014.

[20] R. E. Kalman, ''A new approach to linear filtering and prediction problems,'' *Journal of Fluids Engineering, Transactions of the ASME*, vol. 82, no. 1, pp. 35–45, 1960.

[21] P. Zipp, ''Recommendations for the Standardization of Lead Positions in Surface Electromyography*,'' *European Journal of Applied Physiology and Occupational Physiology*, vol. 50, pp. 41–54, 1982.

[22] E. Farago, D. MacIsaac, M. Suk, and A. D. Chan, ''A review of techniques for surface electromyography signal quality analysis,'' 2023.

[23] C. Sinderby, L. Lindstrom, and A. E. Grassino, ''Automatic assessment of electromyogram quality,'' *Journal of Applied Physiology*, vol. 79, no. 5, pp. 1803–1815, 1995.

[24] J. Chang, A. Phinyomark, and E. Scheme, ''Assessment of EMG Benchmark Data for Gesture Recognition Using the NinaPro Database,'' *Proceedings of the Annual International Conference of the IEEE Engineering in Medicine and Biology Society, EMBS*, vol. 2020-July, pp. 3339–3342, 2020.

[25] M. Tomczak and E. Tomczak, ''The need to report effect size estimates revisited. An overview of some recommended measures of effect size,'' *Trends in Sport Sciences*, vol. 1, no. 21, pp. 19–25, 2014.

[26] S. Mangiafico, *Summary and Analysis of Extension Program Evaluation in R*. Rutgers Cooperative Extension, New Brunswick, NJ, version 1 ed., 2016. Retrieved from https://rcompanion.org/handbook/.

[27] T. W. Beck, T. J. Housh, J. T. Cramer, M. H. Malek, M. Mielke, R. Hendrix, and J. P. Weir, ''A comparison of monopolar and bipolar recording techniques for examining the patterns of responses for electromyographic amplitude and mean power frequency versus isometric torque for the vastus lateralis muscle,'' *Journal of Neuroscience Methods*, vol. 166, no. 2, pp. 159–167, 2007.

[28] D. A. Gabriel, ''Effects of monopolar and bipolar electrode configurations on surface EMG spike analysis,'' *Medical Engineering and Physics*, vol. 33, pp. 1079–1085, nov 2011.

[29] R. G. Molinari, F. R. Santos, and L. A. Elias, ''Quality assessment of high-density surface myoelectric recordings from a new wearable electrophysiological signal acquisition and processing system for human-machine interfaces,'' in *XXIX Congresso Brasileiro de Engenharia Biomédica*, pp. 728–729, 2024.

[30] G. L. Cerone, A. Botter, and M. Gazzoni, ''A modular, smart, and wearable system for high density sEMG detection,'' *IEEE Transactions on Biomedical Engineering*, vol. 66, no. 22, pp. 3371–3380, 2019.

[31] S. Koutsoftidis, D. Y. Barsakcioglu, K. Petkos, D. Farina, and E. M. Drakakis, ''Myolink: A 128-Channel, 18 nV/$\sqrt{Hz}$, Embedded Recording System, Optimized for High-Density Surface Electromyogram Acquisition,'' *IEEE Transactions on Biomedical Engineering*, vol. 69, pp. 3389–3396, nov 2022.

[32] T. Stuart, J. Hanna, and P. Gutruf, ''Wearable devices for continuous monitoring of biosignals: Challenges and opportunities,'' *APL Bioengineering*, vol. 6, no. 2, pp. 1–15, 2022.

[33] P. Gkonis, A. Giannopoulos, P. Trakadas, X. Masip-Bruin, and F. D'Andria, ''A Survey on IoT-Edge-Cloud Continuum Systems: Status, Challenges, Use Cases, and Open Issues,'' *Future Internet*, vol. 15, no. 12, pp. 1–27, 2023.

[34] H. Bernhard, H. Seyhan, M. Wagner, and Z. Rainer, *Hand and Wrist anatomy and Biomechanics - A Comprehensive Guide*. Thieme, frist edit ed., 2016.

[35] M. Porta, C. Filetti, A. Chiari, I. Leo, E. Padua, G. Briotti, G. Messina, W. Moalla, and B. Ruscello, ''Examining the association between speed and myoelectric activity: Time-based differences and muscle group balance,'' *PLOS ONE*, vol. 19, 2024.

[36] E. J. Weiss and M. Flanders, ''Muscular and postural synergies of the human hand,'' *Journal of Neurophysiology*, vol. 92, no. 1, pp. 523–535, 2004.

[37] S. Tanzarella, S. Muceli, A. Del Vecchio, A. Casolo, and D. Farina, ''Non-invasive analysis of motor neurons controlling the intrinsic and extrinsic muscles of the hand,'' *Journal of Neural Engineering*, vol. 17, aug 2020.

[38] E. Martinez-Valdes, F. Negro, D. Falla, A. M. De Nunzio, and D. Farina, ''Surface electromyographic amplitude does not identify differences in neural drive to synergistic muscles,'' *Journal of Applied Physiology*, vol. 124, no. 4, pp. 1071–1079, 2018.

[39] W. A. Gardner, ''The spectral correlation theory of cyclostationary time-series,'' *Signal Processing*, vol. 11, no. 1, pp. 13–36, 1986.

[40] E. Efimov, ''On the Effect of a Signal Delay on Cross-Spectral Correlation Function,'' *2022 Systems of Signals Generating and Processing in the Field of on Board Communications, SOSG 2022 - Conference Proceedings*, vol. 2, pp. 1–6, 2022.

RICARDO G. MOLINARI received the Ph.D. degree in Electrical Engineering from the University of Campinas (UNICAMP), Brazil, in 2025. He is currently a Postdoctoral Researcher at the Center for Biomedical Engineering, UNICAMP. He also holds an M.Sc. in Electrical Engineering (2021) and a B.Eng. in Control and Automation Engineering (2020) from UNICAMP, and previously earned a B.Eng. in Civil Engineering from São Paulo State University (UNESP, 2010). His research focuses on computational neuroscience, biological signal processing, and the development of assistive technologies for motor rehabilitation. His work integrates high-density surface electromyography, multiscale neuromuscular modeling, and real-time embedded systems for proportional and simultaneous control of upper-limb prostheses.

VALERIA AVILÉS-CARRILLO received the B.S. degree in Mechatronics Engineering from the Universidad Militar Nueva Granada (UMNG), Bogotá, Colombia, in 2021, and an M.S. degree in Mechanical Engineering from the University of Campinas (UNICAMP), Brazil, in 2023. She is currently pursuing a Ph.D. degree in Electrical Engineering at UNICAMP under the supervision of Prof. Leonardo Abdala Elias. From 2021 to 2022, she worked as a Research Assistant at UMNG, where she developed simulation and implementation of advanced control strategies for a hexacopter-type unmanned aerial vehicle. Her research interests include mechatronics, robotics, control systems, and biomedical engineering, with a focus on human–machine interfaces.

GUILHERME A. G. DE VILLA received the B.S. degree in Electrical Engineering from the Federal University of Goiás, Brazil, in 2016, and the M.S. and Ph.D. degrees in Electrical and Computer Engineering from the same institution in 2019 and 2023, respectively. He completed postdoctoral training in Biomedical Engineering at the University of Campinas (UNICAMP), Brazil, in 2025. Since 2025, he has been an Assistant Professor at the State University of Goiás. Dr. De Villa has authored several articles and book chapters in biomechanics and biomedical engineering. His research interests include neuromechanical modeling of human movement, biomechanical signal processing, coordination variability analysis, nonlinear motor control dynamics, and neuroengineering approaches for orthotic and prosthetic device development.

LEONARDO A. ELIAS (M'24) received the Ph.D. degree in Biomedical Engineering from the University of São Paulo, Brazil, in 2013. He was a Postdoctoral Fellow at the Biomedical Engineering Laboratory, University of São Paulo (2013-2014), and a Visiting Researcher at the Department of Neurorehabilitation Engineering, Georg-August University (Goettingen, Germany, 2015). He is currently an Associate Professor at the Department of Electronics and Biomedical Engineering, School of Electrical and Computer Engineering, University of Campinas. He is the Founder Director of the Neural Engineering Research Laboratory at the Center for Biomedical Engineering, University of Campinas. His research in neural engineering focuses on theoretical and computational, as well as experimental, investigations that aim to understand how different elements of the neuromusculoskeletal system interact during normal and pathological control of human movement. Additionally, based on basic research, his group designs new technologies for motor neurorehabilitation of patients with neurological disorders and amputees. He is a Research Productivity Fellow of CNPq (Brazilian National Science Foundation). He is a member of the International MotoNeuron Society, the IEEE Engineering in Medicine and Biology Society, the Brazilian Society for the Progress of Science, and the Brazilian Society of Biomedical Engineering. He is a member of the Board of Reviewing Editors of the eLife journal.

· · ·