The impact of EEG preprocessing parameters on ultra-low-power seizure detection

Patrick Reisinger[1*], Jonathan Larochelle[2], Ciamak Abkai[1], Sotirios Kalousios[3,4], Nico Zabler[2,3,4], Matthias Dümpelmann[2,3,4], Andreas Schulze-Bonhage[3,4], Peter Woias[2], Laura Comella[2,5]

[1]Precisis GmbH, Research & Development, Heidelberg, Germany

[2]Department of Microsystems Engineering - IMTEK, University of Freiburg, Freiburg, Germany

[3]Epilepsy Center, Department of Neurosurgery, Medical Center — University of Freiburg, Faculty of Medicine, University of Freiburg, Freiburg, Germany

[4]BrainLinks-BrainTools, Freiburg, Germany

[5]Faculty for Mechanical Engineering and Mechatronics, Karlsruhe University of Applied Sciences, Karlsruhe, Germany

*Corresponding author: p.reisinger@precisis.de

Conflict of interest statement

PR and CA are employees of Precisis GmbH. ASB has received research support and personal honoraria for lectures and advice from Precisis GmbH. The remaining authors have no conflicts of interest.

Funding statement

This work was supported by the German federal state of Baden-Württemberg, through the Invest BW Project "Brain-MEP" (BW1_1276/03).

Data availability statement

The data and code to reproduce figures and statistics are available at GitHub (https://github.com/reispat/impact_preproc_seizure_detection).

Abstract

Objective

Closed-loop neurostimulation is a promising treatment for drug-resistant focal epilepsy. A major
challenge is fast and reliable seizure detection via electroencephalography (EEG). While many
approaches have been published, they often lack statistical power and practical utility. The use of
various EEG preprocessing parameters and performance metrics hampers comparability.
Additionally, the critical issue of energy consumption for an application in medical devices is rarely
considered. Addressing these points, we present a systematic analysis on the impact of EEG
preprocessing parameters on seizure detection performance and energy consumption, using one
to four EEG channels.

Methods

We analyzed in 145 patients with focal epilepsy the impact of different sampling rates, window
sizes, digital resolutions and number of EEG channels on seizure detection performance and
energy consumption. Focusing on clinically relevant, event-based metrics, we evaluated seizure
detection performance of a state-of-the-art convolutional neural network (CNN) via the Seizure
Community Open-Source Research Evaluation (SzCORE) framework. Statistical relevance of
parameter changes was assessed using linear mixed-effects models. Energy consumption was
analyzed using an ultra-low-power microcontroller.

Results

Reducing the sampling rate from 256 to 64 Hz led to a decrease in sensitivity ($p = .015$) and false
detections per hour (FD/h; $p = .002$). Larger window sizes reduced sensitivity between 1 and 8
second windows ($p = .033$) and FD/h between one second and all other sizes (all p values $< .001$).
Average detection delays increased between one second and 4 and 8 second windows (both $p <$
$.01$). Lower digital resolutions decreased sensitivity between 16 and 8 bits ($p = .007$). Compared
to four channels, using only one EEG channel resulted in a decrease in sensitivity ($p < .001$) and
an increase in the average detection delay ($p = .020$), but showed less FD/h ($p = .005$). CNN
energy consumption decreased from 49.15 to 17.26 µJ/s when the sampling rate was reduced
from 256 to 64 Hz. Lowering the number of channels from four to one reduced the CNN energy
consumption from 79.04 to 31.63 µJ/s.

Significance

This study provides guidance on choosing EEG preprocessing parameters for innovative
developments of closed-loop neurostimulation devices to further advance the treatment of drug-
resistant focal epilepsy.

Key points

● A major challenge in closed-loop neurostimulation is fast and reliable seizure detection,
ideally with minimal energy consumption.
● Many published seizure detection approaches are not ready for application and lack statistical
power and comparability.
● The impact of EEG preprocessing parameters was systematically evaluated in 145 patients
with focal epilepsy.
● The chosen window size and number of channels had the strongest impact on seizure
detection performance and energy consumption.
● Our results offer guidance for EEG preprocessing choices to advance the treatment of drug-
resistant focal epilepsy.

Keywords: Drug-resistant focal epilepsy, Closed-loop neurostimulation, Seizure detection, EEG,
Neural networks, Energy consumption

Introduction

In children and adults with epilepsy, focal epilepsy is the most common form (1), which places a great burden on those affected, caregivers and healthcare systems (2). Although there are several antiseizure medications on the market, one third of individuals with epilepsy show drug-resistance (3,4), with higher prevalence in focal epilepsy (5). An alternative therapy option for drug-resistant focal epilepsy is neurostimulation, where invasive approaches such as vagus nerve stimulation (VNS), deep brain stimulation (DBS) and responsive neurostimulation (RNS) exist (6,7). A novel, minimally invasive approach is the EASEE® system (Precisis GmbH, Heidelberg, Germany), where a thin electrode is placed subcutaneously over the epileptic focus (8,9). In order to improve therapeutic efficacy, closed-loop capabilities are increasingly considered in neurostimulation devices (10).

One major challenge in closed-loop neurostimulation is fast and reliable seizure detection, in order to trigger stimulation pulses, which could prevent the further spread or even the onset of seizures (11,12). Over the last decades, seizure detection based on electroencephalography (EEG) data with annotated seizures has been extensively studied (13–16). The most common approaches are deep learning techniques such as convolutional (17) or recurrent neural networks (18), as well as machine learning algorithms such as random forest (19). These algorithms are usually trained and evaluated with a patient-specific approach, because of its higher performance compared to a patient-generic approach (20).

However, many of these approaches are not ready to use in a neurostimulation device. First, only a small number of EEG channels can be used for detection, since constantly wearing an EEG cap is impractical and stigmatizes the patient (21). Although there are many minimally visible EEG devices on the market (22), a fully implanted device is often more suitable for closed-loop neurostimulation, such as DBS where subcortical brain regions are targeted (10). Next, the power consumption of seizure detection models is usually not investigated, although battery lifetime is one of the central factors enabling seizure detection on ultra-low-power devices (20). Extending the battery lifetime decreases the frequency of surgical procedures required for device replacement, thereby reducing both healthcare costs and patient risk (23). Furthermore, most seizure detection models are evaluated using the openly available CHB-MIT Scalp EEG Database, consisting of EEG recordings from a small group of 22 pediatric patients (24,25). Since epileptic seizures have different EEG characteristics in children (26), generalizability of results obtained with this database to adult patients is limited. Many publications use conventional

sample-based evaluation metrics, which tend to show high performance in imbalanced datasets (27). While these studies provide valuable insights, it is advisable to use evaluation metrics that incorporate enhanced clinical and practical relevance. For real-world applications, an event-based approach such as the recently proposed Seizure Community Open-Source Research Evaluation framework (SzCORE) is therefore more suitable (28). Furthermore, appropriate statistical testing is seldom applied when comparing different models (29) and statistical power is in general reduced when using the small CHB-MIT database. In addition to that, many variations of EEG preprocessing parameters are used and only a limited number of studies investigated their impact on seizure detection performance and energy consumption (20,30). Commonly varied parameters are window size (31), sampling rate (32) and number of channels (33). To our best of knowledge, no work exists that evaluates the effects of varying the digital resolution of EEG data.

Here, we systematically analyze the impact of different EEG preprocessing parameters on patient-specific seizure detection performance and energy consumption in a large group of 145 patients with focal epilepsy (Figure 1). We deployed a state-of-the-art convolutional neural network on an ultra-low-power microcontroller and statistically tested the impact of different sampling rates, window sizes, digital resolutions and number of channels using linear mixed-effects models. We show that ultra-low-power seizure detection is feasible with low sampling rates, small window sizes, low digital resolutions, as well as using only one EEG channel. All analyzed parameters had their own unique impact on seizure detection performance and energy consumption. The overall goal of this study is to provide guidance on the choice of EEG preprocessing parameters for the development of closed-loop neurostimulation to further advance the treatment of drug-resistant focal epilepsy.

A) EEG data

EASEE®   Scalp EEG   Time (s)

B) Seizure detection model

Quantized model

C) Preprocessing parameters

Sampling rate

Window size

Digital resolution

Number of channels

D) Metrics

Seizure detection performance

Energy consumption

Figure 1. Overview of study and analysis rationale. (A) To mimic the electrode of the EASEE® system,
scalp EEG data is reduced to a central channel at the epileptic focus and its four closest channels. Example
EEG data with an annotated seizure is shown for four channels re-referenced to the central channel. (B) A
convolutional neural network (CNN) is used for seizure detection, which is quantized in order to be executed
on a microcontroller. (C) Examples of the different used sampling rates, window sizes, digital resolutions
and numbers of channels from the highest to the lowest value. (D) Seizure detection performance was
evaluated using event-based scoring, with a focus on sensitivity, detection delay and false detections per
hour. CNN energy consumption was measured across each varied parameter and analog to digital
converter (ADC) energy was estimated.

Materials & Methods

The following is an abbreviated description. Further details for each section can be found in the supplementary material.

EEG database and preprocessing

We used surface EEG recordings of the EPILEPSIAE database (34) from a total of 150 patients with focal epilepsy (35). General EEG preprocessing was done using MNE-Python (36) and custom scripts. When necessary, the EEG data was downsampled to 256 Hz. To remove the DC offset and power line noise, a bandpass filter was applied between 0.5 and 48 Hz. A previous study demonstrated that sub-scalp EEG recorded via the electrode of the EASEE® system is highly similar to surface EEG recordings (37). To mimic the electrode configuration of the EASEE® system with the surface EEG data used in this study (38), the number of electrodes was reduced to one central and four additional peripheral electrodes covering the seizure onset zone (see Figure 1A). Subsequently, the data was re-referenced to the central electrode, resulting in four EEG channels.

Seizure detection model

Seizure detection was modeled as a binary classification task and trained using TensorFlow and Keras. We adapted *EpiDeNet* (39), a lightweight seizure detection convolutional neural network (CNN). A model using 2-channel EEG with a sampling rate of 256 Hz, a window size of one second (with 0% overlap) and a digital resolution of 16 bits served as reference for comparison (see Table 1). For computational reasons, we only changed the preprocessing parameters in one dimension and compared them with the other parameters investigated in the corresponding dimension.

Block	Type	Number of filters	Kernel	Output
0	Input			1024, 2, 1
1	Conv2D + BatchNorm + ReLU	4	4, 1	1024, 2, 4
	MaxPooling2D + Dropout (20%)		8, 1	128, 2, 4
2	Conv2D + BatchNorm + ReLU	16	16, 1	128, 2, 16
	MaxPooling2D + Dropout (20%)			32, 2, 16
3	Conv2D + BatchNorm + ReLU	16	8, 1	32, 2, 16

	MaxPooling2D + Dropout (20%)		4, 1	8, 2, 16
4	Conv2D + BatchNorm + ReLU	16	16, 1	8, 2, 16
	MaxPooling2D + Dropout (20%)		1, 2	
5	Conv2D + BatchNorm + ReLU	16	1, 8	8, 1, 16
	AveragePooling2D + Dropout (20%)		1, 8	1, 1, 16
6	Dense + Sigmoid			1

Table 1. CNN architecture adapted from EpiDeNet (39) for the baseline model of this study.

Since the focus of this study is on patient-specific models, time-series cross-validation is applied to preserve the chronological order of recordings and prevent performance overestimation (28). In each cross-validation step, the next chronological training data segment is added, and the subsequent segment is used as testing data for performance evaluation. This process was repeated until all segments were used per patient, which were on average 5.7 segments. Segments were one hour long and contained at least one seizure. All data was normalized based on a scaler (z-scoring) fitted using the training data. Additionally, the windowed training data and its corresponding labels were shuffled.

Sampling rate

Sampling rates of 256, 128, and 64 Hz were investigated to determine their impact on seizure detection and energy consumption. CNN parameters for 256 and 128 Hz were changed in the first input dimension, corresponding to the number of samples. When using a sampling rate of 64 Hz, kernel sizes were also adapted.

Window size

We also investigated different window sizes and their impact on seizure detection performance and energy consumption. In this study, we considered non-overlapping window sizes of 1, 2, 4, and 8 seconds. Additionally, windows with an overlap of 50% were also analyzed. CNN parameters were adapted in the first input dimension, ranging from 256 samples in 1 second to 2048 samples in 8 seconds.

Digital resolution

The digital resolution, in bits, is given by the EEG analog to digital converter (ADC) which samples
the analog raw signal. The data used for this study has a digital resolution of 16 bits. Digital
resolutions of 16, 14, 12, 10, and 8 bits were analyzed regarding their effects on seizure detection
performance and energy consumption. No adjustments of CNN parameters were conducted,
since the input sizes did not change compared to the baseline model.

Number of channels

Another major preprocessing parameter is the number of used EEG channels. In this study,
seizure detection performance and power consumption were evaluated using as few as one
channel and up to a maximum of four channels, all re-referenced to a central channel. We used
a pseudo-randomized scheme and labeled the initially selected four channels as E1 to E4. These
channels represent the closest four channels to the seizure onset zone within each participant.
When using three channels, we kept the channels with the labels E2, E3 and E4. When using two
channels, we kept E1 and E3. In the case of one channel, we trained and evaluated the models
for each patient using E1 to E4 once to minimize bias towards one of the channels. We report the
seizure detection performance metrics averaged across these four one-channel models. CNN
parameters were changed in the second input dimension, corresponding to the number of EEG
channels.

Seizure detection performance

For evaluating the performance of the seizure detection, we followed the guidelines and
recommendations of the recently proposed SzCORE framework (28). In this study, we focus on
event-based performance metrics that are more relevant for practical applications compared to
traditional sample-based metrics (40). Specifically, we analyzed sensitivity, false detections per
hour and average detection delay based on the averaged metrics obtained per patient. Since we
used a pre-ictal tolerance of up to 30 seconds, as advised by SzCORE, the average detection
delay can also be negative. Furthermore, the classification threshold that maximizes the F1 score
of the training data was chosen. All reported metrics are based on models quantized to 8 bits with
TensorFlow Lite to enable a more realistic performance evaluation for a neurostimulation
application.

 Energy consumption

To characterize the energy consumption, we consider the sum of ADC sample energy and CNN
energy. We measure the CNN energy on an EFR32MG24 microcontroller, which is able to
accelerate CNNs (Silicon Laboratories Inc., Austin, USA) and report it as mean CNN energy per
second. ADC energy cannot be trivially obtained, because different commercially available chips
are optimized for different digital resolutions and sampling rates. Therefore, it is estimated using
Boris Murmann's ADC Performance Survey (41) and reported as median ADC energy per second.
The corresponding interquartile ranges (IQR) and further details on CNN energy are reported in
the supplementary material.

Statistical analysis

To statistically compare the impact of preprocessing parameters on seizure detection
performance while accounting for the structure of the data, we calculated linear mixed-effects
models (LMMs) in R using the lmerTest package. The fixed effect for the preprocessing parameter
was entered into the model as an ordered factor, with 256 Hz as the reference value for the
sampling rate, 1 second for the window length, 16 bits for the digital resolution and 4 for the
number channels. For each model, we report regression coefficients (*β*) and p values (*p*),
separately for each statistically significant comparison with the reference value of the respective
preprocessing parameter. For all statistical tests, a significance level of α = .05 was used. Full
model metrics and additional post-hoc contrasts are reported in the supplementary material.

Results

From the initial 150 patients, five patients were excluded due to either too short seizure EEG data,
flat channels, incorrect timestamps or incomplete datasets. This resulted in a final sample size of
145 patients with a total data length of 2229 hours, including 1126 annotated seizures, equivalent
to 21 hours of seizure data. The reported seizure detection performance metrics are dependent
on the chosen threshold when an event is classified as a detection. Across all investigated
parameters, this classification threshold was on average 83.0%, with a standard deviation of
11.5%. Due to substantial interindividual variability in the seizure detection performance metrics,
median values are reported in the following sections (for detailed metrics see supplementary
tables S12-16).

 Impact of sampling rate

First, we compared the impact of using different sampling rates on sensitivity (Figure 2). Median

sensitivities for 256 Hz were 83.3%, 72.7% for 128 Hz and 66.7% for 64 Hz. There was a

significant difference from 256 Hz in 128 Hz ($β$ = -5.70, p = .008) and 64 Hz ($β$ = -5.16, p = .015).

Figure 2. Impact of sampling rate on performance metrics and energy consumption. The gray points

represent the individual patients. The error bars for ADC energy consumption represent the IQR. $^*p$ < .05,

$^{**}p$ < .01

Median false detections per hour were 5.6 FD/h for 256 Hz, 5.4 FD/h for 128 Hz and 4.4 FD/h for

64 Hz, with a significant difference between 256 Hz and 64 Hz ($β$ = -0.64, p = .002).

The average detection delay showed a median of 1.6 s when a sampling rate of 256 Hz was used.

With a sampling rate of 128 Hz, the average detection delay was -0.3 s and 3.0 s for 64 Hz. There

was no significant difference.

The variation of the sampling rate showed that the mean CNN energy consumption was 49.15

µJ/s for 256 Hz, 29.41 µJ/s for 128 Hz and 17.26 µJ/s for 64 Hz. The median ADC energy

consumption was 3.79 µJ/s when using 256 Hz, 1.89 µJ/s for 128 Hz and 0.95 µJ/s for 64 Hz.

Impact of window size

Next, we analyzed the impact of the chosen window size (Figure 3). The median sensitivity for 1

second windows was 83.3%, 75.0% for 2 seconds, 80.0% for 4 seconds and 66.7% for 8 seconds.

There was a significant difference in sensitivity when comparing the 1 second window size with 8

seconds ($β$ = -4.06, p = .033).

Figure 3. Impact of window size with 0% overlap on performance metrics and energy consumption. The gray points represent the individual patients. The error bars for ADC energy consumption represent the IQR. *$p < .05$, **$p < .01$, ***$p < .001$

We observed a major impact of increased window sizes on false detections per hour, with a subsequent median reduction from 5.6 FD/h for 1 second, 4.1 FD/h for 2 seconds, 3.2 FD/h for 4 seconds and 2.5 FD/h for 8 seconds. There was a significant difference between 1 second windows and 2 seconds (β = -1.31, $p < .001$), 4 seconds (β = -2.20, $p < .001$) and 8 seconds (β = -2.73, $p < .001$).

With larger windows, the average detection delay increased from a median of 1.6 s in 1 second to 3.9 s in 2 seconds, 7.2 s in 4 seconds and 8.0 s in 8 seconds. There was a statistically significant difference between 1 second and 4 seconds (β = 6.41, $p = .005$) and 8 seconds (β = 7.27, $p = .001$).

While mean CNN energy consumption was 49.15 µJ/s in 1 second, 41.33 µJ/s in 2 seconds and 36.80 µJ/s in 4 seconds, a window size of 8 seconds exceeded the input size of the CNN accelerator and therefore led to a consumption of 91.34 µJ/s. ADC energy consumption was 3.79 µJ/s for all window sizes.

Compared to non-overlapping windows, using a 50% overlap led to an increase in sensitivity and a decrease in the average detection delay (Figure S1 and Table S14). The CNN and ADC energy consumption increased by up to twofold (Table S4 and S9).

Impact of digital resolution

When using different digital resolutions (Figure 4), median sensitivity was 83.3% for 16 bits, 80.0%
for 14 bits, 82.4% for 12 bits, 75.0% for 10 bits and 69.2% for 8 bits. There was a significant
difference between 16 and 8 bits (β = -4.22, p = .007).

Figure 4. Impact of digital resolution on performance metrics and energy consumption. The gray points
represent the individual patients. The error bars for ADC energy consumption represent the IQR. *p < .05,
**p < .01

False detections per hour showed median values of 5.6 FD/h for 16, 14, 10 and 8 bits and 5.7
FD/h for 12 bits. There was no significant difference.

When analyzing the average detection delay along decreased digital resolutions, it showed a
median of 1.6 s for 16 bits, -3.7 s for 14 bits, -1.3 s for 12 bits, -3.5 s for 10 bits and -1.0 s for 8
bits. There was a significant difference between 16 bits and 14 bits (β = -3.90, p = .041).

Different digital resolutions only had a negligible impact on mean CNN energy consumption with
49.15 µJ/s for 16 bits, 49.45 µJ/s for 14 bits, 49.49 µJ/s for 12 bits, 49.77 µJ/s for 10 bits and
49.39 µJ/s for 8 bits. The estimated ADC energy showed a consumption of 3.79 µJ/s for 16 bits,
0.61 µJ/s for 14 bits, 0.19 µJ/s for 12 bits, 0.37 µJ/s for 10 bits and 0.28 µJ/s for 8 bits.

Impact of number of channels

In a final step, we analyzed the impact of the used number of channels on seizure detection
performance (Figure 5). Four channels showed a median sensitivity of 100.0%, followed by 85.7%
for three channels, 83.3% for two channels and 75.0% for one channel. There was a significant

difference between four channels and both two channels (β = -8.10, p < .001) and one channel
(β = -9.06, p < .001).

Figure 5. Impact of number of channels on performance metrics and energy consumption. The gray points
represent the individual patients. The error bars for ADC energy consumption represent the IQR. *p < .05,
***p < .001

The false detections per hour showed a median value of 5.8 FD/h for four channels and 5.6 FD/h
for three and two channels. Using one channel showed a median of 5.4 FD/h. A significant
difference was found when comparing four channels with three channels (β = -0.35, p = .045),
two channels (β = -0.41, p = .020) and one channel (β = -0.49, p = .005).

The average detection delay showed a median of -2.5 s when using four channels, -2.8 s for three
channels, 1.6 s for two channels and 0.5 s for one channel. There was a significant difference
between four channels and both two (β = 4.58, p = .014) and one channel (β = 4.25, p = .020).

CNN power consumption was majorly affected by using different numbers of channels, with four
channels showing a median of 79.04 µJ/s, followed by 64.22 µJ/s for three channels, 49.15 µJ/s
for two channels and 31.63 µJ/s for one channel. This was also the case for ADC energy, where
the median consumption was 7.58 µJ/s for four channels, 5.68 µJ/s for three channels, 3.79 µJ/s
for two channels and 1.89 µJ/s for one channel.

Discussion

Fast and reliable seizure detection has the potential to improve the efficacy of all currently available EEG-based neurostimulation devices that treat drug-resistant focal epilepsy, in order to reduce seizure frequency or even completely suppress seizures (10). In the current literature, many approaches were published with a wide range of detection frameworks with varying complexity and preprocessing strategies, primarily evaluated using a small number of patients (17,42). In our work, we address current limitations by 1) using an energy-efficient neural network, 2) systematically investigating the impact of EEG preprocessing parameters and 3) evaluating the performance with a large group of patients.

We chose a patient-specific seizure detection approach because it generally shows better seizure detection performance compared to patient-generic or hybrid approaches. However, a patient-specific approach involves a higher implementation effort (43), since seizure detection models need to be trained with previously collected, patient-specific EEG data, where seizures are either manually marked by experts or automatically marked by seizure detection models (44), which then also need to be validated by experts. Future research should focus on advancing approaches that are not entirely dependent on patient-individual EEG data, since they could reach market readiness faster and thus help patients in a more timely manner.

All seizure detection results are dependent on the chosen classification threshold (45). However, only a limited number of studies report on how the chosen thresholds were determined (46,47). In this study, we report all parameter choices in order to enhance transparency and comparability. We also observed a large interindividual variability in all evaluated seizure detection metrics. One possible reason could be differences in data quality, an issue that has previously been investigated when using wearables for seizure monitoring (48). Data quality can be improved by using a second model for artifact detection (49). However, including more advanced preprocessing techniques usually leads to an increased energy consumption. The evaluation of this tradeoff should be the subject of future research.

Lowering the sampling rate showed a decrease in sensitivity. Interestingly, there was also a decrease in FD/h, which could be due to lower signal complexity. No significant impact on the average detection delay was observed, indicating that this metric is robust to lower sampling rates. When compared to previous studies that used 256 Hz, our results show a substantial improvement in the average detection delay and FD/h (46). However, comparability is limited since the metrics were not calculated as proposed by the SzCORE framework. In a closed-loop

neurostimulation approach, lowering the sampling rate can reduce energy consumption by over
60% while maintaining reasonable seizure detection performance.

The metric with the strongest overall impact on seizure detection performance and energy
consumption was the chosen window size. When using both non-overlapping and overlapping
windows, sensitivity especially decreased when the window size was prolonged to 8 seconds.
Larger window sizes also led to a substantial reduction in FD/h, which goes in line with a previous
work that compared similar window sizes using sample-based performance metrics (20). In
contrast, longer windows significantly increased the average detection delay. A previously
proposed model named *SeizureNet* used a window size of 1 second with 50% overlap to obtain
a median sensitivity of 96%, 10.1 FD/h and an average detection delay of 3.7 seconds (50). Apart
from a slightly higher median sensitivity of 100%, our approach shows substantially lower values
regarding FD/h and average detection delay. However, comparability is limited since intracranial
EEG data from 22 EPILEPSIAE patients was used. For 8 second windows with and without an
overlap, CNN energy consumption was substantially larger, since the maximum CNN accelerator
input size of the used microcontroller was exceeded. Using a different microcontroller can resolve
this limitation (39). Overall, larger window sizes can especially be useful for applications where
FD/h should be minimized, such as wearables that warn the patient on upcoming seizures (31).

Using different digital resolutions only had a small impact on the three seizure detection
performance metrics of interest. This can be explained to the applied quantization level of the
CNN, where the input data and model weights are always reduced to a digital resolution of 8 bits.
A recent study used different CNN quantization levels, where a reduction in performance was
only observed when using digital resolutions of less than 8 bits (51). However, the used datasets
also included intracranial EEG recordings from non-human subjects, which limits comparability
with our work. We observed a significant difference in sensitivity between 16 and 8 bits and in the
average detection delay between 16 and 14 bits. This suggests that reducing the digital resolution
has to some extent an impact on seizure detection performance. Minor, non-significant
fluctuations were observed in the FD/h. Due to the model quantization, the impact on CNN energy
consumption was only negligible. In contrast, ADC energy consumption is reduced when using
digital resolutions smaller than 16 bits, which has implications on the choice of a suitable ADC for
designing a closed-loop neurostimulation device.

Usually, all available EEG channels are used for seizure detection (17,43). It is important to
highlight that previous studies used computational approaches to identify optimal channel

combinations (52) or systematically reduced the number of channels (53), using standard EEG

setups as a basis. However, they used non-CNN approaches and only reported sample-based

performance metrics, which limits comparability with our work. Since standard EEG setups with

many channels are not practicable for a closed-loop neurostimulation device, studies also

explored the use of CNNs with a smaller number of channels and reduced them to up to two

channels (33,46). To the best of our knowledge, this work represents the first systematic analysis

on the effects of reducing the number of channels from four to only one channel in a CNN-based

ultra-low power application. As expected, sensitivity was highest when using four channels and

was subsequently reduced when lowering the number of channels. Interestingly, FD/h were

minimally reduced when lowering the number of channels and the average detection delay

increased when using two or one channel. This could be due to a reduced complexity of the model

input. Since we only used channels that cover the seizure onset zone, they are spatially close

and thus share mutual information (54). Furthermore, the four channels were always re-

referenced to a central channel that was determined in the selection procedure and subsequently

reduced afterwards (38). In future studies, the effects of different re-referencing schemes (55) on

seizure detection performance should be explored. An important aspect in the choice of the

number of channels is power consumption, where we observed a major reduction in CNN and

ADC energy when reducing the number of channels. Overall, we confirm and extend the findings

of previous studies that a small number of channels is sufficient for performing reliable ultra-low-

power seizure detection, provided that they are close to the seizure onset zone.

In the context of closed-loop neurostimulation, systems such as RNS triggered 600 to 2000

stimulations per day in patients which participated in clinical trials (56). Given that our approach

showed in individual patients up to 14.1 FD/h, corresponding to 338.4 false detections per day, it

would trigger substantially fewer daily stimulations. This also leads to a significant reduction in

energy consumption. However, when it is crucial to minimize FD/h, such as in wearables that alert

users of potential upcoming seizures (31), further research is needed to reduce FD/h while

maintaining low energy consumption.

To our best of knowledge, the microcontroller used in this study has never been used in the

literature. A previous study (46) estimated CNN energy consumption on a low-power

microcontroller, which does not possess a CNN accelerator. With a window size of 1 second and

4 EEG channels, the model required approximately 243 µJ per detection. For similar conditions,

our model required 67% less CNN energy. Another study (30) implemented a CNN on a non-

accelerated microcontroller using a 1 second window size and 9 EEG channels. They reported a

CNN energy consumption of approximately 215 μJ, which corresponds to 24 μJ/channel. We
measured a mean CNN energy of 79 μJ with a non-overlapping window size of 1 second and 4
channels of EEG, which corresponds to 20 μJ/channel. Another limitation of our energy
consumption investigation is that only the ADC and CNN energy were considered. Data
preprocessing is also expected to have a non-negligible energy cost. However, to the best of our
knowledge, the present study is the first work in the context of seizure detection which takes into
consideration the ADC energy. This inclusion has shown to be important for the characterization
of the impact of digital resolution, because the CNN energy did not vary substantially while the
ADC energy was affected.

Conclusion

This study represents the first systematic analysis on the impact of EEG preprocessing on seizure
detection in the context of an ultra-low-power application. We show that seizure detection
performance and energy consumption are especially influenced by the chosen window size and
number of channels. Our study applies a novel event-based evaluation framework on a large
dataset, where we show that seizure detection can be performed with detection delays below one
second. We address common issues in the current literature and offer guidance on the selection
of appropriate EEG preprocessing parameters for closed-loop neurostimulation approaches.
These insights should ultimately support in providing more effective treatment options for patients
with drug-resistant focal epilepsy.

Author contributions

PR: Conceptualization, Data curation, Formal Analysis, Investigation, Methodology, Software,
Visualization, Writing – original draft, Writing – review & editing; JL: Data curation, Formal
Analysis, Methodology, Resources, Software, Validation, Writing – original draft, Writing – review
& editing; CA: Conceptualization, Funding acquisition, Project administration, Supervision, Writing
– original draft, Writing – review & editing; SK: Conceptualization, Validation, Writing – review &
editing; NZ: Conceptualization, Validation, Writing – review & editing; MD: Data curation,
Methodology, Resources, Writing – review & editing; ASB: Funding acquisition, Supervision,
Writing – review & editing; PW: Funding acquisition, Supervision, Writing – review & editing; LC:
Funding acquisition, Supervision, Writing – review & editing

Ethical publication statement

We confirm that we have read the Journal's position on issues involved in ethical publication and
affirm that this report is consistent with those guidelines.

References

1. Nascimento FA, Friedman D, Peters JM, Bensalem-Owen MK, Cendes F, Rampp S, et al.
    Focal epilepsies: Update on diagnosis and classification. Epileptic Disord. 2023;25(1):1–17.

2. Ioannou P, Foster DL, Sander JW, Dupont S, Gil-Nagel A, Drogon O'Flaherty E, et al. The
    burden of epilepsy and unmet need in people with focal seizures. Brain Behav.
    2022;12(9):e2589.

3. Perucca E, Brodie MJ, Kwan P, Tomson T. 30 years of second-generation antiseizure
    medications: impact and future perspectives. Lancet Neurol. 2020 Jun 1;19(6):544–56.

4. Perucca E, Perucca P, White HS, Wirrell EC. Drug resistance in epilepsy. Lancet Neurol.
    2023 Aug 1;22(8):723–34.

5. Kalilani L, Sun X, Pelgrims B, Noack-Rink M, Villanueva V. The epidemiology of drug-
    resistant epilepsy: A systematic review and meta-analysis. Epilepsia. 2018 Dec
    1;59(12):2179–93.

6. Ryvlin P, Rheims S, Hirsch LJ, Sokolov A, Jehi L. Neuromodulation in epilepsy: state-of-the-
    art approved therapies. Lancet Neurol. 2021 Dec 1;20(12):1038–47.

7. Skrehot HC, Englot DJ, Haneef Z. Neuro-stimulation in focal epilepsy: A systematic review
    and meta-analysis. Epilepsy Behav. 2023 May;142:109182.

8. Schulze-Bonhage A. Long-term outcome in neurostimulation of epilepsy. Epilepsy Behav.
    2019 Feb;91:25–9.

9. Schulze-Bonhage A, Hirsch M, Knake S, Kaufmann E, Kegele J, Rademacher M, et al.
    Focal Cortex Stimulation With a Novel Implantable Device and Antiseizure Outcomes in 2
    Prospective Multicenter Single-Arm Trials. JAMA Neurol. 2023 Apr 3;

10. Sun FT, Morrell MJ. Closed-loop Neurostimulation: The Clinical Experience.

Neurotherapeutics. 2014 May;11(3):553–63.

11. Schulze-Bonhage A, Nitsche MA, Rotter S, Focke NK, Rao VR. Neurostimulation targeting
the epileptic focus: Current understanding and perspectives for treatment. Seizure Eur J
Epilepsy. 2024 Mar 1;117:183–92.

12. Dümpelmann M. Early seizure detection for closed loop direct neurostimulation devices in
epilepsy. J Neural Eng. 2019 May;16(4):041001.

13. Baumgartner C, Koren JP. Seizure detection using scalp-EEG. Epilepsia. 2018;59(S1):14–
22.

14. Kerr WT, McFarlane KN, Figueiredo Pucci G. The present and future of seizure detection,
prediction, and forecasting with machine learning, including the future impact on clinical
trials. Front Neurol. 2024 Jul 11;15.

15. Ramgopal S, Thome-Souza S, Jackson M, Kadish NE, Fernández IS, Klehm J, et al.
Seizure detection, seizure prediction, and closed-loop warning systems in epilepsy. Epilepsy
Behav. 2014 Aug 1;37:291–307.

16. Shoeb A, Edwards H, Connolly J, Bourgeois B, Treves ST, Guttag J. Patient-specific
seizure onset detection. Epilepsy Behav. 2004 Aug 1;5(4):483–98.

17. Zhou M, Tian C, Cao R, Wang B, Niu Y, Hu T, et al. Epileptic Seizure Detection Based on
EEG Signals and CNN. Front Neuroinformatics. 2018 Dec 10;12.

18. Verma A, Janghel RR. Epileptic Seizure Detection Using Deep Recurrent Neural Networks
in EEG Signals. In: Rizvanov AA, Singh BK, Ganasala P, editors. Advances in Biomedical
Engineering and Technology. Singapore: Springer; 2021. p. 189–98.

19. Mursalin M, Zhang Y, Chen Y, Chawla NV. Automated epileptic seizure detection using
improved correlation-based feature selection with random forest classifier. Neurocomputing.
2017 Jun 7;241:204–14.

20. Ingolfsson TM, Cossettini A, Wang X, Tabanelli E, Tagliavini G, Ryvlin P, et al. Towards
Long-term Non-invasive Monitoring for Epilepsy via Wearable EEG Devices. In: 2021 IEEE
Biomedical Circuits and Systems Conference (BioCAS). 2021. p. 01–4.

21. Bleichner MG, Lundbeck M, Selisky M, Minow F, Jäger M, Emkes R, et al. Exploring
miniaturized EEG electrodes for brain-computer interfaces. An EEG you do not see? Physiol
Rep. 2015;3(4):e12362.

22. Biondi A, Santoro V, Viana PF, Laiou P, Pal DK, Bruno E, et al. Noninvasive mobile EEG as
a tool for seizure monitoring and management: A systematic review. Epilepsia.
2022;63(5):1041–63.

23. de Schlichting E, Coll G, Zaldivar-Jolissaint JF, Coste J, Marques AR, Mulliez A, et al. Pulse
generator battery life in deep brain stimulation: out with the old… in with the less durable?
Acta Neurochir (Wien). 2019 Oct 1;161(10):2043–6.

24. Goldberger AL, Amaral LAN, Glass L, Hausdorff JM, Ivanov PCh, Mark RG, et al.
PhysioBank, PhysioToolkit, and PhysioNet. Circulation. 2000 Jun 13;101(23):e215–20.

25. Shoeb A. Application of machine learning to epileptic seizure onset detection and treatment
[Thesis]. Massachusetts Institute of Technology; 2009.

26. Fine A, Wirrell EC. Seizures in Children. Pediatr Rev. 2020 Jul 1;41(7):321–47.

27. Thölke P, Mantilla-Ramos YJ, Abdelhedi H, Maschke C, Dehgan A, Harel Y, et al. Class
imbalance should not throw you off balance: Choosing the right classifiers and performance
metrics for brain decoding with imbalanced data. NeuroImage. 2023 Aug 15;277:120253.

28. Dan J, Pale U, Amirshahi A, Cappelletti W, Ingolfsson TM, Wang X, et al. SzCORE: Seizure
Community Open-Source Research Evaluation framework for the validation of
electroencephalography-based automated seizure detection algorithms. Epilepsia. 2024;

29. Rainio O, Teuho J, Klén R. Evaluation metrics and statistical tests for machine learning. Sci
Rep. 2024 Mar 13;14(1):6086.

30. Liu X, Richardson AG. Edge deep learning for neural implants: a case study of seizure
detection and prediction. J Neural Eng. 2021 Apr;18(4):046034.

31. Busia P, Cossettini A, Ingolfsson TM, Benatti S, Burrello A, Jung VJB, et al. Reducing False
Alarms in Wearable Seizure Detection with EEGformer: A Compact Transformer Model for
MCUs. IEEE Trans Biomed Circuits Syst. 2024;1–13.

32. Pan Y, Dong F, Wu J, Xu Y. Downsampling of EEG Signals for Deep Learning-Based
Epilepsy Detection. IEEE Sens Lett. 2023 Dec;7(12):1–4.

33. Hartmann M, Koren J, Baumgartner C, Duun-Henriksen J, Gritsch G, Kluge T, et al. Seizure
detection with deep neural networks for review of two-channel electroencephalogram.
Epilepsia. 2023 Dec;64(S4):S34–9.

34. Ihle M, Feldwisch-Drentrup H, Teixeira CA, Witon A, Schelter B, Timmer J, et al.
EPILEPSIAE – A European epilepsy database. Comput Methods Programs Biomed. 2012
Jun 1;106(3):127–38.

35. Klatt J, Feldwisch-Drentrup H, Ihle M, Navarro V, Neufang M, Teixeira C, et al. The
EPILEPSIAE database: An extensive electroencephalography database of epilepsy
patients: European EEG Database 'EPILEPSIAE.' Epilepsia. 2012 Sep;53(9):1669–76.

36. Gramfort A, Luessi M, Larson E, Engemann D, Strohmeier D, Brodbeck C, et al. MEG and
EEG data analysis with MNE-Python. Front Neurosci. 2013;7.

37. Dümpelmann M, Reinacher PC, Kravalis K, Jagschies L, Tittelbach M, Coenen VA, et al. A
subgaleal electrode array for neurostimulation allows the recording of relevant information in
closed loop applications. J Neurosci Methods. 2021 Oct 1;362:109295.

38. Manzouri F, Khurana L, Kravalis K, Stieglitz T, Schulze-Bonhage A, Dümpelmann M. An
Optimized EEG-Based Seizure Detection Algorithm for Implantable Devices. In: 2021 10th
International IEEE/EMBS Conference on Neural Engineering (NER). 2021. p. 995–8.

39. Ingolfsson TM, Chakraborty U, Wang X, Beniczky S, Ducouret P, Benatti S, et al. EpiDeNet:
An Energy-Efficient Approach to Seizure Detection for Embedded Systems. In: 2023 IEEE
Biomedical Circuits and Systems Conference (BioCAS). 2023.

40. Shah V, Golmohammadi M, Obeid I, Picone J. Objective Evaluation Metrics for Automatic
Classification of EEG Events. In: Obeid I, Selesnick I, Picone J, editors. Biomedical Signal
Processing: Innovation and Applications. Cham: Springer International Publishing; 2021. p.
223–55.

41. Murmann B. ADC Performance Survey 1997-2024 [Internet]. 2024. Available from:
https://github.com/bmurmann/ADC-survey

42. Shen M, Yang F, Wen P, Song B, Li Y. A real-time epilepsy seizure detection approach
based on EEG using short-time Fourier transform and Google-Net convolutional neural
network. Heliyon. 2024 Jun 15;10(11):e31827.

43. Sigsgaard GM, Gu Y. Improving the generalization of patient non-specific model for epileptic
seizure detection. Biomed Phys Eng Express. 2023 Dec;10(1):015010.

44. Tveit J, Aurlien H, Plis S, Calhoun VD, Tatum WO, Schomer DL, et al. Automated
Interpretation of Clinical Electroencephalograms Using Artificial Intelligence. JAMA Neurol.
2023 Aug 1;80(8):805–12.

45. Lyu J, Ishwaran H. Commentary: To classify means to choose a threshold. J Thorac
Cardiovasc Surg. 2023 Apr 1;165(4):1443–5.

46. Manzouri F, Zöllin M, Schillinger S, Dümpelmann M, Mikut R, Woias P, et al. A Comparison
of Energy-Efficient Seizure Detectors for Implantable Neurostimulation Devices. Front
Neurol. 2022;12.

47. Zhang Y, Yao S, Yang R, Liu X, Qiu W, Han L, et al. Epileptic Seizure Detection Based on
Bidirectional Gated Recurrent Unit Network. IEEE Trans Neural Syst Rehabil Eng.
2022;30:135–45.

48. Böttcher S, Vieluf S, Bruno E, Joseph B, Epitashvili N, Biondi A, et al. Data quality
evaluation in wearable monitoring. Sci Rep. 2022 Dec 10;12(1):21412.

49. Ingolfsson TM, Benatti S, Wang X, Bernini A, Ducouret P, Ryvlin P, et al. Minimizing artifact-
induced false-alarms for seizure detection in wearable EEG devices with gradient-boosted
tree classifiers. Sci Rep. 2024 Feb 5;14(1):2980.

50. Hügle M, Heller S, Watter M, Blum M, Manzouri F, Dümpelmann M, et al. Early Seizure
Detection with an Energy-Efficient Convolutional Neural Network on an Implantable
Microcontroller. In: 2018 International Joint Conference on Neural Networks (IJCNN). 2018.
p. 1–7.

51. Zhao S, Yang J, Sawan M. Energy-Efficient Neural Network for Epileptic Seizure Prediction.
IEEE Trans Biomed Eng. 2022 Jan;69(1):401–11.

52. Moctezuma LA, Molinas M. EEG Channel-Selection Method for Epileptic-Seizure

Classification Based on Multi-Objective Optimization. Front Neurosci [Internet]. 2020 Jun 17

[cited 2025 Mar 4];14. Available from:

https://www.frontiersin.org/journals/neuroscience/articles/10.3389/fnins.2020.00593/full

53. Chang NF, Chen TC, Chiang CY, Chen LG. Channel selection for epilepsy seizure

prediction method based on machine learning. In: 2012 Annual International Conference of

the IEEE Engineering in Medicine and Biology Society [Internet]. 2012 [cited 2025 Apr 14].

p. 5162–5. Available from: https://ieeexplore.ieee.org/document/6347156

54. Ramakrishnan AG, Satyanarayana JV. Reconstruction of EEG from limited channel

acquisition using estimated signal correlation. Biomed Signal Process Control.

2016;27:164–73.

55. Yao D, Qin Y, Hu S, Dong L, Bringas Vega ML, Valdés Sosa PA. Which Reference Should

We Use for EEG and ERP practice? Brain Topogr. 2019 Jul 1;32(4):530–49.

56. Skarpaas TL, Jarosiewicz B, Morrell MJ. Brain-responsive neurostimulation for epilepsy

(RNS ® System). Epilepsy Res. 2019 Jul 1;153:68–70.