1	**Title:**	Peripheral neural synchrony in post-lingually deafened adult
2		cochlear implant users

3	**Authors:**	Shuman He[1,3], MD, PhD; Jeffrey Skidmore[1], PhD; Ian C. Bruce[2],
4		PhD; Jacob J. Oleson[4], PhD; Yi Yuan[1], PhD

5	**Affiliations:**	[1]Department of Otolaryngology – Head and Neck Surgery, The
6		Ohio State University, 915 Olentangy River Road, Columbus, OH
7		43212
8		[2]Department of Electrical & Computer Engineering, McMaster
9		University, Hamilton, ON, L8S 4K1, Canada
10		[3]Department of Audiology, Nationwide Children's Hospital, 700
11		Children's Drive, Columbus, OH 43205
12		[4]Department of Biostatistics, The University of Iowa, Iowa City, IA
13		52242

14	**Correspondence:**	Shuman He, MD, PhD
15		Eye and Ear Institute
16		Department of Otolaryngology – Head and Neck Surgery
17		The Ohio State University
18		915 Olentangy River Road, Suite 4000
19		Phone: 614-293-5963
20		Fax: 614-293-7292
21		Email: Shuman.He@osumc.edu

22	**Conflict of Interest:**	None.

23   **Source of Funding:** This work was supported by grants from the National Institutes of

24   Health awarded to SH [grant numbers 1R01 DC016038, 1R01

25   DC017846, R21 DC019458] and a NSERC Discovery Grant

26   awarded to ICB [grant number RGPIN-2018-05778].

27   **Author Contributions:** SH designed this study, participated in data analysis, drafted

28   and approved the final version of this paper. JS participated in data

29   collection and data analysis, provided critical comments, and

30   approved the final version of this paper. IB participated in study

31   design, provided critical comments, and approved the final version

32   of this paper. JO conducted statistical analyses, provide critical

33   comments, and approved the final version of this paper. YY

34   participated in data collection, provided critical comments, and

35   approved the final version of this paper.

ABSTRACT

Objective: This paper reports a noninvasive method for quantifying neural synchrony in the cochlear nerve (i.e., peripheral neural synchrony) in cochlear implant (CI) users, which allows for evaluating this physiological phenomenon in human CI users for the first time in the literature. In addition, this study assessed how peripheral neural synchrony was correlated with temporal resolution acuity and speech perception outcomes measured in quiet and in noise in post-lingually deafened adult CI users. It tested the hypothesis that peripheral neural synchrony was an important factor for temporal resolution acuity and speech perception outcomes in noise in post-lingually deafened adult CI users.

Design: Study participants included 24 post-lingually deafened adult CI users with a Cochlear™ Nucleus® device. Three study participants were implanted bilaterally, and each ear was tested separately. For each of the 27 implanted ears tested in this study, 400 sweeps of the electrically evoked compound action potential (eCAP) were measured at four electrode locations across the electrode array. Peripheral neural synchrony was quantified at each electrode location using the phase locking value (PLV), which is a measure of trial-by-trial phase coherence among eCAP sweeps/trials. Temporal resolution acuity was evaluated by measuring the within-channel gap detection threshold (GDT) using a three-alternative, forced-choice procedure in a subgroup of 20 participants (23 implanted ears). For each ear tested in these participants, GDTs were measured at two electrode locations with a large difference in PLVs. For 26 implanted ears tested in 23 participants, speech perception performance was evaluated using Consonant-Nucleus-Consonant (CNC) word lists presented in quiet and in noise at signal-to-noise ratios (SNRs) of +10 and +5 dB. Linear Mixed effect Models were used to evaluate the

effect of electrode location on the PLV and the effect of the PLV on GDT after controlling

for the stimulation level effects. Pearson product-moment correlation tests were used to

assess the correlations between PLVs, CNC word scores measured in different

conditions, and the degree of noise effect on CNC word scores.

Results: There was a significant effect of electrode location on the PLV after controlling

for the effect of stimulation level. There was a significant effect of the PLV on GDT after

controlling for the effects of stimulation level, where higher PLVs led to lower GDTs. PLVs

were not significantly correlated with CNC word scores measured in any listening

condition or the effect of competing background noise presented at a SNR of +10 dB on

CNC word scores. In contrast, there was a significant negative correlation between the

PLV and the degree of noise effect on CNC word scores for a competing background

noise presented at a SNR of +5 dB.

Conclusions: This newly developed method can be used to assess peripheral neural

synchrony in CI users, a physiological phenomenon that has not been systematically

evaluated in electrical hearing. Poorer peripheral neural synchrony leads to lower

temporal resolution acuity and is correlated with a larger detrimental effect of competing

background noise presented at a SNR of 5 dB on speech perception performance in post-

lingually deafened adult CI users.

Key Words: cochlear implants, cochlear nerve, neural synchrony, speech perception,

temporal resolution acuity

INTRODUCTION

While many cochlear implant (CI) users can achieve excellent listening outcomes

in quiet, speech recognition in background noise remains a significant challenge

(Eisenberg et al., 2016; Torkildsen et al., 2019; Zaltz et al., 2020). The neural mechanisms

underlying the observed speech perception deficits in noise in CI users remain unknown.

In acoustic hearing, discharge synchronization of cochlear nerve (CN) fibers has been

shown to play a critical role in neural representation of speech sounds presented in noise

in animal models (e.g., Delgutte & Kiang, 1984; Heeringa & Koppl, 2022; Sachs et al.,

1983). Simulation results from computational models demonstrated the importance of

synchronized neural firing from CN fibers for robust encoding of consonants in spectro-

temporally modulated background noises (Bruce et al., 2013; Viswanathan et al., 2022).

These simulation results also showed that poor neural synchrony in the CN (i.e.,

peripheral neural synchrony) results in smeared neural representation of temporal

envelope cues, which leads to deficits in processing these cues (Zeng et al., 2005; Zeng

et al., 1999). Aligned with these results from animal models and computational

simulations, listeners with poor peripheral neural synchrony (e.g., patients with auditory

neuropathy spectrum disorder and elderly listeners) have temporal processing deficits

and show excessive difficulties in understanding speech in noise (e.g., Harris et al., 2021;

Kraus et al., 2000; Rance, 2005; Zeng et al., 2005). Overall, these results demonstrate

the importance of peripheral neural synchrony for temporal processing and speech

perception in noise in acoustic hearing.

Deteriorations in anatomical structures of the CN in CI patients have been well

established based on the histological results of human temporal bone studies (e.g., Di

Stadio et al., 2020; Fayad et al., 1991; Fayad & Linthicum, 2006; Heshmat et al., 2020;

Kumar et al., 2022; Kusunoki et al., 2004; Linthicum & Fayad, 2009; Makary et al., 2011;

Merchant et al., 2005; Nadol, 1990, 1997; Nadol et al., 1989; Rask-Andersen et al., 2010;

Suzuka & Schuknecht, 1988; Ungar et al., 2018; Wu et al., 2019; Xing et al., 2012). These

deteriorations start with damages in the myelin sheath and peripheral axon degeneration

(e.g., Heshmat et al., 2020; Kumar et al., 2022; Nadol, 1990; Wu et al., 2019; Xing et al.,

2012). Damaged spiral ganglion neurons (SGNs) with only central axons (i.e., unipolar

SGNs) can survive decades after peripheral axon loss (e.g., Kusunoki et al., 2004;

Linthicum & Fayad, 2009; Nadol, 1990; Rask-Andersen et al., 2010) and still be activated

by electrical stimulation (e.g., Javel & Shepherd, 2000; Shepherd & Hardie, 2001;

Shepherd & Javel, 1997; Sly et al., 2007; van den Honert & Stypulkowski, 1984).

Eventually, the SGN soma and the central axon degenerate, which leads to the

disappearance of the entire SGN (e.g., Fayad et al., 1991; Fayad & Linthicum, 2006;

Linthicum & Fayad, 2009; Suzuka & Schuknecht, 1988; Ungar et al., 2018). The number

and the distribution of surviving SGNs, the number of bipolar vs unipolar SGNs, as well

as the degree of axonal degeneration and demyelination of remaining SGNs, vary

substantially along the cochlea within and across CI patients (Fayad et al., 1991; Fayad

& Linthicum, 2006; Linthicum & Fayad, 2009; Merchant et al., 2005; Nadol, 1997).

Deteriorations in anatomical structures of the CN reduce its discharge

synchronization (i.e., neural synchrony). Specifically, both axonal dystrophy and

demyelination alter many neural properties, such as membrane capacitance and

resistance, nodal leakage resistance, as well as nodal sodium and potassium channel

permeability (e.g., Tasaki, 1955; Waxman & Ritchie, 1993). These changes cause a

reduction in the nodal current density, axonal spiking probability and propagation velocity,

as well as an increase in temporal jitter, spike latency, and conduction vulnerability of

individual CN fibers (e.g., Gonzalez-Gonzalez & Cazevieille, 2019; Heshmat et al., 2020;

Kim et al., 2013; Tasaki, 1955). CN fibers with different degrees of axonal dystrophy and

demyelination generate and conduct action potentials at different speeds, which reduces

the synchronized discharge across the population of CN fibers (Kandel, 2002). Animals

with more demyelination show greater reductions in neural synchrony in the CN (e.g., El-

Badry et al., 2007). In electrical hearing, loss of the peripheral axon and altered

membrane properties can also move the action potential initiation site distally to the SGN

soma or central axon (e.g., Hartmann et al., 1984; Javel & Shepherd, 2000; van den

Honert & Stypulkowski, 1984). Compared with responses initiated at peripheral axons,

spikes initiated at central axons have less temporal dispersion or jitter (Javel & Shepherd,

2000). The difference in the action potential initiation site among CN fibers could further

reduce discharge synchronization across CN fibers. Due to the lack of noninvasive tools

to evaluate neural synchrony in the CN to electrical stimulation in CI users in the past, our

knowledge in this area is primarily based on the results showing the variance in the first

spike latency after stimulus onset (i.e., temporal jitter) of individual CN fibers measured

using single fiber recordings in animal models (e.g., Hartmann et al., 1984; Parkins, 1989;

Shepherd & Hardie, 2001; Shepherd & Javel, 1997; Sly et al., 2007; van den Honert &

Stypulkowski, 1984). How well this knowledge applies to human CI users remains

unknown due to the differences in anatomical/morphometric and biophysical properties

of CN fibers, as well as durations and etiologies of deafness between human listeners

and experimental animals (Skidmore et al., 2022). In addition, these results do not provide

any information about discharge synchronization across electrically stimulated CN fibers

or discharge synchronization of a group of CN fibers across repeated stimulations. To

date, neural synchrony in the electrically stimulated CN in human listeners has not yet

been evaluated and remains unknown. Its role in processing temporal cues and

understanding speech in noise in CI users also remains unknown despite the rich

literature showing its importance for these processes in acoustic hearing.

To address these critical knowledge gaps, we recently developed a noninvasive,

in vivo method for assessing neural synchrony of a population of electrically stimulated

CN fibers by quantifying the trial-to-trial phase coherence in the summated activity to

electrical stimulation using electrophysiological measures of the electrically evoked

compound action potential (eCAP). Using this new method, we studied the effect of

peripheral neural synchrony on temporal resolution acuity by assessing the association

between the degree of peripheral neural synchrony and within-channel gap detection

threshold (GDT) measured using psychophysical procedures. The association between

the degree of peripheral neural synchrony and Consonant-Nucleus-Consonant (CNC)

word scores measured in quiet and in noise was also evaluated. These experiments were

designed to test the hypothesis that peripheral neural synchrony is an important factor for

temporal resolution acuity and speech perception outcomes in noise in post-lingually

deafened adult CI users.

MATERIALS AND METHODS

Study Participants

This study included 24 (14 Female, 10 Male) post-lingually deafened adult CI users

ranging in age from 36.8 to 84.0 years (mean: 63.7 years, SD: 12.8 years). All study

participants were native speakers of American English and used a Cochlear™ Nucleus®

device (Cochlear Ltd, Macquarie, NSW, Australia) with a full electrode insertion in the test

ear, as confirmed based on post-operative, high-resolution computerized tomography

scans. Participants A3, A5, and A12 were implanted bilaterally. For these three

participants, each ear was tested separately. None of these participants has any

functional acoustic hearing in either ear. eCAPs were measured in each of 27 ears tested

in these 24 participants. Participant A16 was unable to participate in the speech

perception evaluation. Participants A10, A16, A18 and A20 were not able to participate in

psychophysical measures of GDT due to their limited availabilities. As a result, speech

perception was evaluated for each of 26 ears tested in 23 participants. Psychophysical

GDTs were measured at two CI electrodes in each of 23 ears tested in 20 participants.

Detailed participant demographic information and the experiments that each participant

completed are provided in Table 1. Written informed consent was obtained from all study

participants at the time of data collection. The study was approved by the Biomedical

Institutional Review Board (IRB) at The Ohio State University (IRB study #: 2017H0131).

190   Insert Table 1 about here

Stimuli

For eCAP recording, the stimulus was a charge-balanced, cathodic-leading,

biphasic pulse with an interphase gap of 7 µs and a pulse phase duration of 25 µs/phase.

For measuring psychophysical GDT, the stimulus was a train of biphasic pulses with the

same characteristics as those of the single-pulse stimulus that was presented for 500 ms

at a stimulation rate of 900 pulses per second (pps) per channel. For both measures, the

stimulus was delivered to individual CI electrodes in a monopolar-coupled stimulation

mode via an N6 sound processor interfaced with a programming pod.

Behavioral C Level Measures

The maximum comfortable level (i.e., the C level) for each type of stimulus was

determined using an ascending procedure. In this procedure, study participants were

instructed to use a visual loudness rating scale [scale of 1-10, where 1 is "barely audible"

and 10 is "very uncomfortable"] to indicate when the sound reached the maximum comfort

level (rating of 8). Stimulation was first presented at a relatively low level and gradually

increased in steps of 5 clinical units (CUs) until a loudness rating of 7 was reached. Then,

stimulation was increased in steps of 1-2 CUs until a rating of 8 ("maximal comfort") was

reached. The C level was measured for each type of stimulation delivered to each test CI

electrode for each participant.

For the single-pulse stimulation used for eCAP recording, the stimulus was

presented to individual CI electrodes using the "Stimulation Only" mode in the Advanced

Neural Response Telemetry (NRT) function implemented in the Custom Sound EP (v.

6.0) commercial software (Cochlear Ltd, Macquarie, NSW, Australia) software. Due to the

challenge of reliably rating loudness for an extremely brief single pulse, the C level was

determined for a group of five pulses presented at 15 Hz. This is a standard clinical

practice for determining the C levels during the programming process. For the pulse-train

stimulation, the stimulus was presented to individual CI electrodes using a custom script

prepared using Nucleus Interface Communicator Routine Library (NIC v. 4.3.1) (Cochlear

Ltd, Macquarie, NSW, Australia).

eCAP Measurements

The eCAP recordings were obtained using the NRT function implemented in the

Custom Sound EP (v. 6.0) commercial software (Cochlear Ltd, Macquarie, NSW,

Australia). The eCAP was measured at individual CI electrode locations using a two-pulse

forward-masking-paradigm (Brown et al., 1990). In this paradigm, the masker and the

probe pulse were presented to the test electrode at the participants' C level and 10 CUs

below the C level, respectively. The stimulation was presented 400 times using a probe

rate of 15 Hz to minimize the potential effect of long-term adaptation on the eCAP (Clay

& Brown, 2007). The number of trials was chosen to be 400 because preliminary analyses

indicated that this number of trials could ensure accurate estimation of neural synchrony

in the CN while maintaining a feasible recording time (Skidmore et al., 2023). Results of

one of our previous studies have demonstrated that using electrophysiological results

measured at single CI electrode locations to correlate with auditory perception outcomes

in CI users can lead to inaccurate, if not wrong, conclusions (He et al., 2023). In

comparison, the averaged results across multiple testing electrode locations provide a

better representation of overall neural function than the result measured at any individual

CI electrode locations. Based on these results, four electrodes across the electrode array

were tested for each participant to get an estimate of overall CN function while maintaining

a feasible testing time. The default testing electrodes were electrodes 3, 9, 15, and 21.

Alternate electrodes were tested in cases where there was an open- or short-circuit at the

default electrode locations. The electrodes tested for each participant are listed in Table

1. Other parameters used to record the eCAP included a recording electrode located two

electrodes away apically from the stimulating electrode except for electrode 21 which was

recorded at electrode 19, a 122-µs recording delay, an amplifier gain of 50 dB, and a

sampling rate of 20,492 Hz.

Measure of Neural Synchrony

Peripheral neural synchrony at individual CI electrode locations was evaluated

based on 400 individual sweeps (trials) of the eCAP. Neural synchrony was quantified

using an index named the phase locking value (PLV) which is a measure of trial-to-trial

phase coherence among the 400 eCAP sweeps. The PLV is a unitless quantity that

ranges from 0 to 1. It quantifies the degree of synchrony in neural responses generated

by target CN fibers across multiple stimulation/trials. The PLV is influenced by temporal

jitter in spike firing of individual CN fibers, discharge synchronization across the

population of activated CN fibers, and discharge synchronization of a group of activated

CN fibers across multiple stimulations. A PLV of 0 means that the distribution of phase

across trials is uniform (i.e., the responses across trials are uncorrelated). The PLV is 1

if phases across trials are perfectly correlated. As a result, larger PLVs indicate

better/stronger neural synchrony in the CN. Mathematically, the PLV is the length of the

vector formed by averaging the complex phase angles of each trial at individual

frequencies obtained via time-frequency decomposition. Specifically, the PLV is

calculated at a specific frequency and time window (i.e., frame) as

260
$$PLV(f,t) = \left| \frac{1}{400} \sum_{k=1}^{400} \frac{F_k(f,t)}{|F_k(f,t)|} \right|$$

where $F_k(f,t)$ is the spectral estimate (i.e., complex number representing the amplitude

and phase of a sinusoid obtained from the short-time Fourier transform) of trial k at

frequency f for the time window t. For this study, the time-frequency decomposition was

performed at six linearly spaced frequencies (788.2, 1576.3, 2364.4, 3152.6, 3941.0 and

4729.2 Hz) with Hanning Fast Fourier Transform tapers, a pad-ratio of 2 and a frame size

of 26 samples (1268.8 μs) using the newtimef function (v. 2022.1) included in the

MATLAB plugin EEGlab (Delorme & Makeig, 2004). For each CI electrode tested in each

participant, a single PLV was obtained by averaging PLVs calculated at six frequencies

for six partially overlapped frames with an onset-to-onset interval of 48.8 μs between two

adjacent frames within a time window of 1561.6 μs. The use of six partially overlapped

frames within the time window of interest allows for higher temporal resolution of the PLV,

with PLV values in the early frames capturing the degree of synchrony in the low-latency

spikes and values in the later frames being dependent on synchrony in the longer-latency

spikes.

The parameters used in PLV calculation were selected based on morphological

characteristics of the eCAP measured in human CI users and the sampling rate offered

by CI manufacturers for eCAP recording. Specifically, the eCAP recorded in human CI

users consists of one negative peak (N1) within a time window of 0.2 – 0.4 ms after

stimulus onset followed by a positive peak (P2) occurring around 0.6 – 0.8 ms (for a

review, see He et al., 2017). As a result, the longest inter-peak latency of the eCAP in

human listeners is 600 μs. Using this duration as the half width of the sinusoid included

in Fast Fourier Transform analysis and the sampling rate of 20,492 Hz offered by

Cochlear™ Nucleus® device for measuring the eCAP, the frame size was determined to

be 1268.8 μs in time which included 26 samples (1268.8/48.8 = 26). As a result, six

frames with an onset-to-onset interval of 48.8 μs between two adjacent frames cover the

entire recording window [(1561.6-1268.8)/48.8 = 6]. This frame size in time also

determines the lowest frequency (1/1268.8 µs = 788.1 Hz) used in the PLV calculation.

The difference in the peak-to-baseline amplitude between the N1 and the P2 peak of the

eCAP and the difference in their widths indicate a complex spectrum instead of a single

fundamental frequency. A Fast Fourier Transform analysis was conducted to determine

the frequency components of the averaged eCAPs over 400 sweeps measured in this

study. Results showed that the harmonic frequency with one quarter of the amplitude

measured at the fundamental frequency was 4482.6 Hz. As a result, the highest

frequency used in PLV calculation was determined to be 4729.2 based on a spectral

resolution of 788.1 Hz determined by the frame size in time. This frequency range (i.e.,

788.1 – 4729.2 Hz) is higher than that used in Harris et al. (2018, 2021). This difference

is caused by morphological differences between the eCAP and the compound action

potential evoked by acoustic clicks.

Figures 1 and 2 use example data recorded at four CI electrode locations in

participant A14 and in the right ear of participant A3 to illustrate this method. These

examples were chosen because they included the lowest and the highest PLV measured

in this study. Electrode number, the resulting PLV and the amplitude of the eCAP

averaged over 400 sweeps/trials are indicated in each panel. It should be noted that these

eCAPs were measured at the C level measured for each tested CI electrode in each

participant. Therefore, the variation in stimulation levels used to measure the eCAP and

the difference in corresponding eCAP amplitudes across different CI electrodes within

each participant are due to participant-related factors instead of measurement bias.

308   Insert Figure 1 about here

309   Insert Figure 2 about here

Psychophysical Measures of Gap Detection Threshold

Within-channel GDTs were measured at two electrode locations with different

PLVs in each of 23 ears tested in 20 participants (see Table 1 for the electrodes tested in

each ear). Pulse trains with and without temporal gaps were presented in a three-

alternative, forced-choice paradigm that incorporated a three-down, one-up adaptive

strategy to estimate 79.4% correct on the psychometric function (Levitt, 1971). Individual

trials consisted of three consecutive 500-ms listening intervals separated in time by 500

-ms silent intervals. The stimulus presented in two of the three listening intervals was a

500-ms pulse train without any interruption. The stimulus presented in the remaining

listening interval, chosen at random, included a temporal gap centered at 250 ms of

stimulation. The participant was asked to determine which of the three listening intervals

included two sounds. Feedback on correct/incorrect choices was not provided to

participants. The gap duration began at 64 ms and was shortened/lengthened based on

the correctness of the participants' choice. The initial step size of the change in gap

duration was 32 ms. This step changed by a factor of two after three consecutive correct

responses or one incorrect response. The minimum and maximum gap durations

permitted were 1 ms and 256 ms, respectively. The GDT was calculated as the average

across two trials in which the mean gap duration over the last four (of twelve) reversals

was calculated.

Speech Measures

Speech perception performance was evaluated separately for each implanted ear

using Consonant-Nucleus-Consonant (CNC) word lists (Peterson & Lehiste, 1962)

presented in quiet and in two noise conditions, following the procedure described in the

new Minimum Speech Test Battery (MSTB, 2011). All auditory stimuli were presented in

a sound-proof booth via a speaker placed one meter in front of the subject at zero degrees

azimuth. The target stimulus was always presented at 60 dB sound pressure level (SPL).

For the noise conditions, speech-shaped noise was presented concurrently with the target

stimulus at 50 dB SPL and 55 dB SPL to create signal-to-noise ratios of +10 dB and +5

dB, respectively. This test and these testing conditions are recommended for assessing

clinical outcomes in adult CI users (Adunka et al., 2018; Audiology, 2019; Carlson et al.,

2018).

Statistical Analyses

Descriptive statistics of PLVs measured at different electrode locations, GDTs and

CNC word scores measured in different testing conditions and the difference in CNC word

scores measured in quiet and in noise were calculated, including the overall mean and

standard deviation. ffects of electrode location and stimulation level on the PLV were

assessed using a Linear Mixed effect Model (LMM) with electrode location and stimulation

level as fixed effects. The effect of the PLV on GDT was evaluated using a LMM with the

PLV, the stimulation level used to measure the GDT and the stimulation used to measure

the PLV as fixed effects. All LMMs used a correlated regression model with an

unstructured correlation matrix to account for repeated observations per participant.

Estimations were obtained using restricted maximum likelihood with Satterthwaite

degrees of freedom. The Tukey's Honest Significant Difference (Tukey's HSD) method

was used to adjust for multiple comparisons. The difference in GDT between results

measured at the two electrodes with different PLVs or stimulation levels were assessed

using paired sample t-tests. One-tailed Pearson product-moment correlation tests with

Bonferroni correction for multiple comparisons were used to assess the association of the

PLV with CNC word scores measured in different conditions ($\alpha = 0.017$), as well as with

the change in CNC word score with competing background noise (i.e., CNC word score

measured in quiet - CNC word score measured in noise, $\alpha = 0.025$). For these correlation

analyses, PLVs measured at all electrode locations were averaged together for each

participant/ear to obtain an estimation of the overall peripheral neural synchrony within

the cochlea and to minimize electrode-location related bias in study results (He et al.,

2023). The strength of correlation was determined based on values of the Pearson

product-moment correlation coefficient (r). Specifically, weak, moderate, and strong

correlations were defined as *r* values between 0 and 0.3 (0 and -0.3), between 0.3 and

0.7 (-0.3 and -0.7), and between 0.7 and 1.0 (-0.7 and -1.0), respectively.

All statistical analyses for this study were performed using R software (v. 4.3.0) (R

Core Team, 2021). All statistical models were fitted using the nlme package (Pinheiro et

al., 2023) and pairwise comparisons were evaluated using the emmeans package (Lenth,

2023).

RESULTS

Neural Synchrony Along the Cochlea

PLVs measured in this study ranged from 0.09 to 0.76 (mean: 0.55, SD: 0.22)

across all electrodes tested. The means and standard deviations of PLVs measured at

each of the four electrode locations are shown in Figure 3. The standard deviations at all

four electrode locations demonstrate variations in the PLV in CI users. In addition, a trend

for the mean PLV to be different across electrode locations is observed. PLVs measured

at apical electrode locations (i.e., electrodes 15 and 21) appear to be larger than those

measured at more basal electrode locations (i.e., electrodes 3 and 9). The results of the

LMM showing a significant effect of electrode location on the PLV ($\chi^2_{(3)}$ = 17.11, p < .001)

after controlling for the significant effect of stimulation level on the PLV ($t_{(101)}$ = 3.90, p <

.001). The results of pairwise comparisons showed that PLVs measured at electrode 15

were significantly larger than those measured at electrode 3 ($t_{(26.9)}$ = -3.46, p = .009) and

electrode 9 ($t_{(27.8)}$ = -3.62, p = .006). The differences in the PLV measured between other

electrode pairs did not reach a statistical significance. Detailed results of pairwise

comparisons are listed in Table 2.

387   <u>Insert Figure 3 about here</u>

388   <u>Insert Table 2 about here</u>

Neural Synchrony and Temporal Acuity

Figure 4 shows psychophysical GDTs measured at two electrode locations per test

ear in 20 participants (23 ears) as a function of the PLV. For the two CI electrode locations

tested in each of 19 ears in 18 participants, smaller GDTs were always measured at the

electrode locations with higher PLVs. Results measured in A8, A24 and the right ear of

A5 showed an opposite pattern. In the left ear of A12, GDTs measured at the two CI

electrode locations with different PLVs were the same (5.75 ms). The result of a paired-

samples t-test showed that GDTs measured at the electrode locations with larger PLVs

were statistically significantly smaller than those measured at electrode locations with

smaller PLVs ($t_{(22)}$ = 2.25, p = .035). The results of the LMM showed a significant effect

of the PLV on GDT ($t_{(42)}$=-3.51, p = .001) after controlling for the stimulation level of GDT

(t(42) = -2.53, p = .015) and the stimulation level of the PLV (t$_{(42)}$ =3.75, p < .001), with

larger PLVs leading to smaller GDTs.

402   Insert Figure 4 about here

Figure 5 shows psychophysical GDT results as a function of stimulation levels

used to measure these GDTs. Smaller GDTs were measured at higher stimulation levels

for the two CI electrode locations tested in each of 10 ears tested in 9 participants. Results

measured in 11 ears tested in 11 participants showed an opposite relation between these

two parameters. For A2, the stimulation levels used to measure GDTs at electrodes 3

and 18 were the same (196 CU). For A12, using different stimulation levels at electrodes

3 and 21 resulted in the same GDT (i.e., 5.75 ms). Overall, despite a significant

stimulation level effect on GDT at a group level as shown in the LMM results, these data

do not demonstrate a consistent association between stimulation level and GDT across

participants, which differs from those shown in Figure 4. Consistent with these

observations, the result of a paired-samples t-test showed that GDTs measured at the

electrode locations with higher stimulation levels were not significantly different from

those measured at the electrode locations with lower stimulation levels (t$_{(22)}$ = -0.53, p =

.599).

417   Insert Figure 5 about here

Neural Synchrony and Speech Perception

Figure 6 shows CNC word scores measured in quiet and in two noise conditions

as a function of the PLV for 23 participants (26 ears). There was substantial variability in

CNC word scores measured in quiet (range: 40.0 – 96.0%, mean: 73.1%, SD: 13.3%)

and in noise (+10 dB SNR: range: 22.0 – 84.0%, mean: 58.1%, SD: 15.8%; +5 dB SNR:

range: 8.0 – 82.0%, mean: 45.6%, SD: 15.6%). There was no obvious relation between

CNC word score and the PLV for each of the testing conditions. This observation was

confirmed by the result of a Pearson product-moment correlation test with Bonferroni

correction for multiple testing (Quiet: r = -0.18, p = 0.193; +10 dB SNR: r = -0.08, p =

0.353; +5 dB SNR: r = 0.15, p = 0.238).

428   Insert Figure 6 about here

The amount of change in CNC word scores with the presence of noise also varied

among CI users (+10 dB SNR: range: -32 – 4.0%, mean: -15.0%, SD: -9.5%; +5 dB SNR:

range: -46.0 – -6.0%, mean: -27.4%, SD: -10.9%). Figure 7 shows the change in CNC

word scores plotted as a function of the PLV for both noise conditions. There was no

obvious relation between the noise effect on CNC word score and the PLV for the +10 dB

SNR noise condition, which was confirmed by the result of a Pearson product-moment

correlation test (r = -0.12, p = 0.281). In comparison, there was a moderate, negative

correlation between the PLV and the degree of detrimental effect of background noise on

CNC word score for the results measured at a SNR of +5 dB (r = -0.42, p = 0.016), with

larger PLVs associated with smaller negative effects of background noise. This

correlation is statistically significant after adjusting for multiple comparisons.

440   Insert Figure 7 about here

Periomodiolar vs. Lateral Wall Electrode Arrays

In this study, 16 ears of 15 participants were implanted with a periomodiolar

electrode array and all other testing ears were implanted with a lateral wall electrode

array. Even though it was not included in our original study design or the primary interest

of this study, we conducted additional data analyses to determine whether the

associations between the PLV, GDT and CNC word results differ between these two

electrode arrays. Specifically, the effect of the PLV on GDT was evaluated using a LMM

with the PLV, the stimulation level used to measure the PLV, the stimulation level used

to measure GDT and electrode array type as fixed effects, participant as a random effect

and an interaction between the PLV and electrode array type. The result showed a

significant interaction ($t_{(73)}$ = 2.55, p = .013), which suggests that the effect of the PLV on

GDT differs between these two electrode arrays. The estimated slopes of linear

regression functions modeling the relation between GDT and the PLV were significantly

different from zero for both electrode arrays (lateral wall array: slope = -0.021, p < .001;

periomodiolar array: slope = -0.006, p = .018). The difference in the estimated slopes

between lateral wall and periomodiolar arrays was statistically significant ($t_{(33.7)}$ = -2.55, p

= .015), which evidences a stronger effect of the PLV on GDT for lateral wall electrode

array than for periomodiolar electrode array.

The relation between the PLV and CNC word results by electrode array type was

evaluated using linear regression analyses. The outcome variable was the PLV with linear

predictors of CNC word results and electrode array type, and the interaction between

electrode array type and CNC scores/changes in CNC scores with noise. The interaction

term included in the linear regression was used to determine if the relation between CNC

results and the PLV differed by electrode array type. Evaluations were conducted with a

total of five regression models with each model built for each CNC result. Overall, none

of these models showed a significant interaction between electrode array type and CNC

results (p > .05). Therefore, there is no sufficient evidence to suggest that the relation

between the PLV and CNC word results differs by electrode array type.

DISCUSSION

This paper reports a newly developed method for quantifying neural synchrony in

the electrically stimulated CN in human CI users. Using this newly developed method/tool,

we evaluated the effects of peripheral neural synchrony on temporal resolution acuity and

speech perception outcomes in human CI users. Results of this study showed variations

in the degree of peripheral neural synchrony among CI users and demonstrated the

important role that peripheral neural synchrony played in determining temporal resolution

acuity in post-lingually deafened adult CI users. Our results also demonstrated a lack of

association between the PLV and CNC word scores measured in quiet or in noise, as well

as between the PLV and the amount of change in CNC word scores when a competing

background noise at a SNR of +10 dB was added. However, there was a statistically

significant negative correlation between the PLV and the degree of negative effect of

background noise at a SNR of +5 dB. Overall, these results support our study hypothesis.

Peripheral Neural Synchrony in Electrical Hearing

PLVs measured in CI users in this study ranged from 0.09 to 0.76, which is much

higher than those measured in listeners with acoustic hearing (Harris et al., 2021). These

results are consistent with the literature in animal models showing lower temporal jitters

(i.e., higher discharge synchronization) of neural responses evoked by electrical

stimulation than those evoked by acoustic stimulation (e.g., van den Honert &

Stypulkowski, 1984). As a result, morphological characteristics of the eCAP are different

from those of the compound action potential evoked by acoustic stimulation, which lead

to the differences in frequency range, frame size and the number of linearly spaced

frequencies used in Fast Fourier Transform analysis between this study and Harris et al.

(2021). In addition, the recording window used in Harris et al. (2021) for PLV calculation

is much longer than that used in this study (i.e., 10 ms vs 1561.6 μs). As a result, the

number of frames used in these two studies are also different. Another important

difference is how the final, single PLV is defined. In Harris et al. (2021), it was defined as

the peak PLV across a 2-ms window around the N1 peak of the CAP. In our study, it was

defined as the averaged PLV across six partially overlapped frames to better capture the

degree of synchrony in spikes with varied latencies. All these factors could contribute to

the different PLV ranges observed in these two studies. Note that our use of the mean

PLV is more similar to the approach use in an earlier study by Harris and colleagues, in

which they calculated a single PLV value by taking the *median* value across time and

frequency (Harris et al., 2018).

Results of previous histological and functional studies have shown unpredictable

patterns of CN health within and among typical CI users with heterogeneous etiologies

(e.g., DeVries et al., 2016; Nadol et al., 2012; Sagers et al., 2017; Schvartz-Leyzac &

Pfingst, 2016). Therefore, variations in peripheral neural synchrony would be expected

across CI users and across electrode locations within individual patients, which is

consistent with the wide ranges of PLVs being measured at different electrode locations

across the cochlea in this study. Neural structures at the apex tend to be healthier than

those located at more basal region of the cochlea in typical listeners with sensorineural

hearing loss (Zimmermann et al., 1995), which could contribute to the higher PLVs

measured at more apical locations in this study.

Peripheral Neural Synchrony and Auditory Perception Outcomes

GDTs measured in this study are consistent with those reported in other studies that used similar testing paradigms and conditions (e.g., Busby & Clark, 1999; Garadat & Pfingst, 2011; Shader et al., 2020). Despite variations in GDTs and PLVs measured among participants, larger GDTs were observed at the electrode locations with smaller PLVs in all except for four implanted ears tested in this study. These data demonstrated that poor peripheral neural synchrony led to declined temporal resolution acuity in CI users, which is consistent with those measured in acoustic hearing (Michalewski et al., 2005; Zeng et al., 2005; Zeng et al., 1999). It should be noted that stimulation rate affects peripheral neural synchrony in electrical hearing, with higher stimulation rates resulting in lower/worse neural synchrony (Rubinstein et al., 1999). As a result, the degree of peripheral neural synchrony induced by the pulse train stimulation used to measure GDT is expected to be much lower than that quantified by the PLV in this study. Nevertheless, the results of both measures are affected by dyssynchronous neural firing, which explains to the strong relation between these two measures.

Our results showed a lack of correlation between peripheral neural synchrony and CNC word scores. These results are not consistent with the significant correlation between peripheral neural synchrony and CNC word scores measured in quiet reported by Dong et al. (2023). However, it should be noted that peripheral neural synchrony was not directly assessed in the experimental design of Dong et al. (2023). Instead, it was estimated using computational modeling techniques by deconvolving intraoperative recordings of the eCAP with an estimated human unitary response to obtain the distribution of firing latencies summed across CN fibers. As acknowledged by the authors,

the estimation of neural synchrony using this modeling approach is highly dependent on

the shape of the assumed unitary response from CN fibers, which has not been

assessed/validated directly in humans (Dong et al., 2020; Dong et al., 2023). It is possible

that degeneration of CN fibers leads to changes in the effective unitary response functions

for each fiber, such that their simulated results did not fully reflect the actual peripheral

neural synchrony in CI users. This methodological difference could contribute to the

discrepancy between the results of Dong et al. (2023) and the present study. Speech

perception outcomes in noise were not evaluated by Dong et al. (2023).

One finding of this study is the moderate correlation between the PLV and the

detrimental effect of background noise on speech perception outcomes measured for the

+5 dB SNR noise condition. This finding suggested that the degree of neural synchrony,

as quantified using the PLV, accounted for approximately 18% of the negative effect of

competing background noise presented at a SNR of +5 dB on CNC word scores. This

statistically significant result could also be clinically meaningful given the fact that

combining multiple factors could only explain less than 40% of variance in speech

perception outcomes in CI users (Blamey et al., 1996; Blamey et al., 2013; Holden et al.,

2013; James et al., 2019; Lazard et al., 2012). This association was not observed for

speech perception outcomes measured at +10 dB SNR. Overall, these results indicated

that peripheral neural synchrony could be an important factor determining the degree of

the noise effect on speech perception outcomes in CI users in the case of mixed speech

and masker signals presented to the same ear. The importance of peripheral neural

synchrony to speech perception seems to increase with elevated background noise,

which is consistent with the literature reporting the stronger impact of CN function on

speech perception outcomes in more challenging listening conditions (e.g., Canfarotta et

al., 2021; Fitzpatrick et al., 2014; Skidmore et al., 2023).

Methodological Considerations

There are several methodological factors that need to be considered when applying

this method in future studies. First, using different parameters in mathematical calculation

will result in different PLV results. To determine whether this is a crucial factor for this

newly developed method, we used three additional sets of parameters to calculate the

PLV and assessed their associations with GDTs, CNC word scores measured in different

conditions and the noise effect on CNC word scores using the same statistical analysis

methods as those reported in this study. Overall, PLVs calculated using all four sets of

parameters are strongly correlated with each other (Pearson correlation coefficients:

0.94-0.98, p< .001). More importantly, the results calculated using different sets of

parameters are consistent and lead to the same conclusions. These three additional sets

of parameters used to calculate the PLV are reported in Table A1 included in

Supplemental Digital Content 1. GDTs plotted as a function for PLVs calculated using

these additional parameters are shown in Figure A1 included in Supplemental Digital

Content 2. The association between PLVs and CNC word scores measured in different

conditions and the association between the PLV and the noise effect on CNC word scores

are shown in Figures B1 and C1 included in supplemental Digital Content 3 and 4,

respectively. The results of Pearson-Moment Product correlation tests are also shown in

these two figures. Descriptive results of PLVs calculated using these three additional sets

of parameters and LMMs results showing the effect of stimulation level and electrode

location on the PLV are reported in Table B1 included in Supplemental Digital Content 5.

Results of pairwise comparisons for comparing PLVs measured at different electrode

locations are reported in Table C1 included in Supplemental Digital Content 6. Overall,

these data suggest that this method does not rely on the specific parameters used in the

time-frequency decomposition.

Second, the recording window for measuring the eCAP should not be confused with

the frame size in time used in the time-frequency decomposition. The recording window

offered by different CI manufacturers' software ranges from 1561.6-2500 μs, which is

longer than a time window where the eCAP is expected for in human CI users (i.e., within

the first 1200 μs) (Botros et al., 2007). The inter-trial phase coherence is low for the part

where the recorded traces only contain noise. As a result, including prolonged time

window in the time-frequency decomposition is not always beneficial or appropriate.

Admittedly, the duration of the recording window affects the number of frames that could

be included in the time-frequency decomposition. However, our results reported in

Supplemental Digital Contents suggest that it is not a determing factor for this method.

Third, Advanced Bionics and MedEL devices offer higher sampling rates

(Advanced Bionics: 56 kHz, MedEL: 1.2 MHz) than Cochlear™ Nucleus® device for

eCAP recording. This parameter is determined by each CI manufacturer and cannot be

changed in their clinical software. In human CI users, the shortest possible interpeak

latency of the eCAP is around 0.2 ms (for a review, see He et al., 2017). In a Fast Fourier

Transform analysis, this corresponds to a fundamental period of 0.4 ms or a fundamental

frequency of 2.5 kHz. Cochlear™ Nucleus® device offers a sampling rate of 20,492 Hz,

and therefore the fundamental frequency and first few harmonics of these shortest eCAP

waveforms fall below the Nyquist frequency of 10,246 Hz. Thus, this sampling rate, which

is the lowest among all three major CI devices, is sufficient for eCAP recording and is not

a factor that could limit the sensitivity of PLV measures. Nevertheless, the difference in

sampling rate affects two parameters used in the time-frequency decomposition: the

number of frames that can be included in the time-frequency decomposition and the

number of samples that can be included in each frame. Higher sampling rates allow for

shorter onset-to-onset intervals between two adjacent frames and more samples included

in each frame. As a result, more frames with more samples included per frame can be

included to calculate the PLV for Advanced Bionics and MedEL devices than for

Cochlear™ Nucleus® device, which will affect the resulting PLV. This issue would not be

problematic when comparing PLVs measured using the device from the same

manufacturer. Only including the PLVs calculated for the frames with similar central

spectral time windows to calculate the averaged PLV could eliminate the cross-device

difference in the number of frames used in PLV calculation. One potential solution to

minimize the effect of hardware-related difference on study results when comparing PLVs

across devices is to normalize PLVs measured in individual participants based on the

PLV range measured in a large group of patients with the same device, and to use the

normalized results in comparison. This topic requires additional studies and is beyond the

scope of this work.

Fourth, parameter modifications might be needed when applying this method to

some patient populations whose morphological characteristics of the eCAP differ from

those recorded in "typical" CI users. For example, eCAPs recorded in children with

cochlear nerve deficiency show prolonged interpeak latencies and less prominent P2

peak, which could affect the frequency range used in the time-frequency decomposition.

Finally, results of previously published studies showed that the variation in

discharge synchronization increases with pulse phase duration (Bruce et al., 1999) and

during refractory recovery (Miller et al., 2001). The potential difference in spike initiation

site for cathodic vs anodic stimulation also affects temporal jitter (Javel & Shepherd,

2000). As a result, the PLV could be affected by characteristics of the electrical pulse and

the artifact rejection technique used to measured eCAP traces.

Potential Study Limitations

This study has four potential limitations. First, this method is developed based on

morphological characteristics of the eCAP measured in human CI users. Parameters

used in this method may need to be modified to suit different animal models due to the

anatomical difference in the CN between animal models and human listeners and the

difference in durations and etiologies of deafness between experimental animals and

human CI users. Second, the stimulation level could be a confounding factor for the

results of this study because results of previous studies suggested a CN-health-

dependent effect of stimulation level on peripheral neural synchrony. Specifically, Harris

et al. (2021) reported larger PLVs measured at higher stimulation levels in listeners with

acoustic hearing. However, this association was only observed in listeners with good CN

health (i.e., young hearing listeners) and not in elderly listeners who have been shown to

have poor peripheral neural synchrony and reduced CN densities. These results

suggested that the stimulation level could be a confounding factor for the results of this

study and thereby needs to be controlled for. Using stimulation levels that are balanced

based on subjective perception of loudness has been widely used to control/minimize the

potential stimulation level effect in psychophysical studies. In this study, both single-pulse

and pulse-train stimuli delivered to different CI electrodes tested in each participant were

presented at the levels that were determined to be "maximal comfort" (rating 8 on the

same visual loudness rating scale). Therefore, in a certain sense and to a certain degree,

the stimulation levels used at different electrodes can be considered loudness balanced

within each participant and even across participants. However, electrical biphasic pulses

that evoke neural responses with comparable amplitudes or these matched in current

level are not necessarily perceived as equally loud by CI users (Kirby et al., 2012).

Similarly, neural responses evoked by pulses that are perceived equally loud by CI users

can have a large difference in neural response amplitude (Kirby et al., 2012). In addition,

comparing loudness for single pulse stimulation with a total duration of only 57 µs could

be impossible for many CI users, as demonstrated during our pilot study. Therefore, using

loudness-balanced stimulation levels may not be a good solution to eliminate the potential

level effect on study results. Instead, the stimulation level effect on results of this study

was controlled using statistical analyses. Third, as an initial step toward understanding

the role of peripheral neural synchrony in determining CI clinical outcomes, this study only

evaluated the association between neural synchrony in the CN and monoaural auditory

perception outcomes in human CI users. The modeling study by Resnick and Rubinstein

(2021) suggests that degraded neural synchrony might have an even greater impact in

binaural listening conditions where interaural timing difference cues are needed to help

separate a speech stream from background noise. Further studies are warranted to

determine the role of neural synchrony in the CN in binaural hearing. Finally, despite

these results, the exact biological underpinning (e.g., demyelination, peripheral axon

degeneration, or total SGN loss) of the PLV remains unknown and requires further

investigation. Due to the lack of noninvasive tools, it is not feasible to use experimental

approaches to determine physiological conditions of the CN in living human listeners.

Computational modeling techniques have been widely used to probe neuroanatomical

conditions underlying neural response patterns in neuroscience, which holds the potential

to be used to answer this important question.

CONCLUSIONS

Neural synchrony in the electrically stimulated CN could be estimated at individual

electrode locations in CI users by calculating the phase coherence across repeated

presentations of a single pulse stimulus using the method reported in this paper.

Peripheral neural synchrony varies across CI users and electrode locations. Poorer

peripheral neural synchrony leads to lower temporal resolution acuity. The degree of

peripheral neural synchrony is associated with the size of detrimental effect of competing

background noise on speech perception performance in post-lingually deafened adult CI

users. Further studies are warranted to fully understand the role of peripheral neural

synchrony in determining auditory perception outcomes in electrical hearing.

REFERENCES

Blamey, P., Arndt, P., Bergeron, F., Bredberg, G., Brimacombe, J., Facer, G., Larky, J.,

Lindström, B., Nedzelski, J., Peterson, A., Shipp, D., Staller, S., & Whitford, L.

(1996). Factors affecting auditory performance of postlinguistically deaf adults

using cochlear implants. *Audiology and Neuro-Otology*, *1*(5), 293-306.

https://doi.org/10.1159/000259212

Blamey, P., Artieres, F., Baskent, D., Bergeron, F., Beynon, A., Burke, E., Dillier, N.,

Dowell, R., Fraysse, B., Gallego, S., Govaerts, P. J., Green, K., Huber, A. M.,

Kleine-Punte, A., Maat, B., Marx, M., Mawman, D., Mosnier, I., O'Connor, A. F., .

. . Lazard, D. S. (2013). Factors affecting auditory performance of postlinguistically

deaf adults using cochlear implants: An update with 2251 patients. *Audiology and*

Neuro-Otology, *18*(1), 36-47. https://doi.org/10.1159/000343189

Botros, A., van Dijk, B., & Killian, M. (2007). Autonrt: An automated system that measures

ecap thresholds with the nucleus freedom cochlear implant via machine

intelligence. *Artificial Intelligence in Medicine*, *40*(1), 15-28.

https://doi.org/10.1016/j.artmed.2006.06.003

Brown, C. J., Abbas, P. J., & Gantz, B. (1990). Electrically evoked whole-nerve action

potentials: Data from human cochlear implant users. *The Journal of the Acoustical*

Society of America, *88*(3), 1385-1391. https://doi.org/10.1121/1.399716

Bruce, I. C., Léger, A. C., Moore, B. C., & Lorenzi, C. (2013). Physiological prediction of

masking release for normal-hearing and hearing-impaired listeners. *Proceedings*

of Meetings on Acoustics, *19*(1). https://doi.org/10.1121/1.4799733

Bruce, I.C., White, M.W., Irlicht, L.S., O'Leary, S.J., Dynes, S., Javel, E., & Clark, G.M.

(1999). A stochastic model of the electrically stimulated auuditory nerve: single-

pulse response. *IEEE Transactions on Biomedical Engineering, 46*(6), 617-629.

https//doi: 10.1109/10.764938

Busby, P. A., & Clark, G. M. (1999). Gap detection by early-deafened cochlear-implant

subjects. *Journal of the Acoustical Society of America*, *105*(3), 1841-1852.

https://doi.org/Doi 10.1121/1.426721

Canfarotta, M. W., O'Connell, B. P., Giardina, C. K., Buss, E., Brown, K. D., Dillon, M. T.,

Rooth, M. A., Pillsbury, H. C., Buchman, C. A., Adunka, O. F., & Fitzpatrick, D. C.

(2021). Relationship between electrocochleography, angular insertion depth, and

cochlear implant speech perception outcomes. *Ear and Hearing*, *42*(4), 941-948.

https://doi.org/10.1097/AUD.0000000000000985

Clay, K. M. S., & Brown, C. J. (2007). Adaptation of the electrically evoked compound

action potential (ecap) recorded from nucleus ci24 cochlear implant users. *Ear and*

Hearing, *28*(6), 850-861. https://doi.org/10.1097/aud.0b013e318157671f

Delgutte, B., & Kiang, N. Y. (1984). Speech coding in the auditory nerve: I. Vowel-like

sounds. *Journal of the Acoustical Society of America*, *75*(3), 866-878.

https://doi.org/10.1121/1.390596

Delorme, A., & Makeig, S. (2004). Eeglab: An open source toolbox for analysis of single-

trial eeg dynamics including independent component analysis. *Journal of*

Neuroscience Methods, *134*(1), 9-21.

https://doi.org/10.1016/j.jneumeth.2003.10.009

DeVries, L., Scheperle, R., & Bierer, J. A. (2016). Assessing the electrode-neuron

interface with the electrically evoked compound action potential, electrode

position, and behavioral thresholds. *Journal of the Association for Research in*

Otolaryngology, *17*(3), 237-252. https://doi.org/10.1007/s10162-016-0557-9

Di Stadio, A., Volpe, A. D., Ralli, M., Korsch, F., Greco, A., & Ricci, G. (2020). Spiral

ganglions and speech perception in the elderly. Which turn of the cochlea is the

more relevant? A preliminary study on human temporal bones. *The Journal of*

International   Advanced   Otology,   *16*(3),   318-322.

https://doi.org/10.5152/iao.2020.8481

Dong, Y., Briaire, J. J., Biesheuvel, J. D., Stronks, H. C., & Frijns, J. H. M. (2020).

Unravelling the temporal properties of human ecaps through an iterative

deconvolution   model.   *Hearing   Research*,   *395*,   108037.

https://doi.org/10.1016/j.heares.2020.108037

Dong, Y., Briaire, J. J., Stronks, H. C., & Frijns, J. H. M. (2023). Speech perception

performance in cochlear implant recipients correlates to the number and synchrony

of excited auditory nerve fibers derived from electrically evoked compound action

potentials.   *Ear   and   Hearing*,   *44*(2),   276-286.

https://doi.org/10.1097/Aud.0000000000001279

Eisenberg, L. S., Fisher, L. M., Johnson, K. C., Ganguly, D. H., Grace, T., Niparko, J. K.,

& Team, C. D. I. (2016). Sentence recognition in quiet and noise by pediatric

cochlear implant users: Relationships to spoken language. *Otology & Neurotology*,

37(2), e75-81. https://doi.org/10.1097/MAO.0000000000000910

El-Badry, M. M., Ding, D.-L., McFadden, S. L., & Eddins, A. C. (2007). Physiological effects of auditory nerve myelinopathy in chinchillas. *European Journal of Neuroscience*, *25*(5), 1437-1446. https://doi.org/10.1111/j.1460-9568.2007.05401.x

Fayad, J., Linthicum, F. H., Jr., Otto, S. R., Galey, F. R., & House, W. F. (1991). Cochlear implants: Histopathologic findings related to performance in 16 human temporal bones. *Annals of Otology, Rhinology and Laryngology*, *100*(10), 807-811. https://doi.org/10.1177/000348949110001004

Fayad, J. N., & Linthicum, F. H., Jr. (2006). Multichannel cochlear implants: Relation of histopathology to performance. *Laryngoscope*, *116*(8), 1310-1320. https://doi.org/10.1097/01.mlg.0000227176.09500.28

Fitzpatrick, D. C., Campbell, A. P., Choudhury, B., Dillon, M. T., Forgues, M., Buchman, C. A., & Adunka, O. F. (2014). Round window electrocochleography just before cochlear implantation: Relationship to word recognition outcomes in adults. *Otology & Neurotology*, *35*(1), 64-71. https://doi.org/10.1097/MAO.0000000000000219

Garadat, S. N., & Pfingst, B. E. (2011). Relationship between gap detection thresholds and loudness in cochlear-implant users. *Hearing Research*, *275*(1-2), 130-138. https://doi.org/10.1016/j.heares.2010.12.011

Gonzalez-Gonzalez, S., & Cazevieille, C. (2019). Myelination of the auditory nerve: Functions and pathology. *Scientific Journal of Research & Reviews*, *1*(3). https://doi.org/10.33552/sjrr.2019.01.000513

Harris, K. C., Ahlstrom, J. B., Dias, J. W., Kerouac, L. B., McClaskey, C. M., Dubno, J.

R., & Eckert, M. A. (2021). Neural presbyacusis in humans inferred from age-

related differences in auditory nerve function and structure. *Journal of*

Neuroscience, *41*(50), 10293-10304. https://doi.org/10.1523/JNEUROSCI.1747-

21.2021

Harris, K.C., Vaden Jr., K.I., McClaskey, C.M., Dias, J.W., & Dubno, J.R. (2018).

Complementary metrics of human auditory nerve function derived from compound

action potentials. *Journal of Neurophysiology, 119(3)*, 1019-1028. https://doi:

10.1152/jn.00638.2017

Hartmann, R., Topp, G., & Klinke, R. (1984). Discharge patterns of cat primary auditory

fibers with electrical stimulation of the cochlea. *Hearing Research*, *13*(1), 47-62.

https://doi.org/10.1016/0378-5955(84)90094-7

He, S., Skidmore, J., Koch, B., Chatterjee, M., Carter, B. L., & Yuan, Y. (2023).

Relationships between the auditory nerve sensitivity to amplitude modulation,

perceptual amplitude modulation rate discrimination sensitivity, and speech

perception performance in postlingually deafened adult cochlear implant users.

Ear and Hearing, *44*(2), 371-384. https://doi.org/10.1097/Aud.0000000000001289

He, S., Teagle, H.F.B., & Buchman, C.A. (2017). The electrically evoked compound action

potential: From laboratory to clinic. *Frontiers in Neuroscience, 11*, 339. https://doi:

10.3389/fnins.2017.00339

Heeringa, A. N., & Koppl, C. (2022). Auditory nerve fiber discrimination and

representation of naturally-spoken vowels in noise. *eNeuro*, *9*(1).

https://doi.org/10.1523/ENEURO.0474-21.2021

Heshmat, A., Sajedi, S., Johnson Chacko, L., Fischer, N., Schrott-Fischer, A., & Rattay,

F. (2020). Dendritic degeneration of human auditory nerve fibers and its impact on

the spiking pattern under regular conditions and during cochlear implant

stimulation. *Frontiers in Neuroscience*, *14*, 599868.

https://doi.org/10.3389/fnins.2020.599868

Holden, L. K., Finley, C. C., Firszt, J. B., Holden, T. A., Brenner, C., Potts, L. G., Gotter,

B. D., Vanderhoof, S. S., Mispagel, K., Heydebrand, G., & Skinner, M. W. (2013).

Factors affecting open-set word recognition in adults with cochlear implants. *Ear*

and Hearing, *34*(3), 342-360. https://doi.org/10.1097/aud.0b013e3182741aa7

James, C. J., Karoui, C., Laborde, M. L., Lepage, B., Molinier, C. E., Tartayre, M., Escude,

B., Deguine, O., Marx, M., & Fraysse, B. (2019). Early sentence recognition in adult

cochlear implant users. *Ear and Hearing*, *40*(4), 905-917.

https://doi.org/10.1097/AUD.0000000000000670

Javel, E., & Shepherd, R. K. (2000). Electrical stimulation of the auditory nerve. Iii.

Response initiation sites and temporal fine structure. *Hearing Research*, *140*(1-2),

45-76. https://doi.org/10.1016/s0378-5955(99)00186-0

Kandel, E. R. (2002). Disease of the motor unit. . In E. R. Kandel, J. H. Schwartz, & T. M.

Jessell (Eds.), *Principles of neural science* (4th ed., pp. 695-703). McGraw-Hill,

Health Professions Division.

Kim, J. H., Renden, R., & von Gersdorff, H. (2013). Dysmyelination of auditory afferent

axons increases the jitter of action potential timing during high-frequency firing.

Journal of Neuroscience, *33*(22), 9402-9407.

https://doi.org/10.1523/Jneurosci.3389-12.2013

Kirby, B., Brown, C., Abbas, P., Etler, C., & O'Brien, S. (2012). Relationships between

electrically evoked potentials and loudness growth in bilateral cochlear implant

users. *Ear and Hearing*, *33*(3), 389-398.

https://doi.org/10.1097/aud.0b013e318239adb8

Kraus, N., Bradlow, A. R., Cheatham, M. A., Cunningham, J., King, C. D., Koch, D. B.,

Nicol, T. G., McGee, T. J., Stein, L. K., & Wright, B. A. (2000). Consequences of

neural asynchrony: A case of auditory neuropathy. *Journal of the Association for*

Research in Otolaryngology, *1*(1), 33-45. https://doi.org/10.1007/s101620010004

Kumar, P., Sharma, S., Kaur, C., Pal, I., Bhardwaj, D. N., Vanamail, P., Roy, T. S., &

Jacob, T. G. (2022). The ultrastructural study of human cochlear nerve at different

ages. *Hearing Research*, *416*, 108443.

https://doi.org/10.1016/j.heares.2022.108443

Kusunoki, T., Cureoglu, S., Schachern, P. A., Baba, K., Kariya, S., & Paparella, M. M.

(2004). Age-related histopathologic changes in the human cochlea: A temporal

bone study. *Otolaryngology and Head and Neck Surgery*, *131*(6), 897-903.

https://doi.org/10.1016/j.otohns.2004.05.022

Lazard, D. S., Vincent, C., Venail, F., Van de Heyning, P., Truy, E., Sterkers, O.,

Skarzynski, P. H., Skarzynski, H., Schauwers, K., O'Leary, S., Mawman, D., Maat,

B., Kleine-Punte, A., Huber, A. M., Green, K., Govaerts, P. J., Fraysse, B., Dowell,

R., Dillier, N., . . . Blamey, P. J. (2012). Pre-, per- and postoperative factors

affecting performance of postlinguistically deaf adults using cochlear implants: A

new conceptual model over time. *PloS One*, *7*(11), e48739.

https://doi.org/10.1371/journal.pone.0048739

Lenth, R. (2023). emmeans: Estimated Marginal Means, aka Least-Squares Means. R

848   package version 1.8.6. https://CRAN.R-project.org/package=emmeans.

849   Levitt, H. (1971). Transformed up-down methods in psychoacoustics. *Journal of the*

850   *Acoustical Society of America*, *49*(2), 467-&. https://doi.org/Doi

851   10.1121/1.1912375

852   Linthicum, F. H., Jr., & Fayad, J. N. (2009). Spiral ganglion cell loss is unrelated to

853   segmental cochlear sensory system degeneration in humans. *Otology &*

854   *Neurotology*, *30*(3), 418-422. https://doi.org/10.1097/mao.0b013e31819a8827

855   Makary, C. A., Shin, J., Kujawa, S. G., Liberman, M. C., & Merchant, S. N. (2011). Age-

856   related primary cochlear neuronal degeneration in human temporal bones. *Journal*

857   *of the Association for Research in Otolaryngology*, *12*(6), 711-717.

858   https://doi.org/10.1007/s10162-011-0283-2

859   Merchant, S. N., Adams, J. C., & Nadol, J. B., Jr. (2005). Pathology and pathophysiology

860   of idiopathic sudden sensorineural hearing loss. *Otology & Neurotology*, *26*(2),

861   151-160. https://doi.org/10.1097/00129492-200503000-00004

862   Michalewski, H. J., Starr, A., Nguyen, T. T., Kong, Y. Y., & Zeng, F. G. (2005). Auditory

863   temporal processes in normal-hearing individuals and in patients with auditory

864   neuropathy. *Clinical Neurophysiology*, *116*(3), 669-680.

865   https://doi.org/10.1016/j.clinph.2004.09.027

866   Miller, C.A., Abbas, P.J., & Robinson, B.K. (2001). Response properties of the refractory

867   auditory nerve fiber. *Journal of the Association for Research in Otolaryngology*,

868   *2*(3), 216-232. https://doi: 10.1007/s101620010083

Nadol, J. B., Adams, J. C., & O'Malley, J. T. (2012). Temporal bone histopathology in a

case of sensorineural hearing loss caused by superficial siderosis of the central

nervous system and treated by cochlear implantation. *Otology & Neurotology*,

32(5), 748-755. https://doi.org/10.1097/mao.0b013e31820e7195

Nadol, J. B., Jr. (1990). Degeneration of cochlear neurons as seen in the spiral ganglion

of man. *Hearing Research*, *49*(1-3), 141-154. https://doi.org/10.1016/0378-

5955(90)90101-t

Nadol, J. B., Jr. (1997). Patterns of neural degeneration in the human cochlea and

auditory nerve: Implications for cochlear implantation. *Otolaryngology and Head*

and Neck Surgery, *117*(3 Pt 1), 220-228. https://doi.org/10.1016/s0194-

5998(97)70178-5

Nadol, J. B., Jr., Young, Y. S., & Glynn, R. J. (1989). Survival of spiral ganglion cells in

profound sensorineural hearing loss: Implications for cochlear implantation. *Annals*

of   Otology,   Rhinology   and   Laryngology,   *98*(6),   411-416.

https://doi.org/10.1177/000348948909800602

Parkins, C. W. (1989). Temporal response patterns of auditory nerve fibers to electrical

stimulation in deafened squirrel monkeys. *Hearing Research*, *41*(2-3), 137-168.

https://doi.org/10.1016/0378-5955(89)90007-5

Pinheiro, J., Bates, D., & R Core Team (2023). nlme: Linear and Nonlinear Mixed Effects

Models. R package version 3.1-162, https://CRAN.R-project.org/package=nlme.

Rance, G. (2005). Auditory neuropathy/dys-synchrony and its perceptual consequences.

Trends in Amplification, *9*(1), 1-43. https://doi.org/10.1177/108471380500900102

Rask-Andersen, H., Liu, W., & Linthicum, F. (2010). Ganglion cell and 'dendrite'

populations in electric acoustic stimulation ears. *Advances in Oto-Rhino-*

Laryngology, *67*, 14-27. https://doi.org/10.1159/000262593

Resnick, J. M., & Rubinstein, J. T. (2021). Simulated auditory fiber myelination

heterogeneity desynchronizes population responses to electrical stimulation

limiting inter-aural timing difference representation. *Journal of the Acoustical*

Society of America, *149*(2), 934-947. https://doi.org/10.1121/10.0003387

Rubinstein, J.T., Wilson, B.S., Finley, C.C., & Abbas, P.J. (1999). Pseudospontaneous

activity: stochastic independence of auditory nerve fibers with electrical

stimulation. *Hearing Research, 127*(1-2), 108-118.

Sachs, M. B., Voigt, H. F., & Young, E. D. (1983). Auditory nerve representation of vowels

in background noise. *Journal of Neurophysiology*, *50*(1), 27-45.

https://doi.org/10.1152/jn.1983.50.1.27

Sagers, J. E., Landegger, L. D., Worthington, S., Nadol, J. B., & Stankovic, K. M. (2017).

Human cochlear histopathology reflects clinical signatures of primary neural

degeneration. *Scientific Reports*, *7.* https://doi.org/10.1038/s41598-017-04899-9

Schvartz-Leyzac, K. C., & Pfingst, B. E. (2016). Across-site patterns of electrically evoked

compound action potential amplitude-growth functions in multichannel cochlear

implant recipients and the effects of the interphase gap. *Hearing Research*, *341*,

50-65. https://doi.org/10.1016/j.heares.2016.08.002

Shader, M. J., Gordon-Salant, S., & Goupell, M. J. (2020). Impact of aging and the

electrode-to-neural interface on temporal processing ability in cochlear-implant

users: Gap detection thresholds. *Trends in Hearing*, *24*, 233121652095656.

https://doi.org/10.1177/2331216520956560

Shepherd, R. K., & Hardie, N. A. (2001). Deafness-induced changes in the auditory

pathway: Implications for cochlear implants. *Audiology and Neuro-Otology*, *6*(6),

305-318. https://doi.org/10.1159/000046843

Shepherd, R. K., & Javel, E. (1997). Electrical stimulation of the auditory nerve. I.

Correlation of physiological responses with cochlear status. *Hearing Research*,

108(1-2), 112-144. https://doi.org/10.1016/s0378-5955(97)00046-4

Skidmore, J., Bruce, I. C., Yuan, Y., & He, S. (2023). *Quantifying neural synchrony at the*

level of the auditory nerve in cochlear implant users with recordings of the

electrically evoked compound action potential [poster sa34] [Poster]. Association

for Research in Otolaryngology (ARO) 46th MidWinter Meeting, Orlando, Florida.

Skidmore, J., Oleson, J. J., Yuan, Y., & He, S. (2023). The relationship between cochlear

implant speech perception outcomes and electrophysiological measures of the

electrically evoked compound action potential. *Ear and Hearing*, *44*(6), 1485-1497.

https://doi.org/10.1097/AUD.0000000000001389

Skidmore, J., Ramekers, D., Bruce, I. C., & He, S. (2022). Comparison of response

properties of the electrically stimulated auditory nerve reported in human listeners

and in animal models. *Hearing Research*, *426*, 108643.

https://doi.org/10.1016/j.heares.2022.108643

Sly, D. J., Heffer, L. F., White, M. W., Shepherd, R. K., Birch, M. G. J., Minter, R. L.,

Nelson, N. E., Wise, A. K., & O'Leary, S. J. (2007). Deafness alters auditory nerve

fibre responses to cochlear implant stimulation. *European Journal of*

Neuroscience, *26*(2), 510-522. https://doi.org/10.1111/j.1460-9568.2007.05678.x

Starr, A., Michalewski, H. J., Zeng, F. G., Fujikawa-Brooks, S., Linthicum, F., Kim, C. S.,

Winnier, D., & Keats, B. (2003). Pathology and physiology of auditory neuropathy

with a novel mutation in the mpz gene (tyr145 -> ser). *Brain*, *126*, 1604-1619.

https://doi.org/10.1093/brain/awg156

Suzuka, Y., & Schuknecht, H. F. (1988). Retrograde cochlear neuronal degeneration in

human subjects. *Acta Oto-Laryngologica Supplementum*, *450*, 1-20.

https://doi.org/10.3109/00016488809098973

Tasaki, I. (1955). New measurements of the capacity and the resistance of the myelin

sheath and the nodal membrane of the isolated frog nerve fiber. *American Journal*

of Physiology, *181*(3), 639-650. https://doi.org/10.1152/ajplegacy.1955.181.3.639

Torkildsen, J. V. K., Hitchins, A., Myhrum, M., & Wie, O. B. (2019). Speech-in-noise

perception in children with cochlear implants, hearing aids, developmental

language disorder and typical development: The effects of linguistic and cognitive

abilities. *Frontiers in Psychology*, *10*, 2530.

https://doi.org/10.3389/fpsyg.2019.02530

Ungar, O. J., Handzel, O., & Santos, F. (2018). Rate of spiral ganglion cell loss in

idiopathic sudden sensorineural hearing loss. *Otology & Neurotology*, *39*(10),

e944-e949. https://doi.org/10.1097/MAO.0000000000001992

van den Honert, C., & Stypulkowski, P. H. (1984). Physiological properties of the

electrically stimulated auditory nerve. Ii. Single fiber recordings. *Hearing Research*,

14(3), 225-243. https://doi.org/10.1016/0378-5955(84)90052-2

Viswanathan, V., Shinn-Cunningham, B. G., & Heinz, M. G. (2022). Speech

categorization reveals the role of early-stage temporal-coherence processing in

auditory scene analysis. *Journal of Neuroscience*, *42*(2), 240-254.

https://doi.org/10.1523/JNEUROSCI.1610-21.2021

Wasserstein, R. L., & Lazar, N. A. (2016). The asa statement on p-values: Context,

process, and purpose. *The American Statistician*, *70*(2), 129-133.

https://doi.org/10.1080/00031305.2016.1154108

Waxman, S. G., & Ritchie, J. M. (1993). Molecular dissection of the myelinated axon.

Annals of Neurology, *33*(2), 121-136. https://doi.org/10.1002/ana.410330202

Wu, P. Z., Liberman, L. D., Bennett, K., de Gruttola, V., O'Malley, J. T., & Liberman, M.

C. (2019). Primary neural degeneration in the human cochlea: Evidence for hidden

hearing loss in the aging ear. *Neuroscience*, *407*, 8-20.

https://doi.org/10.1016/j.neuroscience.2018.07.053

Xing, Y., Samuvel, D. J., Stevens, S. M., Dubno, J. R., Schulte, B. A., & Lang, H. (2012).

Age-related changes of myelin basic protein in mouse and human auditory nerve.

PloS One, 7(4), e34500. https://doi.org/10.1371/journal.pone.0034500

Zaltz, Y., Bugannim, Y., Zechoval, D., Kishon-Rabin, L., & Perez, R. (2020). Listening in

noise remains a significant challenge for cochlear implant users: Evidence from

early deafened and those with progressive hearing loss compared to peers with

normal hearing. *Journal of Clinical Medicine*, *9*(5).

https://doi.org/10.3390/jcm9051381

Zeng, F. G., Kong, Y. Y., Michalewski, H. J., & Starr, A. (2005). Perceptual consequences

of disrupted auditory nerve activity. *Journal of Neurophysiology*, *93*(6), 3050-3063.

https://doi.org/10.1152/jn.00985.2004

Zeng, F. G., Oba, S., Garde, S., Sininger, Y., & Starr, A. (1999). Temporal and speech

processing deficits in auditory neuropathy. *Neuroreport*, *10*(16), 3429-3435.

https://doi.org/10.1097/00001756-199911080-00031

Zimmermann, C. E., Burgess, B. J., Nadol, J. B. (1995). Patterns of degeneration in the

human cochlear nerve. *Hear Res, 90(1-2)*, 192-201. https://doi: 10.1016/0378-

5955(95)00165-1

TABLE 1. Demographic information of all study participants.
CI24RE (CA), Freedom Contour Advance electrode array; SHL, sudden hearing loss; AN, acoustic neuroma

Participant ID	Sex	Ear tested	Age (years)	Internal device and electrode array	Etiology of hearing loss	Electrodes tested for PLV	Electrodes tested for GDT	Speech scores included
A1	M	L	60s	CI512	SHL	4, 6, 9, 12	4, 9	•
A2	M	L	60s	CI512	Meniere's	3, 9, 12, 15	3, 18	•
A3	F	L	60s	CI24RE (CA)	Hereditary	3, 9, 15, 21	3, 15	•
A3	F	R	60s	CI24RE (CA)	Hereditary	3, 9, 15, 21	3, 21	•
A4	F	L	30s	CI24RE (CA)	Trauma	3, 9, 15, 21	9, 21	•
A5	F	L	50s	CI532	Unknown	4, 9, 15, 21	4, 21	•
A5	F	R	50s	CI24RE (CA)	Unknown	3, 9, 15, 21	9, 15	•
A6	M	R	60s	CI522	Trauma	6, 9, 18, 21	9, 15	•
A7	M	R	30s	CI24RE (CA)	Hereditary	3, 9, 15, 21	3, 15	•
A8	F	R	50s	CI24RE (CA)	Hereditary	3, 12, 15, 21	3, 21	•
A9	F	R	60s	CI532	Unknown	3, 9, 15, 20	3, 21	•
A10	M	R	70s	CI532	Trauma	3, 9, 15, 21		•
A11	F	L	70s	CI422	Noise	4, 9, 15, 20	9, 20	•
A12	M	L	60s	CI632	Unknown	3, 9, 15, 21	3, 21	•
A12	M	R	60s	CI532	Unknown	3, 9, 15, 20	3, 20	•
A13	F	L	70s	CI24RE (CA)	Autoimmune	3, 7, 12, 18	3, 18	•
A14	M	L	60s	CI532	AN	4, 9, 15, 21	9, 15	•
A15	F	R	80s	CI532	Hereditary	3, 7, 10, 17	7, 17	•
A16	F	L	30s	CI532	Unknown	3, 9, 15, 21		
A17	F	L	50s	CI532	Unknown	3, 9, 15, 21	9, 21	•
A18	F	L	70s	CI622	Unknown	6, 9, 15, 21		•
A19	M	R	80s	CI632	Unknown	3, 9, 15, 21	3, 9	•
A20	M	R	50s	CI632	SHL	3, 9, 15, 21		•
A21	F	L	50s	CI632	Unknown	3, 15, 18, 21	15, 18	•
A22	F	R	70s	CI622	Unknown	3, 9, 15, 21	3, 15	•
A23	M	L	50s	CI532	Usher	3, 9, 15, 21	3, 9	•
A24	M	L	70s	CI632	Unknown	3, 9, 15, 21	3, 9	•

992   **Table 2.** Results of pairwise comparisons for comparing phase locking values measured at different electrode locations.

Electrode Pair	Estimate	Standard Error	Degree of Freedom	T Ratio	p Value
E3 vs. E9	-0.022	0.021	30.2	-1.025	.736
E3 vs. E15	-0.080	0.023	26.9	-3.463	.009
E3 vs. E21	-0.087	0.031	30.9	-2.865	.035
E9 vs. E15	-0.059	0.016	27.8	-3.622	.006
E9 vs. E21	-0.066	0.028	33	-2.575	.067
E15 vs. E21	0.007	0.020	30.9	-0.352	.984

Figure 1. Representative data from participant A14 demonstrating the method for

estimating neural synchrony at the level of the cochlear nerve at individual electrode

locations in cochlear implant users. Top panels: Recordings of electrically evoked

compound action potentials (eCAPs) for individual trials (gray lines) with the across-trial

average (black line). The amplitude of the across-trial average is also provided. Bottom

panels: Heat maps indicating the phase-locking value (PLV) as a function of time and

frequency.

1002

Figure 2. Representative data recorded in the right ear of participant A3 demonstrating

the method for estimating neural synchrony at the level of the cochlear nerve at individual

electrode locations in cochlear implant users. Top panels: Recordings of electrically

evoked compound action potentials (eCAPs) for individual trials (gray lines) with the

across-trial average (black line). The amplitude of the across-trial average is also

provided. Bottom panels: Heat maps indicating the phase-locking value (PLV) as a

function of time and frequency.

1010

1011 **Figure 3.** The means and standard deviations of phase-locking values measured at four

1012 electrode locations in 24 adult cochlear implant users (27 ears).

1013

Figure 4. Phase-locking values and psychophysical gap detection thresholds measured at two electrode locations in each of 23 implanted ears of 20 participants. Lines connect the data measured at the two electrode locations tested in the same ear.

1020

1021 **Figure 5.** Stimulation levels and psychophysical gap detection thresholds measured at

1022 two electrode locations in each of 23 implanted ears of 20 participants. Lines connect the

1023 data measured at the two electrode locations tested in the same ear.

1024

1025

1026

1027

Figure 6. Consonant-Nucleus-Consonant (CNC) word scores measured in quiet and in two noise conditions as a function of the phase-locking value averaged across electrode locations for 23 adult cochlear implant users (26 ears). The best fit line across all 26 data points is illustrated with a solid line. The results from Pearson's correlation analysis are also provided in each panel.

1038

Figure 7. The change in Consonant-Nucleus-Consonant (CNC) word scores with the addition of background noise as a function of the phase-locking value averaged across electrode locations. The best fit line across all 26 data points is illustrated with a solid line. The results from Pearson's correlation analysis are also provided in each panel.