Comparisons of Auditory Steady State and Auditory Brainstem Response Thresholds in Infants with Normal Hearing and Conductive Hearing Loss

Hope Valeriote[1,2,3] and Susan A. Small[3]

[1]Audiology Services, Glenrose Rehabilitation Hospital, Edmonton, AB Canada

[2]Early Hearing Detection and Intervention Program, Alberta Health Services, AB Canada

[3]School of Audiology and Speech Sciences, The University of British Columbia, Vancouver, BC Canada

*Address for correspondence:
Hope Valeriote
Audiology Services, Glenrose Rehabilitation Hospital
10230 111 Ave, Edmonton, AB
Phone: (780) 735-6019
FAX: (780) 735-6013
email: hope.valeriote@ahs.ca

This research was supported by a Discovery Grant from the Natural Sciences and Engineering Research Council of Canada to Dr. Susan Small. Ethics approval for this project was obtained from the University of British Columbia's Clinical Research Ethics Board (certificate # H13-02445) and the University of Saskatchewan's Biomedical Research Ethics Board (certificate # 13-319).

Preliminary findings were presented in 2015 at Biennial Symposium of the International Evoked Response Audiometry Study Group IERASG: Valeriote, H., & Small, S. A. (2015). Comparison of air- and bone-conduction auditory brainstem and multiple 80-Hz auditory steady-state responses in infants with normal hearing and conductive hearing loss. Abstracts of the XXIV Biennial Symposium of the International Evoked Response Audiometry Study Group IERASG (May 10–14; Busan, Korea). Retrieved April 4, 2015, from http://www.ierasg 2015.org

Acknowledgements

Dr. Susan Small was supervisor and mentor for the first author's M.Sc. thesis research. Sadly, Dr. Small passed away in 2022. Thanks to Dr. Charlotte Douglas for her assistance in obtaining ethics approval, recruitment of participants and supervision of data collection; Drs. Robert Burkard and David Stapells for their mentorship in the preparation of this manuscript, and Alex Gascon for his assistance with data analysis.

ABSTRACT

This study investigates how well the air- and bone-conduction auditory steady-state response

detects mild conductive hearing loss compared to the auditory brainstem response in young

infants. Air-bone gap sizes are compared between infants with normal hearing and conductive

loss using a two-group cross-sectional design. Twenty-three (500 Hz) and 22 (2000 Hz) infants

(0-6 months of age) with normal hearing and 15 (500 Hz) with conductive loss were recruited

from newborn hearing screening. Thresholds were obtained to frequency-specific air- and bone-

conducted stimuli. There were no instances of conductive loss at 2000 Hz. 500 Hz mean

thresholds and air-bone gap sizes were compared. Sensitivity and specificity for identifying

conductive loss were measured. Overall, mean bone-conduction thresholds were similar between

groups, and mean 500-Hz air conduction thresholds were higher with larger air-bone gap size for

infants with conductive loss. Sensitivity and specificity for identifying conductive loss was

highest for air-conduction auditory brainstem response threshold measurement compared to

screening and auditory steady-state response threshold measurements. The variability of auditory

steady-state response thresholds and air-bone gap size was too great to reliably separate normal

hearing from mild conductive loss compared to the auditory brainstem response. More research

is needed using infants with varying degrees of hearing loss at multiple frequencies to fully

assess the appropriateness of the auditory steady-state response as a clinical diagnostic tool for

an infant population.

Keywords : Auditory Brainstem Response (ABR), Auditory Steady-State Response (ASSR), Air-
conduction, Bone-conduction, Air-bone gap

Comparisons of Auditory Steady State and Auditory Brainstem Response Thresholds in Infants

2   with Normal Hearing and Conductive Hearing Loss

Early hearing detection and intervention (EHDI) programs continue to be implemented

internationally and are a major driving force for current research on infant hearing. Within this

context, finding more efficient, less time-consuming methods of evaluating hearing in young

infants has been of interest with some looking for alternatives to the current diagnostic gold-

standard method, the auditory brainstem response (ABR), to integrate in their programs. For

decades, the ABR has been the proven and reliable method that major EHDI (Bagatto, 2020;

Hatton, Van Maanen & Stapells, 2022; JCIH, 2019) rely on to identify hearing loss in the infant

population. Like behavioural methods of auditory assessment, ABR thresholds can be obtained

using both air- and bone-conducted stimuli (Stapells & Ruben, 1989; Yang et al., 1987, 1993).

Bone-conduction (BC) ABR assessment of infant hearing is required to differentiate between

conductive and sensorineural hearing losses when air-conduction (AC) thresholds are elevated

(Hatton et al., 2012). When conductive hearing loss (CHL) is present, an air-bone gap can be

seen between elevated AC and normal BC thresholds.

Previous research to assess optimal testing conditions, including bone oscillator

placement on the infant head and coupling method (i.e., handheld vs. band) and force, have

informed clinical best practice in assessing BC thresholds in this young population who is unable

to respond behaviourally (Small et al., 2007; Yang et al., 1991). The ASSR is another auditory

evoked potential that is of interest to clinicians and researchers as an alternative to ABR because

it also assesses hearing using both AC and BC stimuli, with the added benefit of testing multiple

frequencies and ears simultaneously.The decision to use the ASSR as a method to assess infant

hearing requires clear demonstration that the ASSR is comparable (or superior) to current gold-

standards in its ability to assess infant AC and BC frequency-specific hearing thresholds in an

accurate and precise way. An EHDI program requires high sensitivity to detect hearing loss in its

target population and high specificity in differentiating elevated from normal hearing levels.

Comparisons are needed between the ASSR and current gold-standard methods that take into

account the participants' age (i.e., behavioural audiometry as the gold standard for infants >6

months and ABR for infants ≤6 months, JCIH, 2019), AC and BC modes of presentation, and

hearing presentations from normal hearing ability to all degrees of sensorineural, conductive and

mixed hearing loss. Maturational changes in BC ASSR responses and infant/adult differences in

skull properties are discussed in Small & Stapells (2008a). Given these differences, it is

important to understand how the BC ASSR behaves in infants with hearing loss. External ear

canal changes and maturation for AC are understood and can be measured, but maturation effects

for these infants are not as well documented for BC results. Understanding this is relevant to

understanding the ASSR/ABR and their clinical use.

A review of the literature shows that many of these comparisons have been investigated

and published over the last few decades and comparisons between ASSR and behavioural

thresholds to date have been encouraging. For example, several studies have shown that AC and

BC ASSR and behavioural thresholds in infants with normal hearing (NH) (Casey & Small,

2014; Luts et al., 2006) and infants with hearing loss (Aimoni et al., 2018) correlate highly. One

study with a small number of participants also suggests the BC ASSR is able to identify normal

cochlear sensitivity in young children with conductive hearing loss (Nagashima et al., 2013).

It is known that there are differences in ASSR thresholds by age likely due to skull

maturation (discussed in detail in Casey & Small, 2014 and Small & Stapells, 2008a); however,

the ASSR introduces other possible factors to consider, such as the use of high stimulus rates and

multiple stimuli, that may have an effect on ASSR thresholds that does not apply to the ABR. It

is especially important to establish a comprehensive body of literature for infants who are too

young to respond behaviourally and who define the target population for EHDI programs.

Studies comparing AC ASSR thresholds to the tone-ABR (using varied stimulus parameters and

test protocols) thus far have shown that AC ASSR thresholds (in dB HL) in infants with NH and

with hearing loss are consistently poorer than AC ABR thresholds (in dB nHL) but are highly

correlated and accurate (Michel & Jørgensen, 2017; Rance et al., 2006; Rance & Rickards, 2002;

Rodrigues et al., 2010; Van Maanen & Stapells, 2009, 2010). More recently, however, at least

one other study using different collection protocols and stimulus parameters have suggested the

reverse, with thresholds (in dB eHL) for ABR being poorer than for ASSR (Sininger et al., 2018)

This latter study, however, used larger correction factors for ASSR compared to ABR, which

may explain this finding. More studies with infants with hearing loss are needed, but the existing

AC ASSR data appear promising. Studies that compare frequency-specific BC toneburst-ABR

thresholds with sinusoidal amplitude modulated (SAM) tone ASSR thresholds in young infants

with NH and hearing loss are significantly lacking and is the focus on the present study. Small &

Stapells (2008a) published BC ASSR normative data proposing a set of "normal" or minimum

ASSR intensities, among others, for infants 0-11 months but did not compare frequency specific

BC ASSR to BC ABR. Swanepoel et al. (2008) did provide some BC ASSR data for infants with

hearing loss, but did not compare these results to toneburst ABR results and tested a broad age

range (0.25-11.5 years of age). To our knowledge, no data comparing BC ASSR to BC ABR

thresholds in young infants with hearing loss exist in the form of peer-reviewed publications.

For the present study, AC and BC ABR and ASSR thresholds in NH infants and infants

with CHL confirmed by the gold-standard ABR thresholds were compared to investigate the

following questions:

(1) What are ABR and ASSR thresholds in young infants with NH and CHL?

(2) How does the air-bone gap (ABG) compare between ABR and ASSR in young

infants with NH and CHL?

(3) What are appropriate minimum intensity cutoffs to differentiate NH from CHL using

AC and BC ASSR in young infants?

(4) Does the ASSR detect CHL as well as the ABR in young infants?

Methods

Stimulus and recording setups for ABR followed those described in the BCEHP ABR protocol

(Hatton et al., 2022). Stimulus and recording setups for ASSR were similar to those described in

Casey & Small (2014), with minor differences between the research and clinical versions of the

MASTER software. Details of methodology for ABR and ASSR are provided below.

Participants

Infants were recruited through the newborn hearing screening program at the Royal

University Hospital, Saskatoon. Participants were recruited if they failed newborn hearing

screening or if they were unable to be screened at birth. Participation was entirely voluntary.

Sixty four infants between the ages of 0 and 6 months participated (NH mean age = 7.36 weeks,

range 0.6-12.9 weeks, CHL mean age = 6.71 weeks, range 2.9-20.6 weeks); 61 from the well-

baby nursery and 3 graduates from the neonatal intensive care unit (NICU), none of whom

presented with congenital aural atresia or microtia. Fourteen infants were excluded because they

did not sleep and did not complete any conditions of the testing session.

Each frequency (500 and 2000 Hz) was assessed individually and was categorized as a

normal hearing or conductive hearing loss threshold based on the relationship between the AC

and BC ABR results. In other words, if AC ABR was within normal limits at a specific

frequency, that frequency's threshold was placed in the normal hearing group. If AC ABR was

elevated with normal BC ABR results at the same frequency, the frequency's threshold was

placed in the conductive hearing loss group. Normal versus elevated levels correspond to those

specified in the British Columbia Early Hearing Program (BCEHP) protocols. The BCEHP

minimum stimulus intensities for 500 Hz are AC: 35 dB nHL BC: 20 dB nHL and for 2000 Hz

are AC: 30 dB nHL and BC: 30 dB nHL (Hatton, Van Maanen, & Stapells, 2022).

Results were included in the analysis whether partial or complete conditions were

obtained. Infants who did not complete any portion of the protocol due to inability to sleep were

excluded.

To verify the status of the middle ear and hearing at the time of testing, 1000 Hz

tympanometry and transient-evoked otoacoustic emissions (TEOAEs) were performed using a

Madsen AccuScreen and the OTOflex. The primary purpose of the screening measures was to

corroborate the presence of middle ear pathology when participants were identified with CHL

shown by abnormal tympanograms and absent TEOAEs and to determine the follow-up protocol

as per the Royal University Hospital guidelines. The cross-check principle has been used in

pediatric audiology for decades. As Hall (2016) describes, "no auditory test result should be

accepted and used in the diagnosis of hearing loss until it is confirmed or crosschecked by one or

more independent measures." TEOAE stimulus levels ranged from 70-84 dB SPL and used

noise-weighted averaging. The response detection method involved the counting of significant

signal peaks with self-calibration depending on ear canal volume. To pass the TEOAE test, a

total of eight valid peaks in alternating directions (counted both above and below the median

line) must be present. Of the 50 participants who completed the testing, 31 did not pass

tympanometry and 31 did not pass OAEs. A tympanogram was considered to be a "refer" if there

was no identifiable peak, or maximum admittance was less than or equal to 0.6 mmho

compensated from the negative tail at -400 daPa, and thus, the tympanogram was considered flat

(type B). Type B tympanograms (Jerger, 1970) show minimal or no mobility of the tympanic

membrane supportive of otitis media with effusion (OME) and is considered to be abnormal

tympanometric pattern. TEOAEs were considered to be a "refer" if there was a response in fewer

than three bands. Data collection took place in the context of a single audiology visit per

participant, and the results of any medical and/or audiological follow-up is unknown.

Stimuli

AC stimuli were presented to participants using an ER-3A insert earphones in one ear

(the same ear that was used to establish BC thresholds). BC stimuli were presented to

participants using the B-71 bone oscillator placed on the mastoid, slightly posterior to the upper

portion of the pinna for both ABR and ASSR testing. Small et al. (2007) showed no difference

between lower and upper mastoid bone oscillator placement, so the upper portion was chosen to

avoid interfering with the nearby mastoid electrode. This was coupled to the head with

approximately 400 grams of force using the hand-held method (i.e., held by the first author).

This coupling method was used as it was the least disruptive method to the infants' sleep and

was found to have no significant differences to thresholds obtained by the elastic headband

coupling method (Small et al, 2007). The examiner was trained to apply 400 grams of force (425

± 25 g) by practicing BC application on a compressive spring scale, pressing down on the

transducer with one or two fingers until the desired force was achieved with feedback. Once

trials were completed with feedback, additional trials were completed without feedback, in a

method similar to Small et al. (2007). Once it was determined that examiner was adequately

trained, data collection began. Force was not verified on the infant head during testing. For ABR

testing, the Intelligent Hearing Systems (IHS) SmartEP was used to generate and present stimuli.

BCEHP-specified stimuli were used for both 500 and 2000 Hz (Hatton, Van Maanen, & Stapells,

2022). These stimuli were exact-Blackman-windowed tones (five-cycle total duration, no

plateau) and presented at a rate of 39.1/sec to one ear (Hatton et al., 2019, 2022; Janssen et al.,

2010). For ASSR testing, the two-channel Master II Clinical System was used to generate and

present ASSR stimuli with carrier frequencies 500, 1000, 2000 and 4000 Hz. These stimuli were

AM^2 at modulation frequencies 78, 85, 93 and 101 Hz for carrier frequencies 500, 1000, 2000

and 4000 Hz, respectively, and were presented simultaneously to one ear ("monotic multiple,

MM" ASSR).

Calibration

ABR Stimuli

AC stimuli were calibrated in dB nHL using ppeSPL with a Quest 177 sound level meter

and G.R.A.S. DB 0138 2-CC coupler with 1-inch microphone. The acoustic calibrations for 0 dB

nHL for AC using insert earphones, were 22 and 20 dB ppe SPL for 500 Hz and 2000 Hz,

respectively. BC stimuli were calibrated using the B & K 4930 artificial mastoid, where the

acoustic calibration for 0 dB nHL for BC using the B-71 bone oscillator were 67 and 49 dB re:

1μN ppe at 500 and 2000 Hz, respectively [see Stapells & Small (2017), British Columbia Early

Hearing Program (Hatton, Van Maanen, & Stapells, 2022) or Ontario Infant Hearing Program

(Bagatto, 2020) protocols for Canadian ppeRETSPLs and ppeRETFLs].

ASSR Stimuli

AC ASSR stimuli were calibrated in ppe SPL using the dB SPL RETSPLs as per ANSI

(1996) using a Quest 177 sound level meter and G.R.A.S. DB 0138 2-CC coupler with 1-inch

microphone. Each of the four frequencies were calibrated separately in dB HL and then

combined. Calibrations for 0 dB HL for AC using insert earphones was 5.5 and 3 dB SPL for

500 Hz and 2000 Hz, respectively (ANSI, 1996). BC stimuli were similarly calibrated using

(ANSI, 1996) RETFLs with the Quest 177 sound level meter and B & K Mastoid 4930 artificial

mastoid. Calibrations for 0 dB HL were 58 and 31 dB re: 1μN for BC at 500 and 2000 Hz,

respectively.

Recording

All participants were tested at the Royal University Hospital, Saskatoon in a double-

walled sound-attenuating booth. All recordings were obtained using the Intelligent Hearing

Systems SmartEP ABR system and the Master II Natus/Biologic clinical ASSR System. Four

disposable electrodes were placed on the infant's scalp using the typical electrode montage for

infant ABR testing: one (non-inverting) electrode on the vertex, an (inverting) electrode on each

mastoid and the common electrode off-center on the forehead. Impedance for each electrode was

less than 3 kOhms.

For ABR testing, standard BCEHP parameters were used at the time of data collection.

Gain was set to 100,000 and band-pass filtering from 30 to 1500 Hz with an artifact rejection of

± 25 μV. One channel was recorded for AC ABR conditions and two channels were recorded

(i.e., the ipsilateral and contralateral montages) for BC ABR conditions. A minimum of two

replications of 2000 trials each was obtained at threshold levels and one step (of 10 dB) below

threshold. The presence and/or absence of a response were determined visually and by objective

measures (signal to noise ratio and residual noise) and was interpreted by the first author. A

response being "present" was determined by a visually identifiable wave V in the averaged

waveform in the ipsilateral channel recording for AC ABR and by an ipsilaterally dominant

wave V response for BC ABR when ipsilateral and contralateral recordings were compared

(Hatton et al., 2022). In accordance with BCEHP guidelines, "no response" was determined only

when no visually identifiable wave V was present and residual noise was less than or equal to

0.08 µV (Hatton, Van Maanen, & Stapells, 2022). For ABR measures, where a response was

identified, RN and SNR measures were used to support visual interpretation where possible, but

ultimately visual identification of a response was considered sufficient to determine "response

present". "No response" judgements were made on the basis of both visual interpretation but also

with IHS-SmartEP SNR values <1 and RN ≤0.08uV. The participants were classified as having

CHL at a frequency by demonstrating elevated AC ABR results with normal BC ABR results

(based on BCEHP levels) with abnormal tympanometry findings. In the classification of

particpants, tympanometry and OAE screening was used only as a cross-check to confirm CHL

where identified at a specific frequency to provide additional evidence in the identification of

CHL. The NH group did not have a specific criterion for tympanometry or OAE screening result

and that categorization was made on the basis of normal AC and BC ABR thresholds alone at

that frequency. To ensure the validity in this method of categorization, an independent samples t-

test was performed comparing AC ABR and ASSR NH thresholds in infants with normal OAE

screening results and abnormal OAE screening results for 500 Hz and 2000 Hz separately and

was not significant. This supports the validity of this method of categorization. Where the

typical clinical protocol used in BCEHP does not include testing down to threshold if a present

response has been established at the minimum stimulus intensity, testing down to threshold for

all measures completed (AC and BC ABR and ASSR) did take place in this study.

For ASSR testing, two-channels were recorded but only the ipsilateral channel (i.e., vertex-

ipsilateral mastoid) was examined when determining response presence or absence and was the

only channel analyzed in this study. For ASSR measures, no visual identification was required,

as only SNR (p value) and residual noise were used to make response/no-response

determinations. Masking was not used as the interaural attenuation for infants reported by Small

& Stapells (2008b) is at least 10-30 dB. The EEG was filtered using a 30-150 Hz filter and

amplified 10 000 times with artifact rejection set to ± 125 µV. The analog-to-digital conversion

rate was 1200 Hz. Each sweep consisted of 16 epochs of 1024 data points and took 13.107

seconds of recording time. The ASSRs were averaged in the time domain and analyzed online in

the frequency domain using a fast Fourier transform (FFT) with a resolution of 0.076 Hz over a

range of 0-625 Hz. Amplitudes were measured baseline-to-peak and expressed in nV. Recording

continued until there was a response present with a minimum of 10 sweeps, or the residual noise

levels were at least <15 nV and there was a minimum of 10 sweeps completed; whichever came

first. A F-ratio was calculated by the MASTER II system and a response was considered present

if a significant response value ($p<0.05$), was obtained from the F-ratio compared to critical

values for $F(2, 240)$ for at least three consecutive sweeps. The F-ratio estimated the probability

that the amplitude of the ASSR at the modulation frequency was significantly different from the

average amplitude of the noise at adjacent frequencies. This was calculated within 120 bins, or

+/-60 bins from the modulation frequency (John & Picton, 2000). A response was considered

absent if no significant response value was obtained (p>0.05) and the noise value was

appropriately low (<15 nV).

Procedure

One session lasting between one and three hours took place for each subject. Before

testing began, caregivers consented to participation in the study and were provided a small

honorarium. All infants completed a hearing screening (tympanometry and transient evoked

otoacoustic emissions [TEOAEs]), ABR and ASSR testing in the recording session. One ear was

chosen to be tested using electrophysiologic methods. The selection of test ear was made based

on the outcome of the hearing screening. If only one ear failed, that ear was tested using ABR

and ASSR; if both ears failed, or both ears passed, the ear was chosen based on the most

comfortable position for the infant and the caregiver. Testing was completed with the examiner

inside the booth, next to the infant and caregiver. The examiner held the oscillator and

continually monitored the placement of the earphone in the infant's ear.

Hearing screening using TEOAEs and 1000 Hz tympanometry was conducted and

electrodes were applied while the infant was awake. The infant was given the opportunity to fall

asleep before ABR and ASSR testing began and remained asleep during these tests in the

caregiver's arms during ABR and ASSR testing. If the infant woke during the session, an

opportunity for them to fall back of sleep was given before testing continued.

Electrophysiological testing always began with ABR in order to provide parents with

information from a "gold-standard" test before proceeding with ASSR. AC ABR was followed

by BC ABR.

ABR testing began at BCEHP minimum stimulus intensities that correspond to the upper

limit of normal hearing. For AC ABR, testing began at 35 dB nHL and 30 dB nHL for 500 Hz

and 2000 Hz, respectively. BC ABR testing began at 20 dB nHL and 30 dB nHL for 500 and

2000 Hz, respectively. No masking was used given the age group of the participants and large

interaural attenuation. A 10 dB bracketing method was used. Threshold levels were defined as

the lowest level at which a response is present with an absent response 10 dB below. The lowest

level tested was 0 dB nHL for 2000 Hz AC and BC and 500 Hz BC, and 5 dB nHL for 500 Hz

AC due to starting levels and 10 dB step sizes.

ASSR testing began at 30 dB HL, corresponding to the highest "minimum level"

obtained by Casey & Small (2014). Similar to the ABR testing procedure, a 10 dB bracketing

method was used, and threshold was defined as the lowest level at which a response is present

with an absent response 10 dB below. The lowest level tested was 0 dB HL for ASSR. As the

study was more interested in BC comparisons, BC ASSR was prioritized over AC and was

completed first. Thresholds were found using a 10 dB bracketing procedure. If a response was

present, intensity was decreased by 10 dB. If no response was present, intensity was increased by

20 dB. Testing continued down to threshold.

In the sections to follow, only 500 Hz data for NH and CHL groups will be discussed.

Although 2000 Hz data was collected (shown in Table 2), as there were no instances of CHL

observed at 2000 Hz, these data are only briefly addressed in the remainder of this article.

Data Analyses

AC and BC ABR and ASSR Thresholds

Measures of central tendency and dispersion are provided for each frequency condition

(500 & 2000 Hz) by group (NH, CHL). Independent samples t-tests were performed to compare

500 Hz AC and BC ABR and ASSR thresholds between NH and CHL groups.

Air-Bone Gaps

Air-bone gap (ABG) between ABR and ASSR in infants with NH and CHL were

compared. Air-bone gaps (ABG) were calculated for ABR by subtracting the BC (nHL)

threshold from AC (nHL) threshold for each subject. ASSR ABGs were calculated by

subtracting the BC (dB HL) threshold from the AC (dB HL) threshold. For 500 Hz, an

independent samples t-test was then conducted to determine if means between groups were

significantly different. Differences in thresholds were considered significant at the $p<0.05$ level.

Minimum 'Normal' Intensities

Individual and mean AC and BC ABR and ASSR thresholds were determined for NH

(500 and 2000 Hz) and CHL (500 Hz) groups. "Minimum normal intensities" represent the

minimum test intensity a response would need to be present in a clinical setting to confirm

normal hearing. Minimum intensities were determined by calculating the cumulative percent of

responses present at each stimulus level for each testing method and mode of presentation. The

intensity at which greater than 90 percent of normal-hearing infants had a response was

considered the "minimum intensity" (e.g., Van Maanen & Stapells, 2009; Small & Stapells,

2008). Ninety percent was chosen to represent a intensity that separates "normal" from

"elevated" well according to the gold-standard threshold measure, ABR. The intensities for BC

ABR have been assessed by Hatton et al. (2012).

Sensitivity and Specificity for Conductive Hearing Loss Detection

Sensitivity and specificity using ASSR was measured using the ABR as the gold standard

to determine whether the ASSR detects CHL as well as the ABR. Sensitivity and specificity of

the OAE/tympanometry screening, AC ASSR threshold and air-bone gap and ABR air-bone gap

were also measured. These were calculated as shown in Table 1.The 500 Hz ABR and ASSR

thresholds were averaged separately for AC and BC, and 500 Hz thresholds were compared

between normal and CHL groups. Analyses were performed using an independent samples t-

tests. Differences in thresholds were considered significant at the p<0.05 level.

<INSERT TABLE 1 >

6   **Results**

7   Mean thresholds (as well as SD) for both 500 and 2000 Hz ABR/ASSR AC and BC

thresholds can be found in Table 2. For infants with confirmed CHL, mean AC ABR thresholds

increased compared to infants with NH. Mean AC ABR and ASSR thresholds at 500 Hz were

larger for infants with CHL. Standard deviations were greater for ASSR thresholds compared to

ABR thresholds for both AC and BC. No infants demonstrated CHL at 2000 Hz (as defined as an

elevated 2000 Hz AC threshold in the presence of a 2000 Hz BC threshold within normal limits)

and for this reason are not discussed in sections to follow.

<INSERT TABLE 2>

500 Hz ABR and ASSR Thresholds for CHL and NH Groups

16   Independent samples t-tests showed AC ABR thresholds for the CHL group were higher

than thresholds for the normal-hearing group[$t(36) = -10.95$, $p<0.001$]. BC thresholds did not

significantly differ across groups [$t(37) = -0.67$, $p=0.51$]. AC ASSR thresholds for the CHL

group were also higher than thresholds for the NH group [$t(34) = -2.10$, $p=0.043$]. BC ASSR

thresholds did not significantly differ across groups [$t(36) = 0.56$, $p=0.579$]. Levene's Test for

equality of variances was not significant, so equal variances were assumed. AC ABR and ASSR

and BC ASSR and ABR thresholds were not correlated [AC slope = 0.17, intercept = 26.67, $r^2 =$

0.04; BC slope = 0.15, intercept 15.35, $r^2 = 0.01$].

Air-bone Gap for CHL vs. NH Groups

The air-bone gaps (ABGs) at 500 Hz for the groups with NH and CHL are shown in

Table 3, Figure 1 (ABR) and Figure 2 (ASSR). On average, the mean 500 Hz ABGs for the two

groups were as follows: (i) ABR NH: 15 dB, (ii) ASSR NH: 12 dB (iii) ABR CHL: 36 dB, (iv)

ASSR CHL: 21 dB. Two outliers were present in the ABR ABG data set for the CHL group.

The independent samples bootstrapped t-test comparing mean ABR ABG for the NH and CHL

group showed significantly larger ABGs for the CHL group than in the NH group [t(35) = -7.74,

p<0.001]. Outliers were defined as a data point that is greater than the upper quartile + 1.5x the

interquartile range. A bootstrapped t-test was used to account for the outliers. Similarly, for the

ASSR, the independent samples t-test showed ABGs were also significantly larger in CHL group

[t(33) = -2.30, p=0.028]. Levene's Test for equality of variances was not significant, so equal

variances were assumed. The majority of NH participants had 500-Hz ABR ABGs 25 dB or

smaller (21 of 22) and CHL subjects of 35 dB or larger (13 of 15). As shown in Figures 1 and 2,

compared to ABR, there was more overlap between ASSR NH and CHL groups where the

majority of NH participants had ASSR ABGs of 20 dB or smaller and CHL of 10 dB or larger.

ABR and ASSR ABG size, however, was poorly correlated (slope = 0.24, intercept = 10.02, r^2 =

0.07). For 2000 Hz, the mean ABG for the NH group was approximately -5 and 3 dB for ASSR

and ABR, respectively; the majority of NH infants had 2000-Hz ABR ABGs 10 dB or smaller

(20 of 22), and 10 dB or smaller for ASSR (18 of 20).

<INSERT TABLE 3>

< INSERT FIGURE 1 >

< INSERT FIGURE 2>

Minimum "Normal" Intensities

1    The minimum intensity cutoffs for ABR and ASSR were determined for AC and BC

2 separately by calculating the cumulative percent of responses present at each stimulus intensity

3 for each testing method and mode of presentation. The intensity at which greater than 90 percent

4 of NH infants had a response was considered the "minimum intensity". For ABR, the minimum

5 intensity levels were 30 dB nHL for 2000 Hz AC and BC, and 35 and 20 dB nHL for 500 Hz AC

6 and BC, respectively. For ASSR, the minimum intensity levels were 40 dB HL for 2000 Hz AC

7 and BC and 40 and 30 dB HL for 500 Hz AC and BC, respectively. Minimum ASSR intensities

8 (in dB HL) were found to be higher for AC compared to BC and higher for ASSR compared to

9 the ABR minimum intensities (in dB nHL) used by the BCEHP.

10 **Sensitivity and Specificity for CHL Detection**

11    Table 4 compares sensitivity and specificity for each test completed using different cutoff

12 criteria. Sensitivity and specificity is calculated, with reference to NH or CHL diagnosis using

13 the gold standard ABR, for: Tympanometry/OAE screening, ASSR and ABR ABG size, and AC

14 ASSR thresholds. The subtype for each test category that had the highest specificity and a

15 sensitivity exceeding 90% are bolded. For such a test to be used in the context of an early

16 hearing detection and intervention program, there is very low tolerance for missing cases of

17 hearing loss, so sensitivity must be high. With sensitivity prioritized, the bolded values highlight

18 those where the sum of the two was the largest.

19 <INSERT TABLE 4>

20            **Discussion**

21 **ABR vs ASSR threshold differences**

22    ABR and ASSR thresholds differed when measured in the same infant and were found to

23 be poorly correlated in the present study (AC slope = 0.17, intercept = 26.67, r^2 = 0.04; BC slope

= 0.15, intercept 15.35, r^2 = 0.01). Given the narrow range of thresholds obtained, this is not

surprising. Previous studies have shown strong correlations between ABR and ASSR thresholds,

and they are thought to measure responses from approximately the same part of the auditory

system (Van Maanen & Stapells, 2010; Sininger et al. 2018, etc).. For these reasons, it was

expected that the ABR and ASSR thresholds would be similar. Threshold differences in the

present study may be in part due to the 0 dB HL/nHL values used for ABR and ASSR , starting

intensities being offset by 5 dB (i.e., ABR at 35 dB nHL and ASSR 30 dB HL), a 10 dB step

size, and the rather modest AC threshold shifts due to mild CHL. If smaller step sizes, similar

starting levels were used and populations with greater degrees of CHL were used, this difference

may have followed the trend of Rance et al. (2006) where the difference between thresholds

became minimal when converted to like units. Other contributors to the ASSR-ABR differences

are potentially related to an insufficiently large sample size and a difference in stimuli.

Air-Bone Gaps

To our knowledge, this is the first study to compare AC and BC ASSR thresholds within

participants in infants with ABR-confirmed NH and CHL. ABGs for both ABR and ASSR CHL

groups were larger than their NH counterparts, as expected. We had anticipated that threshold

differences would be observed between ASSR and ABR thresholds because dB nHL threshold

values were used for ABR (i.e., thresholds that included a consideration of temporal integration

issues) whereas the dB HL values for SAM tones were based on dB HL values for long-duration

tones as specified in ANSI S3.6. However, we also anticipated the differences in threshold for

ASSR and ABR to be similar for AC and BC stimuli, thus no impact to estimated ABGs was

expected (i.e., whatever differences may be present between ABR and ASSR would affect AC

and BC thresholds similarly and thus the ABG would not be greatly affected across these

measures). ABR and ASSR ABGs for the NH group did not differ significantly, however CHL

ABR and ASSR ABGs did differ significantly.

We also expected that the ABGs for ABR and ASSR would be larger in infants with CHL

than with NH and this was confirmed. In clinical practice when using behavioural methods of

assessment, clinicians operate under the assumption that individuals with NH and sensorineural

hearing loss do not exhibit clinically significant ABGs; while those with CHL are expected to

show an ABG. In adult audiometry, with test/retest reliability in behavioural audiometry of ±5

dB, an ABG ≥15 dB is often considered clinically significant and this tends to be extrapolated in

clinical practice to define clinically significant ABG sizes in pediatric assessments.

In the clinical setting, it is challenging to assess the magnitude of the ABR and ASSR

ABGs for several reasons. First, most ABR/ASSR clinical protocols do not encourage testing

down to true threshold (at least, not in Canada), but rather recommend the use of d "minimum

normal intensities" where if a response is present, it is considered within normal limits and

testing at lower presentation intensities is not required. The goal of most Canadian EHDI

Programs is to detect permanent congenital hearing losses ≥30 dB HL and this method of

assessment accomplishes this goal in a time-effective manner. Second, ABGs for clinical use (in

many provinces in Canada) are calculated on the estimated hearing levels (eHL) values for ABR

after nHL-to-eHL correction factors have been applied. The purpose of these frequency- and

mode-specific correction factors is to more closely estimate pure-tone behavioural (dB HL)

thresholds used for diagnostic and hearing aid fitting purposes (see the most current BCEHP

clinical protocol for up-to-date correction factors, corresponding stimulus parameters and

recording techniques; Hatton et al., 2022). When AC and BC eHL correction factors are applied,

they come with their own estimation errors (as much as 10-20 dB of error in either direction),

and these errors are additive when calculating the ABG. These estimation errors in combination

with using 10-dB step sizes and/or not testing down to a true threshold make ABG estimations in

clinical practice challenging. The ABR or ASSR ABG can be substantially under- or over-

estimated, and therefore are more appropriately used in a descriptive way to comment on the size

of a conductive component rather than a singular diagnostic criterion. It is important that clinical

protocols recognize these limitations. Clinicians need to keep in mind that unique correction

factors are applied to each individual frequency and differ for AC and BC. When investigating

the diagnostic power of ABG size, this can apply only to a specific frequency and cannot not be

generalized beyond the frequency that is being investigated. Carefully determined correction

factors are necessary and will affect any measure of the ABG. More data is needed for each

frequency with different degrees of CHL. This study continues to support the value of the ABG

as a descriptive tool to *accompany* frequency-specific ABR thresholds and tympanometry

measures in differentiating NH from CHL.

Normal Hearing Thresholds and Minimum Intensities

As shown in Tables 5 and 6, across several studies, normal ASSR intensity levels (i.e.,

ASSR threshold level upper limits for those infants with no hearing loss) are approximately 50

and 40 dB HL for 500 and 2000 Hz AC, and approximately 20-30 and 40 dB HL for BC stimuli.

The present study showed minimum intensities of 40 and 40 dB HL for 500 & 2000 Hz AC and

30 & 40 dB HL for 500 & 2000 Hz BC. The AC values differ by not more than 10 dB from the

average of the other studies using different stimuli (note variations across studies in the

modulation function, or use of one versus multiple simultaneous ASSR stimuli). These

differences may be attributed to differences in sample size, stimuli, whether presentation was

multiple or single, the age range tested, stopping criteria, EEG noise, recording system (and the

system's detection algorithm). The BC minimum intensity at 500 Hz proposed in Small &

Stapells (2008b) of 30 dB HL is consistent with what was found in the present study. The

minimum intensity from this study was slightly higher than 20 dB HL reported by Casey &

Small (2014), however, was likely somewhat overestimated (~5 dB) due to the distribution of the

threshold data and the step size used. The present study and that by Casey & Small (2014) are the

only studies to date that used AM^2 stimuli for BC ASSR, and both studies showed better than the

average of thresholds included in the table. However, ASSR amplitudes are in keeping with these

studies and a study using AM/FM stimuli (Small & Stapells, 2008a). The mechanisms

underlying this difference in thresholds remains an open question. In addition, maturation of the

BC ASSR response makes "cutoff" points less clear for categorizing hearing loss and the use of

an age range of 0-6 months may be too large. Minimum intensities for ABR were in keeping

with those suggested by BCEHP. Importantly, they were not found to be smaller. As mentioned

earlier, t-tests comparing NH participants' AC and BC ABR or ASSR thresholds at 500 and 2000

Hz between those with normal and those with abnormal OAE screening results showed no

significant difference; thus, the NH group includes all NH thresholds, regardless of screening

result. Minimum normal intensities for ABR also did not differ between those in the NH group

with a normal vs. abnormal OAE screen; both subgroups had minimum normal intensities of 30

for 2000 Hz AC and BC and 35 and 20 for 500 Hz AC and BC, respectively.

<INSERT TABLE 5>

<INSERT TABLE 6>

Sensitivity and Specificity for Conductive Hearing Loss Detection

As discussed earlier, 500 Hz AC ASSR thresholds are, on average, higher than BC ASSR

thresholds in the CHL group, with a significantly larger ABG compared to the NH group (see

Tables 2 and 3). In the case of mild CHL, however, the ABR does seem better at identifying

modest ABGs in infants than the ASSR, using the parameters incorporated in this study. For this

reason, clinicians should exercise caution when considering using ASSR AC/BC thresholds to

identify mild CHL with small ABGs. Cutoff thresholds where the ASSR ABG demonstrated

high sensitivity lacked high specificity (See Table 4). The sample for the current study did not

include infants with sensorineural hearing loss, and therefore it was not possible to determine the

number of false negatives for BC ASSR. There was significant overlap in the NH and CHL AC

ASSR threshold distributions (and hence the imperfect sensitivity and specificity). We

hypothesize that this overlap may be a reflection of the sampling between groups. Overall, the

CHL group only demonstrated a very mild degree of hearing loss that was isolated to 500 Hz

(and perhaps in some cases may have been resolving). The NH sample recruited was primarily

"at risk" infants who failed or missed their initial hearing screening, and thus some subclinical

degree of middle ear dysfunction may have been present. Perhaps if the CHL group

demonstrated elevated AC thresholds across frequencies or the degree of loss was greater, and

the NH group had instead been recruited from low-risk infants with confirmed normal middle-

ear function, the overlap would have been minimized. Nevertheless, the present study operated

under conditions that are typical in the clinical setting where the separation between these groups

may be less than ideal.

20   **Clinical Implications**

Previous studies that compared ASSR thresholds to gold-standard methods of infant

hearing assessment reported strong correlations between the methods and reasonable accuracy in

estimating hearing thresholds. Some studies have suggested that the ASSR can accurately

separate NH infants from those with hearing loss. Differing methodology in this body of research

continues to be problematic. This study is one of only a small number of studies comparing the

ASSR to tone-ABR in infants with NH and with hearing loss, and within these, methodologies

and stimulus choices differ. More work still needs to be done to determine the best methodology

and stimulus parameters for ASSR testing in infants. This study added to the body of research by

providing data using AC and BC ASSR to AM^2 tones at 500 Hz in infants with NH or

conductive hearing loss, but it would be beneficial to provide more data with different degrees of

hearing loss and hearing loss at different frequencies. It is our opinion that the ASSR requires

more research to better understand optimal test parameters for use as a screening or diagnostic

measure for EHDI programs before being clinically implemented. When compared to the ABR

and screening measures, ASSR thresholds underperform in their ability to detect *mild* low

frequency CHL. The ABR is widely used, with well-studied diagnostic criteria and protocols and

it is known that the ABR is accurate in differentiating normal hearing sensitivity from a variety

of degrees of CHL, mixed and sensorineural hearing loss in infants. At this time, the ABR

continues to be the gold standard and is the diagnostic test method that clinicians should continue

to use in their EHDI Programs.

Limitations and Future Directions

The study was conducted in the context of a clinical audiology department in Canada,

where it is routine to have one individual making response judgements. This context was perhaps

a limitation of the study. It should be noted that the same individual made threshold estimations

for AC and BC ASSRs and ABRs, and hence any subjective bias across response measures

should have been similar for all measures, and hence it is unlikely the choice of a single expert

judge of response presence is a confounding factor in this study.

The moderate number of infants included in this study demonstrated a mild degree of

CHL that was only observed at 500 Hz. The conclusions regarding the efficacy of the ASSR in

detecting CHL could differ in a sample with more significant degrees of CHL, hearing loss that

extends beyond 500 Hz, and in cases of more extensive middle ear dysfunction (e.g., congenital

aural atresia, congenital fixation of the ossicular chain, acute otitis media). The results of the

present study suggesting that the ASSR may not be as good an indicator of ABG and CHL (or

middle ear abnormality) as the ABR may be limited to ASSR protocols using multitone AM^2

stimuli, and only for infants with what appears to be a rather mild conductive loss. Further

studies with more participants and degrees of CHL may help to provide a larger picture of the

efficacy of the ASSR in detection CHL in infants. Of note, acoustic reflexes were not measured

in the initial assessment of infants in either NH or CHL groups. In future studies with a wider

range of hearing loss degrees, the addition of acoustic reflexes may be beneficial to include to

more completely assess in middle ear status. Acoustic reflexes can be problematic, however, in

that they may wake the infant and thus are a lower priority measure in most Canadian ABR

protocols.

Monotic multiple (MM) ASSR stimuli (500, 1000, 2000, 4000 Hz) were presented;

however, due to time constraints only 2000 and 500 Hz were able to be measured down to true

threshold and compared with ABR thresholds in this study. The assumption is that if this were to

be used clinically as the only electrophysiologic measure of hearing, the clinician would ideally

assess threshold to all four stimuli to provide a more complete threshold assessment. In previous

studies, it has been demonstrated in human subjects that the use of multiple SAM stimuli is more

efficient than a single SAM stimulus (Hatton & Stapells, 2011) and the present study aimed to

investigate a possible alternative to the ABR using a technique that more time efficient than the

single-frequency technique that is used in diagnostic ABR assessments. In this particular

instance, focusing on two frequencies of interest (500 Hz, 2000 Hz) stimuli, while presenting

four AM[2] stimuli may have added some noise to the recordings, and perhaps modestly elevated

ASSR thresholds, but the authors are not aware of any published evidence that MM results in

higher thresholds than MS in human subjects. It should be noted that 4 SAM[2] stimuli were used

for both AC and BC ASSR stimuli, and hence would not have expected this to substantially

influence the magnitude of the ABG. Future studies aimed to provide clinical evidence of

threshold changes resulting from the use of multiple ASSR stimuli would directly address this

possibility.

This study aimed to answer a research question while providing some clinically relevant

information. As such the test protocol was inefficient and if adopted in a routine clinical setting,

would almost certainly have resulted in limited or inadequate information being acquired before

the infant wakes. The key procedural elements that would need to be changed in the clinical

setting include the test strategy of testing down to true threshold for all infants (clearly

unnecessary once it is known that their hearing is 'Normal'), as well as the use of both the ABR

and ASSR as electrophysiological techniques to assess hearing in the same test session (not ever

required clinically). The BCEHP protocol for clinical use recommends testing down to a

minimum intensity rather than testing down to true threshold in infants with NH Hatton et al.,

2022). In addition, BCEHP does not include the measurement of ASSR thresholds in their

clinical protocol; ASSR measures were made solely for the purposes of this study. Using only

one electrophysiologic measure of hearing thresholds would significantly reduce test time and

would allow for frequency-specific assessment of both ears in a time period that is more

reasonable in a clinical setting. An important additional procedural consideration is that ABR

testing was the priority for the clinical portion of the assessment, always taking place first. This

may have had an impact on the noise of the later-recorded ASSR recordings. It is also

worthwhile to explore test time and protocol efficiency of ASSR where there is a consideration

for implementation in a clinical setting that is unique to the stimulus and recording parameters

and protocols intended to be used (e.g., Cebulla & Stürzebecher, 2015; Sininger et al., 2018,

2020). The difference in starting levels (5-dB offset) between ABR and ASSR may have

influenced the differences in ABG size between the two methods. Once correction factors for

ASSR are confidently established, a different starting level for ASSR may be more appropriate.

Finally, due to the properties of the underdeveloped skull, the threshold for BC stimuli at

500 Hz is lower (better) in infants than in adults (e.g., Cone-Wesson & Ramirez, 1997; Small &

Stapells, 2008a). A logical next step is to measure ABG differences in infants after applying

infant-specific correction factors. This study reported ABR and ASSR threshold without the use

of any correction factors as these are not yet available for the ASSR (especially for BC stimuli).

Future research to establish ASSR eHL correction factors may assist in the clinical application of

ASSR thresholds, and act as a spring board for future research involving ASSR ABG in infants

with CHL.

Conclusion

EHDI Programs aim to identify hearing loss early in young infants, with many including mild

hearing loss in their target population. Compared to the ABR, the variability of ASSR thresholds

and ABG size was too great to reliably separate normal hearing from mild conductive hearing

loss , at least,using the parameters outlined. Sensitivity and specificity for identifying conductive

loss was highest for AC ABR threshold measurement compared to screening and ASSR

threshold measurements. More research is needed using infants with varying degrees of

conductive hearing loss at multiple frequencies to fully assess the appropriateness of the ASSR

as a clinical diagnostic tool for an infant population.

References

Aimoni, C., Crema, L., Savini, S., Negossi, L., Rosignoli, M., Sacchetto, L., Bianchini, C., &

    Ciorba, A. (2018). Hearing threshold estimation by auditory steady state responses (ASSR)

    in children. *Acta Otorhinolaryngologica Italica*, *38*(4), 361–368.

    https://doi.org/10.14639/0392-100X-1463

ANSI. (1996). American standard specifications for audiometers (ANSI S3.6-1996). *New York*.

Bagatto, M. (2020). Protocol for auditory brainstem response-based audiological assessment

    (ABRA). *Ontario Infant Hearing Program*.

    https://www.uwo.ca/nca/pdfs/clinical_protocols/2018.02 ABRA Protocol_Oct 2020.pdf

Casey, K.-A., & Small, S. A. (2014). Comparisons of auditory steady state response and

    behavioural air conduction and bone conduction thresholds for infants and adults with

    normal hearing. *Ear and Hearing, 35*(4), 423-439.

    https://doi.org/10.1097/AUD.0000000000000021

Cebulla, M., & Stürzebecher, E. (2015). Automated auditory response detection: Further

    improvement of the statistical test strategy by using progressive test steps of iteration.

    International Journal of Audiology, *54*(8), 568–572.

    https://doi.org/10.3109/14992027.2015.1017659

Cone-Wesson, B., Parker, J., Swiderski, N., & Rickards, F. (2002). The auditory steady-state

    response: Full-term and premature neonates. *Journal of the American Academy of*

    Audiology, 13(5), 260–269.

    https://doi.org/10.1055/s-0040-1715969

Cone-Wesson, B., & Ramirez, G. M. (1997). Hearing sensitivity in newborns estimated from

ABRs to bone-conducted sounds. *Journal of the American Academy of Audiology*, *8*(5),

299–307.

Hall, J. W. (2016). Crosscheck principle in pediatric audiology today: A 40-year perspective.

Journal of Audiology and Otology, *20*(2), 59–67. https://doi.org/10.7874/jao.2016.20.2.59

Hatton, J.L., Van Maanen, A., & Stapells, D. R. (2022). *British Columbia Early Earing*

Program: auditory brainstem response (ABR) protocol. http://www.phsa.ca/bc-early-

hearing/Documents/ABR_Protocol.pdf

Hatton, J. L., Janssen, R. M., & Stapells, D. R. (2012). Auditory brainstem responses to bone-

conducted brief tones in young children with conductive or sensorineural hearing loss.

International Journal of Otolaryngology, *2012*. https://doi.org/10.1155/2012/284864

Hatton, J. L., Rowlandson, J., Beers, A., & Small, S.A. (2019). Telehealth-enabled auditory

brainstem response testing for infants living in rural communities: the British Columbia

Early Hearing Program experience. *International Journal of Audiology*, *58*(7), 381–392.

https://doi.org/10.1080/14992027.2019.1584681

Hatton, J. L., & Stapells, D. R. (2011). The efficiency of the single- versus multiple-stimulus

auditory steady state responses in infants. *Ear and Hearing, 32*(3), 349–357.

https://doi.org/10.1097/AUD.0b013e3181ff352c

Janssen, R. M., Usher, L., & Stapells, D. R. (2010). The British Columbia's Children's Hospital

tone-evoked auditory brainstem response protocol: How long do infants sleep and how

much information can be obtained in one appointment? *Ear and Hearing*, *31*(5), 722–724.

https://doi.org/10.1097/AUD.0b013e3181ddf5c0

JCIH. (2019). Year 2019 position statement: Principles and guidelines for early hearing detection

and intervention programs. *The Journal of Early Hearing Detection and Intervention*, *4*(2),

1–44.

Jerger, J. (1970). Clinical experience with impedance audiometry. *Archives of Otolaryngology*,

92, 311–324.

John, M. S., Brown, D. K., Muir, P. J., & Picton, T. W. (2004). Recording auditory steady-state

responses in young infants. *Ear and Hearing, 25*(6), 539–553.

https://doi.org/10.1097/01.AUD.0000148050.80749.AC

John, M. S., & Picton, T. W. (2000). Human auditory steady-state responses to amplitude-

modulated tones: Phase and latency measurements. *Hearing Research*, *141*(1–2), 57–79.

https://doi.org/10.1016/S0378-5955(99)00209-9

Lins, O. G., Picton, T. W., Boucher, B. L., Durieux-Smith, A., Champagne, S. C., Moran, L. M.,

Perez-Abalo, M. C., Martin, V., & Savio, G. (1996). Frequency-specific audiometry using

steady-state responses. *Ear and Hearing*, *17*(2), 81–96. https://doi.org/10.1097/00003446-

199604000-00001

Luts, H., Desloovere, C., & Wouters, J. (2006). Clinical application of dichotic multiple-stimulus

auditory steady-state responses in high-risk newborns and young children. *Audiology &*

Neurotology, 11(1), 24–37. https://doi.org/10.1159/000088852

Michel, F., & Jørgensen, K. F. (2017). Comparison of threshold estimation in infants with

hearing loss or normal hearing using auditory steady-state response evoked by narrow band

CE-chirps and auditory brainstem response evoked by tone pips. *International Journal of*

Audiology, 56(2), 99–105. https://doi.org/10.1080/14992027.2016.1234719

Nagashima, H., Udaka, J., Chida, I., Shimada, A., Kondo, E., & Takeda, N. (2013). Air-bone gap

estimated with multiple auditory steady-state response in young children with otitis media

with effusion. *Auris Nasus Larynx*, *40*(6), 534–538.

https://doi.org/10.1016/j.anl.2013.03.002

Rance, G., & Rickards, F. (2002). Prediction of hearing threshold in infants using auditory

steady-state evoked potentials. *Journal of the American Academy of Audiology*, *13*(5)*,* 236–

245). https://doi.org/10.1055/s-0040-1715967

Rance, G., Roper, R., Symons, L., Moody, L.-J., Poulis, C., Dourlay, M., & Kelly, T. (2005).

Hearing threshold estimation in infants using auditory steady-state responses. *Journal of the*

American Academy of Audiology, 16(5), 291–300. https://doi.org/10.3766/jaaa.16.5.4

Rance, G., Tomlin, D., & Rickards, F. W. (2006). Comparison of auditory steady-state responses

and tone-burst auditory brainstem responses in normal babies. *Ear and Hearing*, *27*(6),

751–762. https://doi.org/10.1097/01.aud.0000240491.68218.ed

Rodrigues, G. R. I., & Lewis, D. R. (2014). Establishing auditory steady-state response

thresholds to narrow band CE-chirps® in full-term neonates. *International Journal of*

Pediatric Otorhinolaryngology, *78*(2), 238–243.

https://doi.org/10.1016/j.ijporl.2013.11.012

Rodrigues, G. R. I., Lewis, D. R., & Fichino, S. N. (2010). Steady-state auditory evoked

responses in audiological diagnosis in children: A comparison with brainstem evoked

auditory responses. *Brazilian Journal of Otorhinolaryngology*, *76*(1), 96–101.

https://doi.org/10.1590/s1808-86942010000100016

Sininger, Y. S., Hunter, L. L., Hayes, D., Roush, P. A., & Uhler, K. M. (2018). Evaluation of

speed and accuracy of next-generation auditory steady state response and auditory

brainstem response audiometry in children with normal hearing and hearing loss. *Ear and*

Hearing, 39(6)*,* 1207–1223. https://doi.org/10.1097/AUD.0000000000000580

Sininger, Y. S., Hunter, L. L., Roush, P. A., Windmill, S., Hayes, D., & Uhler, K. M. (2020).

    Protocol for rapid, accurate, electrophysiologic, auditory assessment of infants and toddlers.

    Journal of the American Academy of Audiology, 31(6)*,* 455–468.

    https://doi.org/10.3766/jaaa.19046

Small, S. A., Hatton, J. L., & Stapells, D. R. (2007). Effects of bone oscillator coupling method,

    placement location, and occlusion on bone-conduction auditory steady-state responses in

    infants. *Ear and Hearing, 28*(1)*,* 83–98.

    https://doi.org/10.1097/01.aud.0000249787.97957.5b

Small, S. A., & Stapells, D. R. (2008a). Maturation of bone conduction multiple auditory steady-

    state responses. *International Journal of Audiology*, *47*(8), 476–488.

    https://doi.org/10.1080/14992020802055284

Small, S. A., & Stapells, D. R. (2008b). Normal ipsilateral/contralateral asymmetries in infant

    multiple auditory steady-state responses to air- and bone-conduction stimuli. *Ear and*

    Hearing, 29(2)*,* 185–198. https://doi.org/10.1097/01.aud.0000305157.83012.f4

Stapells, D.R., & Small, S. A. (2017). Threshold assessment in infants using the frequency-

    specific auditory brainstem response and auditory steady-state response. In Tharpe, A.M., &

    Seewald, R.C. (Eds.), *Comprehensive Handbook of Pediatric Audiology.* (Second Edition*),*

    505–550. Plural Publishing, Inc.

Stapells, D. R., & Ruben, R. J. (1989). Auditory brain stem responses to bone-conducted tones in

    infants. *Annals of Otology, Rhinology & Laryngology*, *98*(12), 941–949.

    https://doi.org/10.1177/000348948909801205

Swanepoel, D. W., Ebrahim, S., Friedland, P., Swanepoel, A., & Pottas, L. (2008). Auditory

    steady-state responses to bone conduction stimuli in children with hearing loss.

International Journal of Pediatric Otorhinolaryngology, 72(12), 1861–1871.

https://doi.org/10.1016/j.ijporl.2008.09.017

Swanepoel, D. W., & Steyn, K. (2005). Short report: establishing normal hearing for infants with

the auditory steady-state response. *The South African Journal of Communication*

Disorders, *52*, 36–39.

Van Maanen, A., & Stapells, D. R. (2009). Normal multiple auditory steady-state response

thresholds to air-conducted stimuli in infants. *Journal of the American Academy of*

Audiology, 20(3), 196–207). https://doi.org/10.3766/jaaa.20.3.6

Van Maanen, A., & Stapells, D. R. (2010). Multiple-ASSR thresholds in infants and young

children with hearing loss. *Journal of the American Academy of Audiology, 21*(8), 535–

545). https://doi.org/10.3766/jaaa.21.8.5

Yang, E. Y., Rupert, A. L., & Moushegian, G. (1987). A developmental study of bone

conduction auditory brain stem response in infants. *Ear and Hearing, 8*(4), 244–251.

https://doi.org/10.1097/00003446-198708000-00009

Yang, E. Y., Stuart, A., Stenstrom, R., & Green, W. B. (1993). Test-retest variability of the

auditory brainstem response to bone-conducted clicks in newborn infants. *International*

Journal of Audiology, *32*(2), 89–94. https://doi.org/10.3109/00206099309071859

Yang, E. Y., Stuart, A., Stenstrom, R., & Hollett, S. (1991). Effect of vibrator to head coupling

force on the auditory brain stem response to bone conducted clicks in newborn infants. *Ear*

and Hearing, *12*(1), 55–60. https://doi.org/10.1097/00003446-199102000-00007

Figure 1. *Auditory brainstem response (ABR) air-bone gaps (ABG) in normal hearing (NH) and conductive hearing loss (CHL) groups.*

SD = Standard Deviation.

Figure 2. *Auditory steady-state response (ASSR) air-bone gaps (ABG) in normal hearing (NH) and conductive hearing loss (CHL) groups.*

SD = Standard Deviation.

Table 1

Sensitivity and Specificity Calculation Method

	CHL on ABR	NH on ABR
CHL on ASSR	A = True positive	B = False positive
NH on ASSR	C = False negative	D = True negative

Note. Sensitivity = A/(A+C) x 100, Specificity = D/(D+B) x 100. ASSR = Auditory Steady-State Response, ABR = Auditory Brainstem Response, NH = Normal Hearing, CHL = Conductive Hearing Loss.

Table 2

AC and BC 2000 and 500 Hz ASSR and ABR mean thresholds for NH and CHL groups

		NH Group				CHL Group	
		2000 Hz		500 Hz		500 Hz	
		ASSR (dB HL)	ABR (dB nHL)	ASSR (dB HL)	ABR (dB nHL)	ASSR (dB HL)	ABR (dB nHL)
AC	Mean	20.47	17.72	29.52	25.43	36.67	48.33
	SD	12.03	9.22	9.20	7.05	11.12	4.88
	n	21	22	21	23	15	15
BC	Mean	21.00	15.00	17.39	10.41	15.33	12.00
	SD	13.96	10.12	9.63	7.50	12.63	7.93
	n	21	22	23	24	15	15

Note. AC = Air-Conduction, BC = Bone-Conduction, ASSR = Auditory Steady-State Response, ABR = Auditory Brainstem Response, NH = Normal Hearing, CHL = Conductive Hearing Loss, SD = Standard Deviation, n = number of participants.

Table 3

2000 and 500 Hz ASSR and ABR mean ABG size- for NH and CHL groups

| | NH Group | | | | CHL Group | |
| | 2000 Hz | | 500 Hz | | 500 Hz | |
	ASSR ABG (dB)	ABR ABG (dB)	ASSR ABG (dB)	ABR ABG (dB)	ASSR ABG (dB)	ABR ABG (dB)
Mean	-5.45	2.73	12.00	15.00	21.33	36.33
SD	18.45	12.41	10.56	9.26	13.56	6.40
n	22	22	16	22	15	15

Note. ASSR = Auditory Steady-State Response, ABR = Auditory Brainstem Response, ABG = Air-Bone Gap, NH = Normal Hearing, CHL = Conductive Hearing Loss, SD = Standard Deviation, n = number of participants.

Table 4

Sensitivity and Specificity of CHL detection compared to gold standard ABR by test type

	Test	Sensitivity	Specificity
Screening	Tymp + OAE	100*	44
	OAE only	100*	58
	Tymp only	100*	60
ASSR ABG size (dB)	≥ 10	93	15
	≥ 20	60	60
	≥ 30	40	95
	≥ 40	13	100
ABR ABG size (dB)	≥ 5	100	0
	≥ 15	100	36
	≥ 25	100	68
	≥ 35	87	95
	≥ 45	26	100
ASSR thresholds (dB HL)	AC ≥20	100	5
	AC ≥30	87	33
	AC ≥40	47	67
	AC ≥50	33	100

Note. *Sensitivity of 100% due to classification criteria for CHL that required "refer" results on both tympanometry and OAE screening. CHL = Conductive Hearing Loss, ABR = Auditory Brainstem Response, ASSR = Auditory Steady State Response, Tymp = Tympanometry, OAE = Otoacoustic Emissions, ABG = Air-Bone Gap, AC = Air-Conduction.

Table 5

A summary of 500 & 2000 Hz AC ASSR "normal levels" in young children in literature

	Modulation	Multiple (M) /Single (S)	Age	Norm Max (dB HL)	
				500 Hz	2000 Hz
Lins et al., (1996) [**]	AM	M	1-10 mos	48	38
Cone-Wesson, Parker, et al., (2002)	AM	S	<4 mos	>71	50
John, Brown et al., (2004)	MM, AM, AM^2	M	3-15 wks	>46	>50
Rance et al., (2005)	MM	S	1-3 mos	52	40
Swanepoel & Steyn (2005)	MM	M	3-8 wks	50	>50
Luts et al., (2006) [**]	MM	M	<3 mos	>44	42
Rance & Tomlin (2006)	MM	S	6 wks	50	
Van Maanen & Stapells (2009)	AM (cos^3 sinusoids*)	M	<6 mos	49	36
Casey & Small (2014)	AM^2	M	6.5-19 mos	30	
Rodrigues & Lewis (2014) [**]	NBchirps	M	2 days	59	31
Present Study	AM^2	M	0-6 mos		40

Note. *Cosine3-windowed sinusoids are nearly equivalent to AM^2 .** Thresholds were converted from dB SPL to dB HL using ANSI-1996 adjustment values. ***Levels provided are in dB HL, converted levels from NB chirp « nHL » using Haughton 2-cc coupler conversions. AC = Air-Conduction, ASSR = Auditory-Steady State Response, AM = Amplitude Modulation, MM = Mixed Modulation, NB = Narrowband, Mos = Months, Wks = Weeks.

Table 6

A summary of 500 & 2000 Hz BC ASSR "normal levels" in young children in literature

	Modulation	Multiple (M) /Single (S)	Age	Norm Max (dB HL)	
				500 Hz	2000 Hz
Small & Stapells (2008)	MM	M	0-11 mos	30	40
			12-24 mos	40	40
Small & Stapells (2008)	MM	M	2-11 mos	30	30
Casey & Small (2014)	AM^2	M	6.5-19 mos	30	40
Present Study	AM^2	M	0-6 mos	30	40

Note. BC = Bone-Conduction, ASSR = Auditory Steady-State Response, MM = Mixed Modulation, AM = Amplitude Modulation,

Mos = Months.